


FEATURES


- * Built-in bias resistors enable the configuration of an inverter circuit without connecting input resistors (see equivalent circuit).
- * Only the on/off conditions need to be set for operation, making device design easy.
- * The bias resistors consist of thin-film resistors with complete isolation to allow negative biasing of the input. They also have the advantage of almost completely eliminating parasitic effects.

●Equivalent circuit



PIN CONNECTIONS AND MARKING


DTC143XE



SOT-523

Abbreviated symbol: 43


DTC143XUA



SOT-323

Abbreviated symbol: 43


DTC143XKA



SOT-23-3L

Abbreviated symbol: 43


DTC143XCA



SOT-23

Abbreviated symbol: 43

DTC143XSA



TO-92S

Absolute maximum ratings (Ta=25°C)

Parameter	Symbol	Limits (DTC143X)					Unit
		E	UA	CA	KA	SA	
Supply voltage	V _{CC}	50					V
Input voltage	V _{IN}	-7~+20					V
Output current	I _O	100					mA
	I _{C(MAX)}	100					
Power dissipation	P _d	150	200			300	mW
Junction temperature	T _j	150					℃
Storage temperature	T _{stg}	-55~150					℃

Electrical characteristics (Ta=25°C)

Parameter	Symbol	Min.	Typ	Max.	Unit	Conditions
Input voltage	$V_{I(off)}$			0.3	V	$V_{CC}=5V, I_O=100\mu A$
	$V_{I(on)}$	2.5				$V_O=0.3V, I_O=20\text{ mA}$
Output voltage	$V_{O(on)}$		0.1	0.3	V	$I_O/I_I=10\text{mA}/0.5\text{mA}$
Input current	I_I			1.8	mA	$V_I=5V$
Output current	$I_{O(off)}$			0.5	μA	$V_{CC}=50V, V_I=0$
DC current gain	G_I	30				$V_O=5V, I_O=10\text{mA}$
Input resistance	R_I	3.29	4.7	6.11	K Ω	
Resistance ratio	R_2/R_1	1.7	2.1	2.6		
Transition frequency	f_T		250		MHz	$V_O=10V, I_O=5\text{mA}, f=100\text{MHz}$

Typical Characteristics




Fig.1 Input voltage vs. output current (ON characteristics)




Fig.2 Output current vs. input voltage (OFF characteristics)




Fig.3 DC current gain vs. output current




Fig.4 Output voltage vs. output current