

SPECIFICATION

L4003

Current Mode PWM Controller VERSION 1.0



- Lixe reserves the right to change this documentation without prior notice

GENERAL DESCRIPTION

L4003 consists of step-down switching regulator with PWM control. These devise include a reference voltage source, oscillation circuit, error amplifier, internal PMOS and etc.

L4003 provides low-ripple power, high efficiency, and excellent transient characteristics. The PWM control circuit is able to the duty ratio linearly form 0 up to 100%. This converter is build out soft start function that prevents overshoot and inrush current at startup. An over current protect function and short circuit protect function are built inside, and when OCP or SCP happens, the operation frequency will be reduced. The operating frequency is decided by outside resistance. An external compensation is easily to system stable.

With the addition of an internal P-channel Power MOS, a coil, capacitors, and a diode connected externally, these ICs can function as step-down switching regulators. They serve as ideal power supply units for portable devices when coupled with the SOP8-EP with exposed pad package, providing such outstanding features as low current consumption. Since this converter can accommodate an input voltage up to 40V, it is also suitable for the operation via an AC adapter.

FEATURES

- Input voltage : 4.2V to 40V
- Output voltage : 0.8V to 38V
- Duty ratio : 0% to 100% PWM control
- Oscillation frequency range is 50K 500KHz by outside resistance setting
- Current Limit, Short Circuit Protect (SCP) and Thermal Shutdown protection
- Built-in internal SW P-channel MOS.
- SOP8-EP Pb-Free package.

Block Diagram



PIN ASSIGNMENT

The package of L4003 is SOP8-EP; the pin assignment is given by:

		Name	Description
		EN	ON/OFF Shutdown OPEN ON / L OFF
	2 090	VSS	GND pin
		OCSET	Add an external resistor to set max output current.
	03	VCC	IC power supply pin
OCSET 3	6 FB	SW	Switch pin. Connect external inductor & diode here.
	5 377	FB	Feedback pin
		COMP	Compensation pin
SOP	3-EP	OSC	Frequency Set Pin. The pin connect a resistance to GND.

ORDER/MARKING INFORMATION



Absolute Maximum Ratings (at Ta=25°C)

Characteristics	Symbol	Rating	Unit
VCC Pin Voltage	V _{CC}	V_{SS} - 0.3 to V_{SS} + 42	V

2013-4

- Lixe

L4003 Shenzhen LIZE Electronic Technology Co., Ltd

Feedback Pin Voltage	V _{FB}	V _{SS} - 0.3 to 6	V
EN Pin Voltage	V _{EN/SS}	V _{SS} - 0.3 to 6	V
OSC Pin Voltage	Vosc	V _{SS} - 0.3 to 3	V
COMP Pin Voltage	V _{COMP}	V _{SS} - 0.3 to 6	V
OCSET Pin Voltage	V _{OCSET}	V_{SS} - 0.3 to V_{CC}	V
Switch Pin Voltage	V_{SW}	$V_{\rm SS}$ - 0.3 to $V_{\rm CC}$ + 0.3	V
Power Dissipation	PD	Internally limited	mW
Storage Temperature Range	T _{ST}	-65 to +150	°C
Operating Junction Temperature Range	T _{OJP}	-40 to +125	°C
Operating Supply Voltage	V _{OP}	4.2 to 40	V
Thermal Resistance from Junction to case	θ_{JC}	15	°C /W
Thermal Resistance from Junction to ambient	θ _{JA}	40	°C/W

Note: θ_{JA} is measured with the PCB copper area(need connect to Exposed Pad) of approximately 1.5 in²(Multi-layer).

Electrical Characteristics (Vcc = 12V, Ta=25°C, unless otherwise specified)

Characteristics	Symbol	Conditions	Min	Тур	Max	Units
Feedback Voltage	V _{FB}	V _{CC} = 10V~30V I _{OUT} = 0 to 2A Tj=-20℃~125℃	0.784	0.800	0.816	V
Quiescent Current	I _{CCQ}	V _{FB} =1.2V force driver off	-	3	6	mA
Feedback Bias Curren	I _{FB}	I _{OUT} =0.1A	-	0.1	0.5	uA
Shutdown Supply Current	I _{SD}	V _{EN/SS} =0V	-	150	300	uA
Switch Current	I _{SW}		3.5	-	-	А
Adjustable frequency range	Fosc		50	-	500	KHz
Short frequency	Fosc /Foscs	V _{CC} = 10V~30V		6		
EN Pin Shutdown Logic input threshold voltage	V _{ENL}		-	-	0.8	V
Internal MOSFET R _{DSON}	R _{DSON}	V _{CC} =12V, V _{FB} =0V	-	100	150	mΩ
Efficiency	EFFI	V _{CC} = 12V, V _{OUT} = 5V, I _{OUT} =2A	-	91	-	%
		V _{CC} = 30V, V _{OUT} = 5V, I _{OUT} =2A		86		

Application Circuit 1



- Yixe

Frequency	L1	R2	C4	C5		
50K—120K	68160uH	330	8.2n	6.8n		
120K—180K	47—68uH	330	4.7n	1.8n		
180K—250K	33—47uH	330	1.8n	1n		
250K—330K	22—33uH	330	1n	510p		
330K—410K	15—22uH	100	510p	510p		
410K—500K	10—15uH	100	330p	330p		

Compensation Table

Function Descriptions

ΕN

This pin can be supplied shutdown function. It is inside pull high function. For normal application, the pin must be connected a capacitor to ground. Allow the switching regulator circuit to be shutdown pulling this pin below a 0.8V threshold voltage; the shutdown supply current is approximately 150uA.

OSC

External frequency set pin. The pin connects a resistance (R3) to reduce system frequency. This converter's frequency can be set from 50K to 500KHz, Please refer the below table to set frequency.

R3	510K	220K	91K	47K	27K	20K
Frequenc	50KHz	100KHz	200KHz	300KHz	400KHz	500KHz

COMP

Compensation pin. For EL output capacitor application, the COMP pin connects R2 and C4 to ground for all condition;

OCSET

The current limit threshold is setting by the external resistor connecting from V_{CC} supply to

L4003 Shenzhen LIZE Electronic Technology Co., Ltd

OCSET. The internal 60uA sink current crossing the resistor sets the voltage at pin of OCSET. When the Vs voltage is less than the voltage at OCSET, an over-current condition is triggered.

Application Information

Setting the Output Voltage

Application circuit item shows the basic application circuit with adjustable output version. The external resistor sets the output voltage according to the following equation:

Table Tresistor select for output voltage setting					
V _{OUT}	R4	R5			
5V	1.3K	6.8K			
3.3V	1.5K	4.7K			
2.5V	2.2K	4.7K			
1.8V	2K	2.5K			
1.5V	2.2K	2.0K			
1.2V	2K	1K			

Table 1 Resistor select for output voltage setting

Inductor Selection

For most designs, the different frequency can be reducing the inductor value; The L4003 is suggested 15μ H to 160μ H for 50K to 500KHz frequencies. Please refer the below table to design.

L1 recommend value (V _{IN} =8~40V ,V _{OUT} =5V, I _{OUT} =3A)					
Frequency (Hz) 300KHz~500KHz 200K~300KHz 100K~200K 50K~10					
L1 Value (uH)	10uH ~ 22uH	22uH ~47uH	33uH ~68uH	68uH ~160uH	

Where is inductor Ripple Current. Large value inductors lower ripple current and small value inductors result in high ripple currents. Choose inductor ripple current approximately 20% of the maximum load current 3A, ΔI_L =0.6A. The DC current rating of the inductor should be at least equal to the maximum load current plus half the ripple current to prevent core saturation (3A+0.3A).

Input Capacitor Selection

This capacitor should be located close to the IC using short leads and the voltage rating should be approximately 1.5 times the maximum input voltage. The RMS current rating requirement for the input capacitor of a buck regulator is approximately 1/2 the DC load current. A low ESR input capacitor sized

L4003 Shenzhen LIZE Electronic Technology Co., Ltd

for maximum RMS current must be used. A 470µF low ESR capacitor for most applications is sufficient.

Output Capacitor Selection

The output capacitor is required to filter the output and provide regulator loop stability. The important capacitor parameters are; the 100 KHz Equivalent Series Resistance (ESR), the RMS ripples current rating, voltage rating, and capacitance value. For the output capacitor, the ESR value is the most important parameter. The ESR can be calculated from the following formula.

$V_{RIPPLE} = \Delta I_L \times ESR = 0.6A \times 80m\Omega = 48mV$

An aluminum electrolytic capacitor's ESR value is related to the capacitance and its voltage rating. In most case, higher voltage electrolytic capacitors have lower ESR values. Most of the time, capacitors with much higher voltage ratings may be needed to provide the low ESR values required for low output ripple voltage. It is recommended to replace this low ESR capacitor by using a 470 μ F low ESR values < 80m Ω .

Demoboard PCB layout



-Lixe

L4003 Shenzhen LIZE Electronic Technology Co., Ltd

Package Outlines SOP8-EP



2013-4