

SANYO Semiconductors DATA SHEET



Monolithic Linear IC LA42052 — Audio Output for TV application 5W × 2ch Power Amplifier

Overview

LA42052 is 5W 2-channel AF power amplifier intended for televisions.

Functions

- 5W \times 2 channels (V_{CC} = 18V, R_L = 8 Ω)
- Standby function
- Pop noise reduction function
- Ripple filter
- Thermal protection circuit

LA42000 series is power IC which made Pin compatible altogether in 5 to 15W. They consist of four kinds of power ICs (mono, stereo, mono with volume function, stereo with volume function. They realized PCB layout communalization of an audio power block of TV).

Model name	PO	Cha		
		Monaural	Stereo	volume
LA42051	5W	0		
LA42052	5W		0	
LA42351	5W	0		0
LA42352	5W		0	0
LA42071	7W	0		
LA42072	7W		0	
LA42152	15W		0	

Any and all SANYO Semiconductor Co.,Ltd. products described or contained herein are, with regard to "standard application", intended for the use as general electronics equipment (home appliances, AV equipment, communication device, office equipment, industrial equipment etc.). The products mentioned herein shall not be intended for use for any "special application" (medical equipment whose purpose is to sustain life, aerospace instrument, nuclear control device, burning appliances, transportation machine, traffic signal system, safety equipment etc.) that shall require extremely high level of reliability and can directly threaten human lives in case of failure or malfunction of the product or may cause harm to human bodies, nor shall they grant any guarantee thereof. If you should intend to use our products for applications outside the standard applications of our customer who is considering such use and/or outside the scope of our intended standard applications, please consult with us prior to the intended use. If there is no consultation or inquiry before the intended use, our customer shall be solely responsible for the use.

Specifications of any and all SANYO Semiconductor Co., Ltd. products described or contained herein stipulate the performance, characteristics, and functions of the described products in the independent state, and are not guarantees of the performance, characteristics, and functions of the described products as mounted in the customer's products or equipment. To verify symptoms and states that cannot be evaluated in an independent device, the customer should always evaluate and test devices mounted in the customer's products or equipment.

Specifications

Maximum Ratings at $Ta = 25^{\circ}C$

Parameter	Symbol	Conditions	Ratings	unit
Maximum supply voltage	V _{CC} max	No signal	24	V
Allowable power dissipation	Pd max	Infinitely heat sink	15	W
Maximum junction temperature	Tj max		150	°C
Thermal resistance	θјс		3	°C/W
Operating temperature	Topr		-25 to +75	°C
Storage temperature	Tstg		-40 to +150	°C

Operating Conditions at $Ta = 25^{\circ}C$

Parameter	Symbol	Conditions	Ratings	unit
Recommended supply voltage	V _{CC}		18	V
Recommended load resistance	RL		8	Ω
Allowable operating voltage range	V _{CC} op		5.5 to 22	V

Electrical Characteristics at Ta = 25°C, V_{CC} = 18V, R_L = 8 Ω , f = 1kHz, Rg=600 Ω

Parameter	Symbol	Conditions	Ratings			1.1
			min	typ	max	Unit
Standby current	ISTB	Amplifier off		1	10	μΑ
Quiescent current	Icco	Rg = 0	18	50	100	mA
Output power	PO	THD = 10%	4	5		W
Total harmonic distortion	THD	P _O = 1W		0.15	0.4	%
Voltage gain	VG	V _O = 0dBm	33	35	37	dB
Output noise voltage	V _{NO}	Rg = 0, BPF = 20Hz to 20kHz		0.05	0.25	mVrms
Ripple rejection	SVRR	$Rg = 0, f_R = 100Hz, V_{CC}R = 0dBm$	50	60		dB
Channel separation	CH Sep.	$Rg = 10k\Omega$, $V_O = 0dBm$	50	60		dB
Standby control voltage	V _{STB} -H	Amplifier on	1.0		5	V
(The Pin 5 voltage)	V _{STB} -L	Amplifier off	0		0.5	V
Input resistance	Ri		21	30	39	kΩ

Package Dimensions

unit : mm 3107B





Block Diagram



Application Circuit Example



External Components

C1, C2 : Input coupling capacitors, which are recommended to be $1.0\mu F$ or less.

The input pin voltage $2V_{BE}$ (about 1.4V).

Determine the polarity orientation of these capacitors based on the DC current from the circuit connected to the LA42052 front end.

- C3 : The recommended value for the Ripple filter capacitor is 100μ F.
- C4 : The recommended value for the P.P capacitor 4.7μ F. It is a capacitor for there being small Pop sound.
- C5 : Power supply capacitor.
- C6, C7 : The recommended value for the output capacitor is 470 $\mu F.$
- 1. Standby Function (Pin 5)

By means of controlling pin 5 to high and low, the power Supply can be set to ON and OFF.

Control Voltage of pin 5

Pin 5 voltage	Amplifier	Standby
0 to 0.5	OFF	ON
1.0 to 5.0	ON	OFF

When the impression voltage of VS is high, I want to stop 5 pin inflow current. Restriction resistance (RSTB) is inserted in a case.

 $VS = 5V, R_{STB} = 5.1k\Omega$ 5 pin inflow current = about 750µA 5 pin voltage = about 1.2V

2. Ripple filter and Mute function (Pin 1)

Pin voltage is approx. $1/2 V_{CC}$

The recommended value for the Ripple filter capacitor is $100\mu F$. Muting :

The output signal can be controlled by connecting pin 1(Ripple filter) to ground via a resistance of 300 to 500Ω . If resistance is higher than 750Ω , the suppression ratio will decrease.

3. Input Pin (Pin 2,4)

Voltage at the input pins is approx. $2V_{BE}(about 1.4V)$ Determine the polarity orientation of these capacitors based on the DC current from the circuit Connected to the LA42052 front end. Input resistance is approx. $30k\Omega$ (typ)

The recommended value for the input capacitor is $1.0 \mu F.$

4. P.P (Pin 6)

The Pin 6 is Terminal for there being small pop sound at the time of power supply ON/OFF. C4 recommends $4.7\mu F$. When capacitance is higher $10\mu F$, the sound will not be cut off when setting the power supply OFF.

Pin 6 voltage =
$$\frac{V_{CC} - V_{CE} (about 0.3V) - 5.6V}{2} + 5.6V$$





Usage Notes

- 1. Lightening (power supply output short-circuit) and ground fault (GND output short-circuit) protective circuits are not incorporated. Due care must be taken during handling of the product.
- 2. The thermal protective circuit is incorporated and activated when the junction temperature (Tj) rises above about 160°C.

This circuit controls the output gradually to the attenuated condition.

3. Always ensure the sufficient margin for the supply voltage, etc. to operate the product within the area where the maximum rating will never be exceeded. Namely, the maximum rating may be exceeded due to the slight change in conditions, resulting in damage, if the product is used around the maximum rating.

