

The RF MOSFET Line

RF Power Field Effect Transistor


N-Channel Enhancement-Mode Lateral MOSFET

MRF9210R3

Designed for broadband commercial and industrial applications with frequencies from 865 to 895 MHz. The high gain and broadband performance of this device make it ideal for large-signal, common source amplifier applications in 26 volt base station equipment.

- Typical CDMA Performance @ 880 MHz, 26 Volts, $I_{DQ} = 2 \times 950$ mA
IS-95 CDMA Pilot, Sync, Paging, Traffic Codes 8 Through 13
Output Power — 40 Watts
Power Gain — 16.5 dB
Efficiency — 25.5%
Adjacent Channel Power —
750 kHz: -46.2 dBc @ 30 kHz BW
1.98 MHz: -60 dBc @ 30 kHz BW
- Internally Matched, Controlled Q, for Ease of Use
- Integrated ESD Protection
- Designed for Maximum Gain and Insertion Phase Flatness
- Capable of Handling 10:1 VSWR, @ 26 Vdc, 880 MHz, 40 Watts Avg. N-CDMA
- Excellent Thermal Stability
- Characterized with Series Equivalent Large-Signal Impedance Parameters
- In Tape and Reel. R3 Suffix = 250 Units per 56 mm, 13 inch Reel.

**880 MHz, 200 W, 26 V
LATERAL N-CHANNEL
BROADBAND
RF POWER MOSFET**



**CASE 375G-04, STYLE 1
NI-860C3**

MAXIMUM RATINGS

Rating	Symbol	Value	Unit
Drain-Source Voltage	V_{DS}	65	Vdc
Gate-Source Voltage	V_{GS}	- 0.5, +15	Vdc
Total Device Dissipation @ $T_C = 25^\circ\text{C}$ Derate above 25°C	P_D	565 3.2	Watts W/ $^\circ\text{C}$
Storage Temperature Range	T_{stg}	- 65 to +150	$^\circ\text{C}$
Operating Junction Temperature	T_J	200	$^\circ\text{C}$

THERMAL CHARACTERISTICS

Characteristic	Symbol	Value (1)	Unit
Thermal Resistance, Junction to Case	$R_{\theta JC}$	0.31	$^\circ\text{C}/\text{W}$

ESD PROTECTION CHARACTERISTICS

Test Conditions	Class
Human Body Model	1 (Minimum)
Machine Model	M3 (Minimum)
Charge Device Model	C7 (Minimum)

(1) MTTF calculator available at <http://www.motorola.com/semiconductors/rf>. Select Tools/Software/Application Software/Calculators to access the MTTF calculators by product.

NOTE - CAUTION - MOS devices are susceptible to damage from electrostatic charge. Reasonable precautions in handling and packaging MOS devices should be observed.

ELECTRICAL CHARACTERISTICS (T_C = 25°C unless otherwise noted)


Characteristic	Symbol	Min	Typ	Max	Unit
OFF CHARACTERISTICS (1)					
Zero Gate Voltage Drain Leakage Current (V _{DS} = 65 Vdc, V _{GS} = 0)	I _{DSS}	—	—	10	μAdc
Zero Gate Voltage Drain Leakage Current (V _{DS} = 26 Vdc, V _{GS} = 0)	I _{DSS}	—	—	1	μAdc
Gate-Source Leakage Current (V _{GS} = 5 Vdc, V _{DS} = 0)	I _{GSS}	—	—	1	μAdc
ON CHARACTERISTICS (1)					
Gate Threshold Voltage (V _{DS} = 10 Vdc, I _D = 330 μAdc)	V _{GS(th)}	1.5	2.8	4	Vdc
Gate Quiescent Voltage (V _{DS} = 26 Vdc, I _D = 800 mAdc)	V _{GS(Q)}	2.5	3.3	4.5	Vdc
Drain-Source On-Voltage (V _{GS} = 10 Vdc, I _D = 2.2 Adc)	V _{DS(on)}	—	0.2	0.4	Vdc
Forward Transconductance (V _{DS} = 10 Vdc, I _D = 6.7 Adc)	g _{fs}	—	8.8	—	S
DYNAMIC CHARACTERISTICS (1)					
Reverse Transfer Capacitance (V _{DS} = 26 Vdc ± 30 mV(rms)ac @ 1 MHz, V _{GS} = 0 Vdc)	C _{rss}	—	3.6	—	pF
FUNCTIONAL TESTS (In Motorola Test Fixture, 50 ohm system) (2) Single-Carrier N-CDMA, 1.2288 MHz Channel Bandwidth Carrier, Peak/Avg. Ratio = 9.8 dB @ 0.01% Probability on CCDF					
N-CDMA Common-Source Amplifier Power Gain (V _{DD} = 26 Vdc, P _{out} = 40 W Avg. N-CDMA, I _{DQ} = 2 x 950 mA, f = 880 MHz)	G _{ps}	15.8	16.5	—	dB
N-CDMA Drain Efficiency (V _{DD} = 26 Vdc, P _{out} = 40 W Avg. N-CDMA, I _{DQ} = 2 x 950 mA, f = 880 MHz)	η	23	25.5	—	%
Adjacent Channel Power Ratio (V _{DD} = 26 Vdc, P _{out} = 40 W Avg. N-CDMA, I _{DQ} = 2 x 950 mA, f = 880 MHz; ACPR @ 40 W, 1.23 MHz Bandwidth, 750 kHz Channel Spacing)	ACPR	—	-46.2	-45	dBc
Input Return Loss (V _{DD} = 26 Vdc, P _{out} = 40 W Avg. N-CDMA, I _{DQ} = 2 x 950 mA, f = 880 MHz)	IRL	9	17.5	—	dB
N-CDMA Common-Source Amplifier Power Gain (V _{DD} = 26 Vdc, P _{out} = 40 W Avg. N-CDMA, I _{DQ} = 2 x 950 mA, f = 865 MHz and 895 MHz)	G _{ps}	—	16.5	—	dB
N-CDMA Drain Efficiency (V _{DD} = 26 Vdc, P _{out} = 40 W Avg. N-CDMA, I _{DQ} = 2 x 950 mA, f = 865 MHz and 895 MHz)	η	—	25.5	—	%
Adjacent Channel Power Ratio (V _{DD} = 26 Vdc, P _{out} = 40 W Avg. N-CDMA, I _{DQ} = 2 x 950 mA, f = 865 MHz and 895 MHz; ACPR @ 40 W, 1.23 MHz Bandwidth, 750 kHz Channel Spacing)	ACPR	—	-47.5	—	dBc
Input Return Loss (V _{DD} = 26 Vdc, P _{out} = 40 W Avg. N-CDMA, I _{DQ} = 2 x 950 mA, f = 865 MHz and 895 MHz)	IRL	—	15	—	dB
Output Mismatch Stress (V _{DD} = 26 Vdc, P _{out} = 40 W Avg. N-CDMA, I _{DQ} = 2 x 950 mA, f = 880 MHz, VSWR = 10:1, All Phase Angles at Frequency of Tests)	Ψ	No Degradation In Output Power			

- (1) Each side of device measured separately.
(2) Device measured in push-pull configuration.

Freescale Semiconductor, Inc.

Table 1. 880 MHz Test Circuit Component Designations and Values

Part	Description	Value, P/N or DWG	Manufacturer
B1, B2	11 Ω RF Beads, Surface Mount (0805)	2508051107Y0	Fair-Rite
Balun 1, Balun 2	0.8-1 GHz Xinger Balun	3A412	Anaren
C1	27 pF Chip Capacitor, B Case	100B270JP500X	ATC
C2	12 pF Chip Capacitor (0603)	06035J120GBT	AVX / Kyocera
C3, C4	3.3 pF Chip Capacitors (0603)	06035J3R3BBT	AVX / Kyocera
C5	9.1 pF Chip Capacitor, R Case	180R8R2JW500X	ATC
C6	4.3 pF Chip Capacitor, B Case	100B4R3CP500X	ATC
C7	0.4-2.5 pF Variable Capacitor	27283PC	Gigatronics
C8	12 pF Chip Capacitor, B Case	100B120JP500X	ATC
C9, C10	470 μ F, 63 V Electrolytic Capacitors	NACZF471M63V (18x22)	Nippon
C11, C12, C13, C14	22 μ F, 35 V Tantalum Chip Capacitors	T491X226K035AS	Kemet
C15, C17, C19, C21	0.01 μ F, 100 V Chip Capacitors	C1825C103J1GAC	Kemet
C16, C18	0.56 μ F, 50 V Chip Capacitors	C1825C564J5GAC	Kemet
C20, C22	2.2 μ F, 50 V Chip Capacitors	C1825C225J5RAC3810	Kemet
C23, C24	47 μ F, 16 V Tantalum Chip Capacitors	TPSD476K016R0150	AVX
L1	12 nH Inductor (0603)	0603HC-12NHJBU	Coilcraft
L2	22 nH Inductor	B07T-5	Coilcraft
L3, L4	12.5 nH Inductors	A04T-5	Coilcraft
L5, L6	10 nH Inductors (0603)	0603HC-10NHJBU	Coilcraft
PCB Gate	30 mil, $\epsilon_r = 2.56$	DS0928	DS Electronics
PCB Drain	30 mil, $\epsilon_r = 2.56$	DS0978	DS Electronics
R1, R2	24 Ω , 1/8 W Chip Resistors		Dale Vishay


Figure 1. 880 MHz Test Circuit Component Layout

Freescale Semiconductor, Inc.

TYPICAL CHARACTERISTICS




Figure 2. Class AB Broadband Circuit Performance




Figure 3. Power Gain versus Output Power




Figure 4. Intermodulation Distortion versus Output Power




Figure 5. Intermodulation Distortion Products versus Output Power




Figure 6. Power Gain and Efficiency versus Output Power

Freescale Semiconductor, Inc.

TYPICAL CHARACTERISTICS




Figure 7. Power Gain, Efficiency and IMD versus Output Power




Figure 8. N-CDMA Performance Output Power versus Gain, ACPR, Efficiency




Figure 9. Single-Carrier Maximum N-CDMA Linear Output Power versus Drain Voltage






Figure 10. Typical N-CDMA Spectrum



f MHz	Z _{source} Ω	Z _{load} Ω
865	4.19 - j6.71	8.43 - j3.83
880	3.69 - j6.18	8.12 - j3.85
895	3.17 - j5.85	7.84 - j4.08

Z_{load} = Test circuit impedance as measured from drain to drain, balanced configuration.




MRF9210R3

NOTES

Freescal Semiconductor, Inc.


PACKAGE DIMENSIONS



- NOTES:
1. CONTROLLING DIMENSION: INCH.
 2. INTERPRET DIMENSIONS AND TOLERANCES PER ASME Y14.5M-1994.
 3. DIMENSION H TO BE MEASURED 0.030 (0.762) AWAY FROM PACKAGE BODY.
 4. RECOMMENDED BOLT CENTER DIMENSION OF 1.140 (28.96) BASED ON 3M SCREW.

DIM	INCHES		MILLIMETERS	
	MIN	MAX	MIN	MAX
A	1.335	1.345	33.91	34.16
B	0.380	0.390	9.65	9.91
C	0.180	0.224	4.57	5.69
D	0.325	0.335	8.26	8.51
E	0.060	0.070	1.52	1.78
F	0.004	0.006	0.10	0.15
G	1.100	BSC	27.94	BSC
H	0.097	0.107	2.46	2.72
J	0.2125	BSC	5.397	BSC
K	0.135	0.165	3.43	4.19
L	0.425	BSC	10.8	BSC
M	0.852	0.868	21.64	22.05
N	0.851	0.869	21.62	22.07
Q	0.118	0.138	3.00	3.30
R	0.395	0.405	10.03	10.29
S	0.394	0.406	10.01	10.31
bbb	0.010	REF	0.25	REF
ccc	0.015	REF	0.38	REF

- STYLE 1:
- PIN 1. DRAIN
 - DRAIN
 - GATE
 - GATE
 - SOURCE



**CASE 375G-04
ISSUE E
NI-860C3**

Information in this document is provided solely to enable system and software implementers to use Motorola products. There are no express or implied copyright licenses granted hereunder to design or fabricate any integrated circuits or integrated circuits based on the information in this document.

Motorola reserves the right to make changes without further notice to any products herein. Motorola makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Motorola assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation consequential or incidental damages. "Typical" parameters that may be provided in Motorola data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals", must be validated for each customer application by customer's technical experts. Motorola does not convey any license under its patent rights nor the rights of others. Motorola products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the Motorola product could create a situation where personal injury or death may occur. Should Buyer purchase or use Motorola products for any such unintended or unauthorized application, Buyer shall indemnify and hold Motorola and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that Motorola was negligent regarding the design or manufacture of the part.

MOTOROLA and the Stylized M Logo are registered in the US Patent and Trademark Office. All other product or service names are the property of their respective owners. Motorola, Inc. is an Equal Opportunity/Affirmative Action Employer.

© Motorola Inc. 2004

HOW TO REACH US:

USA/EUROPE/LOCATIONS NOT LISTED:
Motorola Literature Distribution
P.O. Box 5405, Denver, Colorado 80217
1-800-521-6274 or 480-768-2130

JAPAN: Motorola Japan Ltd.; SPS, Technical Information Center,
3-20-1, Minami-Azabu, Minato-ku, Tokyo 106-8573, Japan
81-3-3440-3569

ASIA/PACIFIC: Motorola Semiconductors H.K. Ltd.; Silicon Harbour Centre,
2 Dai King Street, Tai Po Industrial Estate, Tai Po, N.T., Hong Kong
852-2668334

HOME PAGE: <http://motorola.com/semiconductors>



MOTOROLA

**For More Information On This Product,
Go to: www.freescale.com**

MRF9210/D