YX605

华晶电子 手机: 180 0250 8857, QQ:166 257 1973

LOW INPUT HIGH EFFICIENCY SYNCHRONOUS STEP-UP CONVERTER

V1.0

FEATURES

- Up to 0.9V Startup Voltage
- Up to 94% Efficiency
- Internal Power Switch
- 3.3V and 5V Fixed or Adjustable Output Voltage
- Zero Supply Current Shutdown Mode
- Tiny SOT 23-5 Package

APPLICATIONS

- Hand-Held Devices
- One to Three Cell Battery Operated Devices
- PDAs
- Cellular Phones
- Digital Cameras
- GPS

GENERAL DESCRIPTION

The YX605 Low Input High Efficiency Synchronous Step-Up Converter is capable of delivering more than 400mA output current using only three external components.

Typical startup voltage is 0.95V and the device can operate down to a 0.6V input voltage. Incorporating an internal synchronous rectifier, the YX6 0.5 can achieve high efficiency of up to 94%. Variable switching frequency operation results in high efficiency for a wide range of loads.

The output voltage is selectable between 3.3V and 5V, or can be externally set to any voltage between 2V and 5V. The YX605 is available in the tiny SOT23-5 Package.



Efficiency vs. Output Current

Figure 1. Typical Application Circuit



YX605

ORDERING INFORMATION

| PART NUMBER | TEMPERATURE RANGE | PACKAGE | PINS | TOP MARK |
|-------------|-------------------|---------|------|----------|
| YX605 | -40° C to 85° C | SOT23-5 | 5 | HBCA |

PIN CONFIGURATION



PIN DESCRIPTION

.

| PIN NUMBER | PIN NAME | PIN DESCRIPTION |
|------------|----------|---|
| 1 | FB | Output Voltage Selected and Feedback Input. Connect to G to select V_{OUT} = 3.3V. Connect to OUT to select V_{OUT} = 3.3V. Connect to a resistor divider to set output voltage between 2V and 5V. |
| 2 | G | Ground |
| 3 | SHDN | Shutdown Input. A low level puts IC in shutdown and a high level activates the IC. |
| 4 | LX | Inductor Connection |
| 5 | OUT | Output. This pin is always used as the supply rail for internal circuitry. |



LOW INPUT HIGH EFFICIENCY SYNCHRONOUS STEP-UP CONVERTER

V1.0

YX605

ABSOLUTE MAXIMUM RATINGS

(Note: Do not exceed these limits to prevent damage to the device. Exposure to absolute maximum rating conditions for long periods may affect device reliability.)

| PARAMETER | VALUE | UNIT |
|---|--------------------------------|------|
| OUT Supply Voltage | -0.3 to 6 | V |
| SHDN Voltage | -0.3 to 6 | V |
| FB, LX Voltage | -0.3 to V _{OUT} + 0.3 | V |
| Continuous LX Current | Internally Limited | А |
| Maximum Power Dissipation (derate 5mW/°C above T _A = 50°C) | 0.53 | W |
| Junction to Ambient Thermal Resistance (θ_{JA}) | 190 | °C/W |
| Operating Junction Temperature | -40 to 150 | °C |
| Storage Temperature | -55 to 150 | °C |
| Lead Temperature (Soldering, 10 sec) | 300 | °C |

ELECTRICAL CHARACTERISTICS

.

(Circuit of Figure 1, V_{IN} = 1.5V, V_{OUT} = 3.3V, T_A = 25°C unless otherwise specified.)

| PARAMETER | SYMBOL | TEST CONDITIONS | MIN | TYP | MAX | UNIT |
|--|---------------------|---|------|------|------|------|
| Minimum Operating Input Voltage | | | | 0.6 | | V |
| Startup Voltage | | | | 0.95 | 1.1 | V |
| | V | FB = OUT | 3.2 | 3.3 | 3.4 | V |
| Oulput voltage | VOUT | FB = G | 4.85 | 5 | 5.15 | V |
| Startup to Normal Transition Voltage Threshold | | | | 1.85 | | V |
| FB Feedback Voltage | V_{FB} | V_{OUT} = 2V to 5V | 1.16 | 1.18 | 1.2 | V |
| FB Input Current | | FB = 1.3V | | | 0.1 | μA |
| Power Switch Current Limit | I _{LIM} | | 1 | 1.2 | 1.4 | А |
| Power Switch On Resistance | R _{ONN} | I _{LX} = 100mA | | 0.15 | 0.3 | Ω |
| Synchronous Rectifier On Resistance | R _{ONP} | I _{LX} = 100mA | | 0.25 | 0.5 | |
| LX Leakage Current | | $\overline{\text{SHDN}}$ = G, V _{LX} = 0 or 3.3V | | 0.1 | 1 | μA |
| Output Voltage Range | | External Feedback divider | 2 | | 5 | V |
| Quiescent Current at OUT | lα | V _{FB} = 1.3V | | 17 | 34 | μA |
| Shutdown Supply Current | I _{SD} | SHDN = G | | 0.1 | 1 | μA |
| Maximum On Time | tONMAX | V_{OUT} = 2V to 5.5V | 1 | 50 | 5 | ns |
| Programming High Time | | | | | 75 | μs |
| Finish High Time | t _{FINISH} | | 500 | | | μs |
| Off Timeout | t _{OFF} | | | 300 | 500 | μs |
| Input Current | | | | | 1 | μA |

LOW INPUT HIGH EFFICIENCY SYNCHRONOUS STEP-UP CONVERTER

V1.0

X605



FUNCTIONAL DESCRIPTION

The YX605 comprises a reference, feedback select error comparator, control logic and timers, internal power MOSFETs and current comparators. The Functional Block Diagram is shown in Figure 2.

MAIN CONTROL LOOP

The YX 605 uses the maximum ON time/minimum OFF time step-up architecture. An error comparator monitors the FB voltage. When FB is below the reference voltage and the 1µs minimum OFF time is exceeded, the latch is set and an ON cycle is initiated. During this period, the N-channel power switch is turned on to connect the LX node to ground. By doing so, the energy is transferred from supply to the inductor. Once the 5µs maximum ON time is exceeded or the 1A current limit is reached, the N-channel power switch is turned off and the OFF cycle begins. During OFF cycle the energy stored in the inductor is released into the load through the synchronous rectifier. After the minimum OFF

APPLICATION INFORMATION

OUTPUT VOLTAGE SELECTION

By connecting FB differently, three options

time, if FB voltage drops below the reference voltage, the IC transitions to the ON cycle again.

LIGHT LOAD OPERATION

At light load, the IC enters power-saving mode by extending the OFF time, resulting in high efficiency across a wide load range.

START UP

The YX 605 uses a proprietary start-up scheme to ensure device start up at a very low supply voltage down to 0.95V. The device stays in the startup mode until V_{OUt} passes 1.85V. During this start-up period, the maximum ON and minimum OFF times are extended.

SHUTDOWN

In shutdown, all internal circuits are disabled. The power switch and the synchronous rectifier are turned off. A DC path from the input supply to the output still exists in shutdown due to the body diode of the synchronous rectifier when output is lower than input by one diode drop.

are available for output voltages: fixed 3.3V, 5V or an adjustable voltage set by an external resistive divider. (Figure 3).

| FB = OUT | V _{OUT} = 3.3V |
|-----------------------------------|------------------------------------|
| FB = G | V _{OUT} = 5V |
| FB connected to resistive divider | V _{out} = 1.18V (1+R1/R2) |



Figure 3.

OUTPUT CAPACITOR SELECTION

The output capacitor value should be in the range of 22μ F to 100μ . A minimum value of capacitance is required to maintain loop stability and normal operation of the IC. To obtain small output ripple, use a large capacitor with low ESR. Ceramic capacitors should be used for highest performance. If a tantalum capacitor is used, choose only low ESR types. For a non-

LOW INPUT HIGH EFFICIENCY SYNCHRONOUS STEP-UP CONVERTER

V1.0

X605

ceramic capacitors a smaller low ESR capacitor of about 1μ F can be used in parallel to filter high frequency noise.

INDUCTOR SELECTION

The inductor value determines its ripple current. For most applications with this device, the inductor value should be in the range of 10μ H to 47μ H. Smaller inductors provide faster load transient response while having a smaller physical size. But they also generate higher ripple current, which reduces the maximum output current available to the load. Inductors with low series resistance are recommended to obtain highest efficiency.

BOARD LAYOUT

To reduce noise and increase efficiency, the traces for high current paths should be large and an extended ground plane used.

In order to reduce electromagnetic radiation, the switching current paths should be as short as possible. In other words, the input and output capacitors should be very close to the IC.

If the external resistor divider is used, it should be very close to the FB and G pins and the high switching current paths.

TYPICAL PERFORMANCE CHARACTERISTICS





Efficiency vs. Load Current



Efficiency vs. Current Load







.

Startup Voltage vs. Output Current



TYPICAL PERFORMANCE CHARACTERISTICS CONT'D









.

Maximum On Time vs. Temperature



LOW INPUT HIGH EFFICIENCY SYNCHRONOUS STEP-UP CONVERTER

V1.0

YX605

TYPICAL PERFORMANCE CHARACTERISTICS CONT'D



V(LX) (2V/Div) Time: 5µs/Div

.





SOT23-5 PACKAGE OUTLINE AND DIMENSIONS







LOW INPUT HIGH EFFICIENCY

SYNCHRONOUS STEP-UP CONVERTER