

JUNCTION FIELD EFFECT TRANSISTOR 2SK4027

N-CHANNEL SILICON JUNCTION FIELD EFFECT TRANSISTOR FOR IMPEDANCE CONVERTER OF ECM

DESCRIPTION

The 2SK4027 is suitable for converter of ECM.


FEATURES

- High gain
 - $-1.0 \text{ dB (V}_{DD} = 2.0 \text{ V, C} = 5 \text{ pF, RL} = 2.2 \text{ k}\Omega)$
- · Low noise
 - $-115 \text{ dB (V}_{DD} = 2.0 \text{ V, C} = 5 \text{ pF, RL} = 2.2 \text{ k}\Omega)$

ORDERING INFORMATION

PART NUMBER	PACKAGE		
2SK4027	SC-59 (Straight)		


PACKAGE DRAWING (Unit: mm)



ABSOLUTE MAXIMUM RATINGS (TA = 25°C)

Drain to Source Voltage (Ves = −1.0 V)	VDSX	20	V
Gate to Drain Voltage	Vgdo	-20	V
Drain Current	ΙD	10	mA
Gate Current	lg	10	mA
Total Power Dissipation	Рт	200	mW
Junction Temperature	Tj	125	°C
Storage Temperature	Tstg	-55 to +125	°C

EQUIVALENT CIRCUIT



- 2: Drain
- 3: Gate

Caution Please take care of ESD (Electro Static Discharge) when you handle the device in this document.

The information in this document is subject to change without notice. Before using this document, please confirm that this is the latest version. Not all products and/or types are available in every country. Please check with an NEC Electronics sales representative for availability and additional information.


ELECTRICAL CHARACTERISTICS (TA = 25°C)

CHARACTERISTICS	SYMBOL	TEST CONDITIONS		TYP.	MAX.	UNIT
Zero Gate Voltage Drain Cut-off Current	IDSS	V _{DS} = 2.0 V, V _{GS} = 0 V	90	250	430	μΑ
Gate Cut-off Voltage	V _{GS(off)}	V _{DS} = 2.0 V, I _D = 1.0 μA		-0.37	-1.0	V
Forward Transfer Admittance	y fs1	V_{DS} = 2.0 V, I_{D} = 30 μ A, f = 1.0 kHz	320	470		μS
	y fs2	V _{DS} = 2.0 V, V _{GS} = 0 V, f = 1.0 kHz	800	1600		μS
Input Capacitance	Ciss	V _{DS} = 2.0 V, V _{GS} = 0 V, f = 1.0 MHz		4.0		pF
Voltage Gain	Gv	V_{DD} = 2.0 V, C = 5 pF, R _L = 2.2 k Ω ,		-1.0		dB
		V _{IN} = 10 mV, f = 1 kHz				
Noise Voltage	NV	V_{DD} = 2.0 V, C = 5 pF, R _L = 2.2 k Ω ,		-115		dB
		A-curve				


IDSS CLASSIFICATION

MARKING	DE	DF	DH	DJ
Ioss (μA)	90 to 180	150 to 240	210 to 350	320 to 430

GAIN TEST CIRCUIT




NOISE VOLTAGE TEST CIRCUIT




les - Gate to Source Current - µA

TYPICAL CHARACTERISTICS (TA = 25°C)


DERATING FACTOR OF POWER DISSIPATION




DRAIN CURRENT vs. DRAIN TO SOURCE VOLTAGE



GATE TO SOURCE CURRENT vs. GATE TO SOURCE VOLTAGE




DRAIN CURRENT vs.




V_{GS} - Gate to Source Voltage - V

INPUT CAPACITANCE vs. DRAIN TO SOURCE VOLTAGE




FORWARD TRANSFER ADMITTANCE AND GATE CUT-OFF VOLTAGE vs. ZERO GATE VOLTAGE DRAIN CURRENT




 ${\sf I}_{\sf DSS}$ - ${\sf Zero}$ Gate Voltage Drain Current - ${\it \mu}{\sf A}$

VOLTAGE GAIN vs. DRAIN CURRENT



NOISE VOLTAGE vs. DRAIN CURRENT



- The information in this document is current as of April, 2005. The information is subject to change
 without notice. For actual design-in, refer to the latest publications of NEC Electronics data sheets or
 data books, etc., for the most up-to-date specifications of NEC Electronics products. Not all
 products and/or types are available in every country. Please check with an NEC Electronics sales
 representative for availability and additional information.
- No part of this document may be copied or reproduced in any form or by any means without the prior written consent of NEC Electronics. NEC Electronics assumes no responsibility for any errors that may appear in this document.
- NEC Electronics does not assume any liability for infringement of patents, copyrights or other intellectual property rights of third parties by or arising from the use of NEC Electronics products listed in this document or any other liability arising from the use of such products. No license, express, implied or otherwise, is granted under any patents, copyrights or other intellectual property rights of NEC Electronics or others.
- Descriptions of circuits, software and other related information in this document are provided for illustrative
 purposes in semiconductor product operation and application examples. The incorporation of these
 circuits, software and information in the design of a customer's equipment shall be done under the full
 responsibility of the customer. NEC Electronics assumes no responsibility for any losses incurred by
 customers or third parties arising from the use of these circuits, software and information.
- While NEC Electronics endeavors to enhance the quality, reliability and safety of NEC Electronics products, customers agree and acknowledge that the possibility of defects thereof cannot be eliminated entirely. To minimize risks of damage to property or injury (including death) to persons arising from defects in NEC Electronics products, customers must incorporate sufficient safety measures in their design, such as redundancy, fire-containment and anti-failure features.
- NEC Electronics products are classified into the following three quality grades: "Standard", "Special" and
 "Specific".
 - The "Specific" quality grade applies only to NEC Electronics products developed based on a customer-designated "quality assurance program" for a specific application. The recommended applications of an NEC Electronics product depend on its quality grade, as indicated below. Customers must check the quality grade of each NEC Electronics product before using it in a particular application.
 - "Standard": Computers, office equipment, communications equipment, test and measurement equipment, audio and visual equipment, home electronic appliances, machine tools, personal electronic equipment and industrial robots.
 - "Special": Transportation equipment (automobiles, trains, ships, etc.), traffic control systems, anti-disaster systems, anti-crime systems, safety equipment and medical equipment (not specifically designed for life support).
 - "Specific": Aircraft, aerospace equipment, submersible repeaters, nuclear reactor control systems, life support systems and medical equipment for life support, etc.

The quality grade of NEC Electronics products is "Standard" unless otherwise expressly specified in NEC Electronics data sheets or data books, etc. If customers wish to use NEC Electronics products in applications not intended by NEC Electronics, they must contact an NEC Electronics sales representative in advance to determine NEC Electronics' willingness to support a given application.

(Note)

- (1) "NEC Electronics" as used in this statement means NEC Electronics Corporation and also includes its majority-owned subsidiaries.
- (2) "NEC Electronics products" means any product developed or manufactured by or for NEC Electronics (as defined above).