

BCX56 TRANSISTOR (NPN)**FEATURES**

Power dissipation

 P_{CM} : 0.5 W ($T_{amb}=25^{\circ}C$)

Collector current

 I_{CM} : 1 A

Collector-base voltage

 $V_{(BR)CBO}$: 100 V


Operating and storage junction temperature range

 T_J, T_{stg} : $-55^{\circ}C$ to $+150^{\circ}C$ **SOT-89**

1. BASE

2. COLLECTOR

3. EMITTER

**ELECTRICAL CHARACTERISTICS** ($T_{amb}=25^{\circ}C$ unless otherwise specified)

Parameter	Symbol	Test conditions	MIN	MAX	UNIT
Collector-base breakdown voltage	$V_{(BR)CBO}$	$I_C=100\mu A, I_E=0$	100		V
Collector-emitter breakdown voltage	$V_{(BR)CEO}$	$I_C=10mA, I_B=0$	80		V
Emitter-base breakdown voltage	$V_{(BR)EBO}$	$I_E=10\mu A, I_C=0$	5		V
Collector cut-off current	I_{CBO}	$V_{CB}=30V, I_E=0$		0.1	μA
Emitter cut-off current	I_{EBO}	$V_{EB}=5V, I_C=0$		0.1	μA
DC current gain BCX56 BCX56-10 BCX56-16	$h_{FE(1)}$	$V_{CE}=2V, I_C=150mA$	63 63 100	250 160 250	
	$h_{FE(2)}$	$V_{CE}=2V, I_C=5mA$	40		
	$h_{FE(3)}$	$V_{CE}=2V, I_C=500mA$	25		
Collector-emitter saturation voltage	$V_{CE(sat)}$	$I_C=500mA, I_B=50mA$		0.5	V
Base-emitter voltage	$V_{BE(ON)}$	$I_C=500mA, V_{CE}=2V$		1	V
Transition frequency	f_T	$V_{CE}=5V, I_C=1mA$ $f=100MHz$	130		MHz

DEVICE MARKING	BCX56=BH BCX56-10=BK BCX56-16=BL
-----------------------	----------------------------------