

#### **Product Search Data Sheet**

Note: This datasheet may be out of date. Please download the latest datasheet of BLE32SN120SN1# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=BLE32SN120SN1%23

"#" indicates a package specification code.

# BLE32SN120SN1#









# < List of part numbers with package codes >

BLE32SN120SN1B

BLE32SN120SN1K

BLE32SN120SN1L




## **Applications**

| Please be sure to read and comply with     |  |  |
|--|--|--|
| these "Precautions for use."               |  |  |
| Consumer equipment,Medical                 |  |  |
| equipment [GHTF A/B/C] except for          |  |  |
| implant & surgery & auto injector,         |  |  |
| Industrial equipment except for            |  |  |
| transportation & facility & energy         |  |  |
| equipment                                  |  |  |
| Please refer to Our Website and            |  |  |
| specifications, etc. for information about |  |  |
| the performance, functions, quality,       |  |  |
| management, and safety required for        |  |  |
| the above applications, and use            |  |  |
| Products after confirming the              |  |  |
| performance and reliability of the actual  |  |  |
| Product.                                   |  |  |
| Consumer equipment                         |  |  |
|  |  |  |



## Appearance & Shape







### Packaging Information

| Packaging | Specifications      | Standard Packing Quantity |
|-----------|---------------------|---------------------------|
| В         | Bulk(Bag)           | 1000                      |
| K         | 330mm Embossed Tape | 7000                      |
| L         | 180mm Embossed Tape | 1500                      |



### **Features**

- 1.Bead inductor BLE series is designed to function nearly as a resistor at noise frequencies, which greatly reduces the possibility of resonance and leaves signal wave forms undistorted.
- 2. The nickel barrier structure of the external electrodes provides excellent solder heat resistance.
- 3.BLE32SN series can be used in high current circuits due to its low DC resistance. It can match power lines to a maximum of 20ADC.

1 of 3

- 1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.
- 2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





# BLE32SN120SN1#

Note: This datasheet may be out of date.

Please download the latest datasheet of BLE32SN120SN1# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=BLE32SN120SN1%23

"#" indicates a package specification code.



# **Specifications**

| Shape                           | SMD            |
|---------------------------------|----------------|
| Size Code (in inch)             | 1210           |
| Length                          | 3.2mm          |
| Length Tolerance                | ±0.2mm         |
| Width                           | 2.5mm          |
| Width Tolerance                 | ±0.2mm         |
| Thickness                       | 2.0mm          |
| Thickness Tolerance             | ±0.2mm         |
| Operating Temperature<br>Range  | -55°C to 125°C |
| Mass(typ.)                      | 0.08g          |
| Number of Circuit               | 1              |
| Rated Current (at 85°C)         | 20A            |
| Rated Current (at 125°C)        | 20A            |
| DC Resistance(max.)             | 0.6mΩ          |
| Impedance (at 100MHz)           | 12Ω            |
| Impedance (at 100MHz) Tolerance | ±5Ω            |
| Size Code (in mm)               | 3225           |

2 of 3

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

 $2. This \ data{sheet has only typical specifications because there is no space for \ detailed \ specifications.}$ 

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



Manufacturing Co., Ltd.

Please download the latest datasheet of BLE32SN120SN1# from the official website of Murata

http://www.murata.com/en-us/products/productdetail?partno=BLE32SN120SN1%23


Note: This datasheet may be out of date.


"#" indicates a package specification code.

# BLE32SN120SN1#



### **Product Data**





Impedance-Frequency Characteristics

**Equivalent Circuit** 

3 of 3

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

