

# SPECIFICATION FOR APPROVAL

(	)	<b>Preliminary</b>	<b>Specification</b>
---	---	--------------------	----------------------

### (♦) Final Specification

Title		13	3.3" WXGA TFT I	LCD
BUYER			SUPPLIER	LG.Philips LCD Co., Ltd.

BUYER	
MODEL	

SUPPLIER	LG.Philips LCD Co., Ltd.
*MODEL	LP133WX1
Suffix	TLC1

<sup>\*</sup>When you obtain standard approval, please use the above model name without suffix

	APPROVED BY	SIGNATURE
-	/	
-	1	
_	/	

Please return 1 copy for your confirmation with your signature and comments.

APPROVED BY	SIGNATURE				
S. C. Yun / G.Manager  REVIEWED BY					
G. J. Han / Manager  PREPARED BY					
B. T. Jang / Engineer S. W. Kim / Engineer					
Products Engineering Dept.					

LG. Philips LCD Co., Ltd



# Contents

No	ITEM			
	COVER	1		
	CONTENTS	2		
	RECORD OF REVISIONS	3		
1	GENERAL DESCRIPTION	4		
2	ABSOLUTE MAXIMUM RATINGS	5		
3	ELECTRICAL SPECIFICATIONS			
3-1	ELECTRICAL CHARACTERISTICS	6		
3-2	INTERFACE CONNECTIONS	8		
3-3	SIGNAL TIMING SPECIFICATIONS	9		
3-4	SIGNAL TIMING WAVEFORMS	9		
3-5	COLOR INPUT DATA REFERNECE	10		
3-6	POWER SEQUENCE	11		
4	OPTICAL SPECIFICATIONS	12		
5	MECHANICAL CHARACTERISTICS	16		
6	RELIABILITY	20		
7	INTERNATIONAL STANDARDS			
7-1	SAFETY	21		
7-2	EMC	21		
8	PACKING			
8-1	DESIGNATION OF LOT MARK	22		
8-2	PACKING FORM	22		
9	PRECAUTIONS	23		
Α	APPENDIX A. Enhanced Extended Display Identification Data	25		



# **RECORD OF REVISIONS**

Revision No	Revision Date	Page	Description	EEDID Ver.
0.0	Mar. 05. 2007	-	Preliminary Specification	V0.0
1.0	Mar. 13. 2007	-	Final CAS	V0.0
1.1	Apr. 13. 2007	26	Final CAS (EDID is changed)	V0.1
				ļ
				ļ
				<b> </b>
				[
				·····
				·····
				ļ




### 1. General Description

The LP133WX1-TLC1 is a Color Active Matrix Liquid Crystal Display with an integral Cold Cathode Fluorescent Lamp (CCFL) backlight system. The matrix employs a-Si Thin Film Transistor as the active element. It is a transmissive type display operating in the normally white mode. This TFT-LCD has 13.3 inches diagonally measured active display area with WXGA resolution(800 vertical by 1280 horizontal pixel array). Each pixel is divided into Red, Green and Blue sub-pixels or dots which are arranged in vertical stripes. Gray scale or the brightness of the sub-pixel color is determined with a 6-bit gray scale signal for each dot, thus, presenting a palette of more than 262,144 colors.

The LP133WX1-TLC1 has been designed to apply the interface method that enables low power, high speed, low EMI.

The LP133WX1-TLC1 is intended to support applications where thin thickness, low power are critical factors and graphic displays are important. In combination with the vertical arrangement of the sub-pixels, the LP133WX1-TLB1 characteristics provide an excellent flat display for office automation products such as Notebook PC.



#### **General Features**

Active Screen Size	13.3 inches diagonal
Outline Dimension	299.0(H)[typ.] × 195.0(V)[typ.] × 5.5(D) mm [Max.]
Pixel Pitch	0.2235 mm × 0.2235 mm
Pixel Format	1280 horiz. By 800 vert. Pixels RGB strip arrangement
Color Depth	6-bit, 262,144 colors
Luminance, White	250 cd/m²[typ.], 5p average
Power Consumption	Total 4.6 Watt(Typ.) @ LCM circuit 0.8 Watt(Typ.), B/L input 3.8 Watt(Typ.)
Weight	350g [Typ.] , 360g [Max.]
Display Operating Mode	Transmissive mode, normally white
Surface Treatment	Anti-Reflection & Glare, hard coating 3H



### 2. Absolute Maximum Ratings


The following are maximum values which, if exceeded, may cause faulty operation or damage to the unit.

Table 1. ABSOLUTE MAXIMUM RATINGS

Parameter	Values		ues	Units	Notes	
Farameter	Symbol	Min Max		Offics		
Power Input Voltage	VCC	-0.3	4.0	Vdc	at 25 ± 5°C	
Operating Temperature	Тор	0	50	°C	1	
Storage Temperature	Нѕт	-20	60	°C	1	
Operating Ambient Humidity	Нор	10	90	%RH	1	
Storage Humidity	Hst	10	90	%RH	1	

Note: 1. Temperature and relative humidity range are shown in the figure below.

Wet bulb temperature should be 39°C Max, and no condensation of water.





### 3. Electrical Specifications

#### 3-1. Electrical Characteristics

The LP133WX1-TLC1 requires two power inputs. One is employed to power the LCD electronics and to drive the TFT array and liquid crystal. The second input which powers the CCFL, is typically generated by an inverter. The inverter is an external unit to the LCD.

**Table 2. ELECTRICAL CHARACTERISTICS** 

Developed	0	Values			I I a it	NI-4
Parameter	Symbol	Min	Тур	Max	Unit	Notes
MODULE :						
Power Supply Input Voltage	VCC	3.0	3.3	3.6	$V_{dc}$	
Power Supply Input Current	I <sub>cc</sub>	.[ <del>.</del>	245	275	mA	Mosaic
Power Consumption	Pc	-	0.8	0.9	Watts	1
Differential Impedance	Zm	90	100	110	Ohm	2
LAMP :						
Operating Voltage	V <sub>BL</sub>	605	640	855	V <sub>RMŞ</sub>	3
Operating Current	I <sub>BL</sub>	2.0	6.0	7.0	mA <sub>RMS</sub>	4
Power Consumption	P <sub>BL</sub>		3.8	4.2		5
Operating Frequency	f <sub>BL</sub>	45	60	80	kHz	6
Discharge Stabilization Time	Ts	-	-	3	Min	7
Life Time		15000			Hrs	8
Established Starting Voltage at 25 $^{\circ}\!$	Vs			1140 1370	$V_{RMS}$	9
INVERTER:						10
Burst-Mode Frequency	Fв	203	213	223	Hz	

#### Note)


- 1. The specified current and power consumption are under the Vcc = 3.3V,  $25^{\circ}C$ , fv = 60Hz condition whereas Mosaic pattern is displayed and fv is the frame frequency.
- 2. This impedance value is needed to proper display and measured form LVDS Tx to the mating connector.
- 3. The variance of the voltage is  $\pm$  10%.
- 4. The typical operating current is for the typical surface luminance  $(L_{WH})$  in optical characteristics.
- 5. The lamp power consumption shown above does not include loss of external inverter. The applied lamp current is a typical one.
- 6. The output of the inverter must have symmetrical (negative and positive) voltage waveform and symmetrical current waveform (Asymmetrical ratio is less than 10%) Please do not use the inverter which has asymmetrical voltage and asymmetrical current and spike wave.
  Lamp frequency may produce interface with horizontal synchronous frequency and as a result this may cause beat on the display. Therefore lamp frequency shall be as away possible from the horizontal synchronous frequency and from its harmonics in order to prevent interference.
- 7. Define the brightness of the lamp after being lighted for 5 minutes as 100%, Ts is the time required for the brightness of the center of the lamp to be not less than 95%.
- 8. The life time is determined as the time at which brightness of lamp is 50% compare to that of initial value at the typical lamp current.
- 9. The voltage above VS should be applied to the lamps for more than 1 second for start-up. Otherwise, the lamps may not be turned on. The used lamp current is the lamp typical current.



Note)

- 10. Requirements for a system inverter design, which is intended to have a better display performance, a better power efficiency and a more reliable lamp, are following.
  It shall help increase the lamp lifetime and reduce leakage current.
  - a. The Burst-Mode Frequency of Inverter may produce wavy noise on the display.

    The Frequency above FB should be applied to the Inverter for the better display performance.
  - b. The asymmetry rate of the inverter waveform should be less than 10%.
  - c. The distortion rate of the waveform should be within  $\sqrt{2 \pm 10\%}$ .
    - \* Inverter output waveform had better be more similar to ideal sine wave.



Do not attach a conducting tape to lamp connecting wire.
If the lamp wire attach to a conducting tape, TFT-LCD Module has a low luminance and the inverter has abnormal action. Because leakage current is occurred between lamp wire and conducting tape.



#### 3-2. Interface Connections

This LCD employs two interface connections, a 20 pin connector is used for the module electronics interface and the other connector is used for the integral backlight system.

The electronics interface connector is a model DF manufactured by LGC.

Table 3. MODULE CONNECTOR PIN CONFIGURATION (CN1)

Pin	Symbol	Description	Notes
1	GND	Ground	A laterface ships
2	VCC	Power Supply, 3.3V Typ.	1, Interface chips 1.1 LCD: LVDS Receiver
3	VCC	Power Supply, 3.3V Typ.	(LVDSRX_SPI_UMOD) or equivalent 1.2 System: it must include international
4	V EEDID	DDC 3.3V power	standard LVDS Transmitter.
5	NC	No Connection	2. Connector 2.1 LCD : DF19KR-20P-1H, HIROSE or
6	CLK EEDID	DDC Clock	its compatibles 2.2 Mating : DF19G-20S-1C or equivalent.
7	DATA EEDID	DDC Data	2.3 Connector pin arrangement
8	RA1-	Odd Channel Differential signal	
9	RA1+	Odd Channel Differential signal	CN1
10	GND	Ground	1 20
11	RB1-	Odd Channel Differential signal	
12	RB1+	Odd Channel Differential signal	
13	GND	Ground —	
14	RC1-	Odd Channel Differential signal	Visuing on Dienley side
15	RC1+	Odd Channel Differential signal	Viewing on Display side CN2
16	GND	Ground	CINZ
17	RCLK1-	Odd Channel Differential signal	20 1
18	RCLK1+	Odd Channel Differential signal	CN1
19	GND	Ground	
20	RA2-	Ground	[LCD Module Rear View]

The backlight interface connector is a model BHSR-02VS-1, manufactured by JST or its compatibles . The mating connector part number is SM02B-BHSS-1 or equivalent.

Table 4. BACKLIGHT CONNECTOR PIN CONFIGURATION (J3)

Pin	Symbol	Description	Notes
1	HV	Power supply for lamp (High voltage side)	1
2	LV	Power supply for lamp (Low voltage side)	1

Notes: 1. The high voltage side terminal is colored pink and the low voltage side terminal is yellow



### 3-3. Signal Timing Specifications


This is the signal timing required at the input of the User connector. All of the interface signal timing should be satisfied with the following specifications and specifications of LVDS Tx/Rx for it's proper operation.

**Table 6. TIMING TABLE** 

ITEM	Symbol		Min	Тур	Max	Unit	Note
DCLK	Frequency	fclk	67.5	71.0	74.5	MHz	
	Period	Thp	1366	1440	1488		
Hsync	Width	twn	16	32	48	tclk	
	Active	twha	1280	1280	1280		
Vsync	Period	t∨P	811	823	847		
	Width	tw∨	3	6	9	tHP	
	Active	twva	800	800	800		
Data	Horizontal back porch	tHBP	54	80	98	tour	
Enable	Horizontal front porch	tHFP	16	48	62	tCLK	
	Vertical back porch	tvbp	5	14	35	tup	
	Vertical front porch	tVFP	3	3	3	tHP	

# 3-4. Signal Timing Waveforms

Condition: VCC =3.3V





### 3-5. Color Input Data Reference


The brightness of each primary color (red,green and blue) is based on the 6-bit gray scale data input for the color; the higher the binary input, the brighter the color. The table below provides a reference for color versus data input.

**Table 7. COLOR DATA REFERENCE** 

									Inp	out Co	olor D	ata							
	Color			RE	D					GRE	EN					BL	UE		
		MSE					LSB							MSE					LSB
	In	R5	R4	R3	R2	R1	R0	G5	G4	G3	G2	G1	G0	B5	B4	В3	B2	B1	B0
	Black	0			0	0	0	0	0		o	0	0	0	0		0		
	Red	1			1	1		0	o	0		0	0	0	0		0	0	
	Green	0	0	0	0	0	0	1	1			1	1	0	0		0		
Basic	Blue	0	0	0	0	0	0	0	0	0	0	0	0	1	1				
Color	Cyan	0	0	0	0	0	0	1	1	1		1	1	1	1	1	1	1	. 1
	Magenta	1	1	1	1	1	1	0	0	0	0	0	0	1	1	1	1	1	1
	Yellow	1	1	1	1	1	1	1	1	1	1	1	1	0	0	0	0	0	0
	White	1	1	1	1	1	1	1_	_ 1	1	1	1	1	1	1	1	1	1	1
	RED (00)	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	RED (01)	0	0	0	0	0	1	0	0	0	0	0	0	0	0	0	0	0	0
RED		ļ																	
	RED (62)	1	1	1	1	1	0	0	0	0	0	0	0	0	0	0	0	0	0
	RED (63)	1	1	1	1	1	1	0	0	0	0	0	0	0	0	0	0	0	0
	GREEN (00)	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	GREEN (01)	0	0	0	0	0	0	0	0	0	0	0	1	0	0	0	0	0	0
GREEN																			
	GREEN (62)	0	0	0	0	0	0	1	1	1	1	1	0	0	0	0	0	0	0
	GREEN (63)	0	0	0	0	0	0	1	1	1	1	1	1	0	0	0	0	0	0
	BLUE (00)	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	BLUE (01)	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	1
BLUE																			
	BLUE (62)	0	0	0	0	0	0	0	0	0	0	0	0	1	1	1	1	1	0
	BLUE (63)	0	0	0	0	0	0	0	0	0	0	0	0	1	1	1	1	1	1



### 3-6. Power Sequence



**Table 8. POWER SEQUENCE TABLE** 

Parameter		Value		Units
	Min.	Тур.	Max.	
T <sub>1</sub>	0.5	-	10	(ms)
T <sub>2</sub>	0	-	50	(ms)
T <sub>3</sub>	200	-	-	(ms)
T <sub>4</sub>	200	-	-	(ms)
T <sub>5</sub>	0	-	50	(ms)
T <sub>6</sub>	0	-	10	(ms)
T <sub>7</sub>	200	-	-	(ms)

#### Note)

- 1. Please avoid floating state of interface signal at invalid period.
- 2. When the interface signal is invalid, be sure to pull down the power supply for LCD VCC to 0V.
- 3. Lamp power must be turn on after power supply for LCD and interface signal are valid.




### 4. Optical Specification

Optical characteristics are determined after the unit has been 'ON' and stable for approximately 30 minutes in a dark environment at 25°C. The values specified are at an approximate distance 50cm from the LCD surface at a viewing angle of  $\Phi$  and  $\Theta$  equal to  $0^{\circ}$ .

FIG. 1 Presents additional information concerning the measurement equipment and method.

FIG. 1 Optical Characteristic Measurement Equipment and Method



**Table 9. OPTICAL CHARACTERISTICS** 

Ta=25°C, VCC=3.3V,  $f_V=60Hz$ ,  $f_{CLK}=71.0MHz$ , lout = 6.0mA

		1a-25 0, vc	0-5.5 v , Iv-	00112, ICLK- 1	1.0111112,	iout = 6.0mA
Parameter	Symbol		Values		Units	Notes
Faranielei	Syrribor	Min	Тур	MAx	Utilis	Notes
Contrast Ratio	CR	350	-	-		1
Surface Luminance, white	L <sub>WH</sub>	220	250	-	cd/m <sup>2</sup>	2
Luminance Variation	$\delta_{\text{WHITE}}$		-	1.7		3
Response Time						4
Rise Time+Decay Time	$Tr_{R+}Tr_{D}$		25	35	ms	
Color Coordinates					]	
RED	RX	0.566	0.590	0.616		
	RY	0.319	0.346	0.369	]	
GREEN	GX	0.307	0.328	0.357		
	GY	0.517	0.546	0.567	]	
BLUE	BX	0.135	0.161	0.185	]	
	BY	0.123	0.148	0.173		
WHITE	WX	0.285	0.313	0.341	1	
	WY	0.309	0.329	0.349	1	
Viewing Angle						5
x axis, right(Φ=0°)	Θr	40	45	<u> </u>	degree	
x axis, left (Φ=180°)	Θl	40	45	]	degree	
y axis, up (Φ=90°)	Θu	10	15	]	degree	
y axis, down (Φ=270°)	Θd	30	35	-	degree	
Gray Scale			-			6



#### Note)

1. Contrast Ratio(CR) is defined mathematically as

Surface Luminance with all white pixels

Contrast Ratio =

Surface Luminance with all black pixels

2. Surface luminance is the average of 5 point across the LCD surface 50cm from the surface with all pixels displaying white. For more information see FIG 1.

$$L_{WH} = Average(L_1, L_2, ... L_5)$$

3. The variation in surface luminance , The panel total variation ( $\delta_{WHITE}$ ) is determined by measuring L<sub>N</sub> at each test position 1 through 13 and then defined as followed numerical formula. For more information see FIG 2.

$$\delta_{\text{WHITE}} = \frac{\text{Maximum}(\textbf{L}_{1}, \textbf{L}_{2}, \ \dots \ \textbf{L}_{13})}{\text{Minimum}(\textbf{L}_{1}, \textbf{L}_{2}, \ \dots \ \textbf{L}_{13})}$$

- Response time is the time required for the display to transition from white to black (rise time, Tr<sub>R</sub>) and from black to white(Decay Time, Tr<sub>D</sub>). For additional information see FIG 3.
- 5. Viewing angle is the angle at which the contrast ratio is greater than 10. The angles are determined for the horizontal or x axis and the vertical or y axis with respect to the z axis which is normal to the LCD surface. For more information see FIG 4.
- 6. Gray scale specification


\*  $f_{V} = 60$ Hz

Gray Level	Luminance [%] (Typ)
LO	0.16
L7	1.45
L15	5.36
L23	12.21
L31	21.01
L39	34.82
L47	52.49
L55	74.17
L63	100




#### FIG. 2 Luminance

<measuring point for surface luminance & measuring point for luminance variation>



### FIG. 3 Response Time


The response time is defined as the following figure and shall be measured by switching the input signal for "black" and "white".





### FIG. 4 Viewing angle

### <Dimension of viewing angle range>






### 5. Mechanical Characteristics

The contents provide general mechanical characteristics for the model LP133WX1-TLC1. In addition the figures in the next page are detailed mechanical drawing of the LCD.

	Horizontal	299.0 $\pm$ 0.5 mm				
Outline Dimension	Vertical	195.0 $\pm$ 0.5 mm				
	Depth	5.5mm MAX				
Bezel Area	Horizontal	289.5 $\pm$ 0.5 mm				
Dezel Alea	Vertical	182.2 $\pm$ 0.5 mm				
Active Diepley Area	Horizontal	286.08 mm				
Active Display Area	Vertical	178.8 mm				
Weight	350g Typ, 360g Max					
Surface Treatment	Anti-Reflection & Glare, hard coating 3H					




### <FRONT VIEW>






### <REAR VIEW>





### [ DETAIL DESCRIPTION OF SIDE MOUNTING SCREW ]



- \* Screw Length "A" Max: 1.9mm \* Hole depth "B" Max: 2.3mm \* Mounting hole location: 2.8mm(typ) \* Screw Torque: Max 2.0kgf.cm (Measurement gauge : torque meter)

Notes: 1. Screw plated through the method of non-electrolytic nickel plating is preferred to reduce possibility that results in vertical and/or horizontal line defect due to the conductive particles from screw surface.



# 6. Reliability

#### Environment test condition

No.	Test Item	Conditions				
1	High temperature storage test	Ta= 60°C, 240h				
2	Low temperature storage test	Ta= -20°C, 240h				
3	High temperature operation test	Ta= 50°C, 50%RH, 240h				
4	Low temperature operation test	Ta= 0°C, 240h				
5	Vibration test (non-operating)	Sine wave, 10 ~ 500 ~ 10Hz, 1.5G, 0.37oct/min 3 axis, 1hour/axis				
6	Shock test (non-operating)	Half sine wave, 180G, 2ms one shock of each six faces(I.e. run 180G 2ms for all six faces)				
7	Altitude operating storage / shipment	0 ~ 10,000 feet (3,048m) 24Hr 0 ~ 40,000 feet (12,192m) 24Hr				

<sup>{</sup> Result Evaluation Criteria }

There should be no change which might affect the practical display function when the display quality test is conducted under normal operating condition.



#### 7. International Standards

### 7-1. Safety

a) UL 60950-1:2003, First Edition, Underwriters Laboratories, Inc.,

Standard for Safety of Information Technology Equipment.

b) CAN/CSA C22.2, No. 60950-1-03 1st Ed. April 1, 2003, Canadian Standards Association,

Standard for Safety of Information Technology Equipment.

c) EN 60950-1:2001, First Edition,

European Committee for Electrotechnical Standardization(CENELEC)

European Standard for Safety of Information Technology Equipment.

#### 7-2. EMC

- a) ANSI C63.4 "Methods of Measurement of Radio-Noise Emissions from Low-Voltage Electrical and Electrical Equipment in the Range of 9kHZ to 40GHz. "American National Standards Institute(ANSI), 1992
- b) C.I.S.P.R. "Limits and Methods of Measurement of Radio Interface Characteristics of Information Technology Equipment." International Special Committee on Radio Interference.
- c) EN 55022 "Limits and Methods of Measurement of Radio Interface Characteristics of Information Technology Equipment." European Committee for Electrotechnical Standardization.(CENELEC), 1998 (Including A1: 2000)



# 8. Packing

### 8-1. Designation of Lot Mark

a) Lot Mark

А	В	С	D	Е	F	G	Н	I	J	K	L	М
			1 1		1 1	1 1		1 1				

A,B,C : SIZE(INCH) D : YEAR

E: MONTH  $F \sim M$ : SERIAL NO.

#### Note

#### 1. YEAR

Year	2001	2002	2003	2004	2005	2006	2007	2008	2009	2010
Mark	1	2	3	4	5	6	7	8	9	0

#### 2. MONTH

Month	Jan	Feb	Mar	Apr	May	Jun	Jul	Aug	Sep	Oct	Nov	Dec
Mark	1	2	3	4	5	6	7	8	9	Α	В	С

#### b) Location of Lot Mark

Serial No. is printed on the label. The label is attached to the backside of the LCD module. This is subject to change without prior notice.

### 8-2. Packing Form

a) Package quantity in one box: 30 pcs

b) Box Size :  $475.0 \text{ mm} \times 348.0 \text{ mm} \times 274.0 \text{ mm}$ 



#### 9. PRECAUTIONS

Please pay attention to the following when you use this TFT LCD module.

#### 9-1. MOUNTING PRECAUTIONS

- (1) You must mount a module using holes arranged in four corners or four sides.
- (2) You should consider the mounting structure so that uneven force(ex. Twisted stress) is not applied to the module.
  - And the case on which a module is mounted should have sufficient strength so that external force is not transmitted directly to the module.
- (3) Please attach a transparent protective plate to the surface in order to protect the polarizer.

  Transparent protective plate should have sufficient strength in order to the resist external force.
- (4) You should adopt radiation structure to satisfy the temperature specification.
- (5) Acetic acid type and chlorine type materials for the cover case are not describe because the former generates corrosive gas of attacking the polarizer at high temperature and the latter causes circuit break by electro-chemical reaction.
- (6) Do not touch, push or rub the exposed polarizers with glass, tweezers or anything harder than HB pencil lead. And please do not rub with dust clothes with chemical treatment. Do not touch the surface of polarizer for bare hand or greasy cloth.(Some cosmetics are determined to the polarizer.)
- (7) When the surface becomes dusty, please wipe gently with absorbent cotton or other soft materials like chamois soaks with petroleum benzene. Normal-hexane is recommended for cleaning the adhesives used to attach front / rear polarizers. Do not use acetone, toluene and alcohol because they cause chemical damage to the polarizer.
- (8) Wipe off saliva or water drops as soon as possible. Their long time contact with polarizer causes deformations and color fading.
- (9) Do not open the case because inside circuits do not have sufficient strength.

#### 9-2. OPERATING PRECAUTIONS

- (1) The spike noise causes the mis-operation of circuits. It should be lower than following voltage : V=±200mV(Over and under shoot voltage)
- (2) Response time depends on the temperature.(In lower temperature, it becomes longer.)
- (3) Brightness depends on the temperature. (In lower temperature, it becomes lower.)

  And in lower temperature, response time(required time that brightness is stable after turned on) becomes longer.
- (4) Be careful for condensation at sudden temperature change. Condensation makes damage to polarizer or electrical contacted parts. And after fading condensation, smear or spot will occur.
- (5) When fixed patterns are displayed for a long time, remnant image is likely to occur.
- (6) Module has high frequency circuits. Sufficient suppression to the electromagnetic interference shall be done by system manufacturers. Grounding and shielding methods may be important to minimized the interference.



#### 9-3. ELECTROSTATIC DISCHARGE CONTROL

Since a module is composed of electronic circuits, it is not strong to electrostatic discharge. Make certain that treatment persons are connected to ground through wrist band etc. And don't touch interface pin directly.

#### 9-4. PRECAUTIONS FOR STRONG LIGHT EXPOSURE

Strong light exposure causes degradation of polarizer and color filter.

#### 9-5. STORAGE

When storing modules as spares for a long time, the following precautions are necessary.

- (1) Store them in a dark place. Do not expose the module to sunlight or fluorescent light. Keep the temperature between 5°C and 35°C at normal humidity.
- (2) The polarizer surface should not come in contact with any other object.

  It is recommended that they be stored in the container in which they were shipped.

### 9-6. HANDLING PRECAUTIONS FOR PROTECTION FILM

- (1) When the protection film is peeled off, static electricity is generated between the film and polarizer. This should be peeled off slowly and carefully by people who are electrically grounded and with well ion-blown equipment or in such a condition, etc.
- (2) The protection film is attached to the polarizer with a small amount of glue. If some stress is applied to rub the protection film against the polarizer during the time you peel off the film, the glue is apt to remain on the polarizer.
  - Please carefully peel off the protection film without rubbing it against the polarizer.
- (3) When the module with protection film attached is stored for a long time, sometimes there remains a very small amount of glue still on the polarizer after the protection film is peeled off.
- (4) You can remove the glue easily. When the glue remains on the polarizer surface or its vestige is recognized, please wipe them off with absorbent cotton waste or other soft material like chamois soaked with normal-hexane.



# APPENDIX A. Enhanced Extended Display Identification Data (EEDID™) 1/3

Byte#	Byte#	5.111	Valu	ue	Value	
(decimal)	(HEX)	Field Name and Comments	(HE		(binary)	
0	00	Header	0	0	0000 0000	
1	01	Header		F	1111 1111	
2	02	Header		F	1111 1111	
3	03	Header	F	F.	1111 1111	Header
4	04	Header		F	1111 1111	
5 6	05	Header		F F	1111 1111	
7	06 07	Header Header	0	0	1111 1111	
8	08	EISA manufacturer code(3 Character ID) = LEN		0	0011 0000	
9	09	Compressed ASCII	A	E	1010 1110	
10	0A	ID Product Code (LSB) - WXGA	3	1	0011 0001	
11	0B	ID Product Code (MSB)	4	0	0100 0000	
12	0C	LCD module Serial No - Preferred but Optional ("0" if not used)	0	0	0000 0000	Vender/
13	0D	LCD module Serial No - Preferred but Optional ("0" if not used)	0	0	0000 0000	Product ID
14	0E	LCD module Serial No - Preferred but Optional ("0" if not used)	0	0	0000 0000	FIOGUCTID
15	0E	LCD module Serial No - Preferred but Optional ("0" if not used)	0	0	0000 0000	
16	10	Week of Manufacture	_	0	0000 0000	
17			1	-		
	11	Year of Manufacture = 2007		1	0001 0001 0000 0001	EDID Varaian/
18 19	12 13	EDID Structure version # = 1 EDID Revision # = 3		3	0000 0001	EDID Version/ Revision
20	14	Video Input Definition = Digital I/P,non TMDS CRGB	8	0	1000 0000	nevision
21	15	Max H image size(cm)=28.608cm(29)		D	0001 1101	Display
22	16	Max V image size(cm)=17.880cm(18)	1	2	0001 0010	Parameter
23	17	Display gamma =2.2	7	8	0111 1000	
24	18	Feature support(DPMS) = Active off, RGB Color	0	Α	0000 1010	
25	19	Red/Green low Bits	2	F	0010 1111	
26	1A	Blue/White Low Bits		0	0011 0000	
27	1B	Red X = 0.590	9	7	1001 0111	
28	1C	Red Y = 0.346		8	0101 1000	
29	1D	Green X = 0.328		3 B	0101 0011 1000 1011	Color
30 31	1E 1F	Green Y = 0.546 Blue X = 0.161	_	9	0010 1011	Characteristic
32	20	Blue Y = 0.148		5	0010 1001	
33	21	White X = 0.313	5	0	0101 0000	
34	22	White Y = 0.329	5	4	0101 0100	
35	23	Established Timing I = 00h(If not used)	0	0	0000 0000	Established
36	24	Established Timing II = 00h(If not used)	0	0	0000 0000	Timings
37	25	Manufacturer's Timings = 00h(If not used)	0	0	0000 0000	_
38	26	Standard Timing Identification 1 was not used	0	1	0000 0001	
39	27	Standard Timing Identification 1 was not used	0	1	0000 0001	
40	28	Standard Timing Identification 2 was not used	0	1	0000 0001	
41	29	Standard Timing Identification 2 was not used	0	1	0000 0001	
42	2A	Standard Timing Identification 3 was not used	0	1	0000 0001	
43	2B	Standard Timing Identification 3 was not used	0	1	0000 0001	
44	2C	Standard Timing Identification 4 was not used	0	1	0000 0001	Standard
45	2D	Standard Timing Identification 4 was not used	0	1	0000 0001	Timing ID
46	2E	Standard Timing Identification 5 was not used	0	1	0000 0001	<u>.</u>
47	2F	Standard Timing Identification 5 was not used	0	1	0000 0001	
48	30	Standard Timing Identification 6 was not used	0	1	0000 0001	
49	31	Standard Timing Identification 6 was not used	0	1	0000 0001	
50	32	Standard Timing Identification 7 was not used	0	1	0000 0001	
51	33	Standard Timing Identification 7 was not used	0	1	0000 0001	
52	34	Standard Timing Identification 8 was not used	Ö	1	0000 0001	
53	35	Standard Timing Identification 8 was not used	0	1	0000 0001	
35	55	Totalidata Titting lactitilication o was not used	U	ı	0000 0001	



# APPENDIX A. Enhanced Extended Display Identification Data (EEDID™) 2/3

Byte# (decimal)	Byte# (HEX)	Field Name and Comments	Val (HE			
54	36	1280X800 @60Hz mode pixel clock (LSB) => 71MHz	,	_	1011 1100	
55	37	(Stored LSB first)	1		0001 1011	
56	38	Horizontal Active = 1280 pixels (lower 8bits)	0		0000 0000	
57	39	Horizontal Blanking = 160 pixels (lower 8bits)	Α		1010 0000	
58	3A	Horizontal Active: Horizontal Blanking (upper 4:4bits)	5	0	0101 0000	
59	3B	Vertical Avtive = 800 lines (lower 8bits)	2		0010 0000	
60	3C	Vertical Blanking = 23 lines (lower 8bits)	1	7	0001 0111	
61	3D	Vertical Active: Vertical Blanking (upper 4:4bits)	3	0	0011 0000	Timing
62	3E	Horizontal Sync. Offset = 48 pixels	3	О	0011 0000	Descriptor
63	3F	Horizontal Sync Pulse Width = 32 pixels	2	0	0010 0000	#1
64	40	Vertical Sync Offset = 3 lines : Sync Width = 6 lines	3	6	0011 0110	
65	41	Horizontal Vertical Sync Offset/Width upper 2bits = 0	0	0	0000 0000	
66	42	Horizontal Image Size = 286.08mm(286)	1	Ε	0001 1110	
67	43	Vertical Image Size = 178.80cm(179)	В		1011 0011	
68	44	Horizontal & Vertical Image Size	1		0001 0000	
69	45	Horizontal Border = 0	0	0	0000 0000	
70	46	Vertical Border = 0	0	0	0000 0000	
71	47	Non-interlaced, Normal display, no stereo, Digital separate sync, H/V pol negatives	1	8	0001 1000	
72	48	Detailed Timing Descriptor #2	0		0000 0000	
73	49		0	0	0000 0000	
74	4A		0		0000 0000	
75	4B		0	0	0000 0000	
76	4C		0	0	0000 0000	
77	4D		0	0	0000 0000	
78	4E		0	0	0000 0000	
79	4F		0		0000 0000	Timing
80	50		0	0	0000 0000	Description
81	51		0		0000 0000	#2
82	52		0		0000 0000	
83	53		0		0000 0000	
84	54		0		0000 0000	
85	55		0		0000 0000	
86	56		0		0000 0000	
87	57		_		0000 0000	
88	58		0		0000 0000	
89	59		0		0000 0000	
90	5A	Detailed Timing Descriptor #3	0		0000 0000	
91	5B		0		0000 0000	
92	5C		0		0000 0000	
93	5D		0		0000 1111	
94	5E		0		0000 0000	
95	5F	(Horizontal active pixel /8)-31	8		1000 0001	
96	60	Image Aspect Ratio(16:10)	0		0000 1010	
97	61	Low Refresh Rate #1(50Hz)	3		0011 0010	Timing
98	62	(Horizontal active pixel /8)-31	8		1000 0001	Description
99	63	Image Aspect Ratio(16:10)	0		0000 1010	#3
100	64	Low Refresh Rate #2(40Hz)	2		0010 1000	
101	65	Brightness(1/10nit) - 250nit	1		0001 1001	
102	66	Feature flag(TN mode)	0		0000 0001	
103	67	Reserved 00h	0		0000 0000	
104	68	EISA manufacturer code(3 Character ID) - LPL	3		0011 0010	
105	69	Compressed ASCII	0		0000 1100	
106	6A	Panel Supplier Reserved - Product code	0		0000 0000	
107	6B	(Hex, LSB first)	F	5	1111 0101	



# APPENDIX A. Enhanced Extended Display Identification Data (EEDID™) 3/3

Byte#	Byte#	Field Nam e and Com m ents		lue	Value	
(decim al)			•	EX)	(b inary)	
108		Detailed Timing Descriptor#4	0		0000 0000	
109	6D		0		0000 0000	
110	6E		0	0	0000 0000	
111	6F		F	Ε	1111 1110	
112	70		0	0	0000 0000	
113	71	L	4		0100 1100	
114	72	Р	5		0101 0000	
115	73		3		0011 0001	Tim ing
116	74	3	3		0011 0011	
117	75	3	3		0011 0011	#4
118	76	W	5		0101 0111	
119	77	Х	5		0101 1000	
120	78	1	3		0011 0001	
121	79		2		0010 1101	
122	7A	T	5		0101 0100	
123	7B		4		0100 1100	
124	7C	C	4		0100 0011	
125	7D	1	3		0011 0001	
126		Extension that - 00	0			Extension Flag
127		Extension flag = 00 Checksum	Ŭ		0111 1000	