

# UNISONIC TECHNOLOGIES CO., LTD


LR5966 cmos ic

# 5A LOW DROPOUT LINEAR REGULATOR

#### DESCRIPTION

The UTC **LR5966** belonged to low quiescent current(60µA typ.), low dropout, linear regulators operating from 2.25V to 6V input and are guaranteed to deliver 5A. Wide range of preset output voltage options are available. Built-in low on-resistance transistor provides low dropout voltage and large output current. The UTC **LR5966** are designed and optimized for battery-powered systems to work with low noise.

The UTC LR5966 consume less than  $0.01\mu A$  in shutdown mode. Other features include ultra low dropout voltage, current limiting protection, thermal shutdown protection and high ripple rejection ratio.




#### **■** FEATURES

- \* 5A Guaranteed Output Current
- \* 0.01µA Shutdown Current
- \* Low Temperature Coefficient
- \* Current Limiting Protection
- \* Thermal Shutdown Protection
- \* Excellent Line/Load Transient

#### ■ ORDERING INFORMATION

Ordering Number  Lead Free Halogen Free		Dookogo	Pin Assignment					Dooking	
		Package	1	2	3	4	5	Packing	
LR5966L-xx-TN5-R	LR5966G-xx-TN5-R	TO-252-5	S		G	0	Α	Tape Reel	
LR5966L-xx-TN5-T	LR5966G-xx-TN5-T	TO-252-5	S	ı	G	0	Α	Tube	

Note: Pin Assignment:  $I:V_{IN}$  O: $V_{OUT}$  G:GND S:  $\overline{SHDN}$  A: SET




www.unisonic.com.tw 1 of 5
Copyright © 2011 Unisonic Technologies Co., Ltd 0w-R102-046.a

Free Datasheet http://www.datasheet4u.com/

#### ■ MARKING INFORMATION

PACKAGE	VOLTAGE CODE	MARKING					
TO-252-5	33 :3.3V	Pin Code  Voltage Code  1 2 3 4 5					


#### ■ PIN CONFIGURATION



#### ■ PIN DESCRIPTION

PIN NO	PIN NAME	DESCRIPTION						
1	SHDN	Active-Low Shutdown Input. A logic low at SHDN reduces supply current to 0.01µA.						
		Connect SHDN to V <sub>IN</sub> for normal operation.						
2	$V_{IN}$	Power Input Voltage. Supply voltage can range from 2.25V to 6V.						
3	GND	Ground						
4	$V_{OUT}$	Output Voltage						
		When this pin is connected to ground, turns to fixed output voltage operation.						
5	SET	When this pin is connected to an external resistor divider, turns to adjustable output						
		voltage mode operation.						

## ■ BLOCK DIAGRAM



#### ■ ABSOLUTE MAXIMUM RATING (T<sub>A</sub>=25°C)

PARAMETER	SYMBOL	RATINGS	UNIT
Supply Voltage	$V_{IN}$	7	V
Power Dissipation	$P_{D}$	1250	mW
Junction Temperature	$T_J$	+125	°C
Operation Temperature	T <sub>OPR</sub>	-40 ~ +125	°C
Storage Temperature	T <sub>STG</sub>	-65 ~ +150	°C

Note: Absolute maximum ratings are those values beyond which the device could be permanently damaged. Absolute maximum ratings are stress ratings only and functional device operation is not implied.

#### ■ THERMAL DATA

PARAMETER	SYMBOL	RATINGS	UNIT
Junction to Ambient	$\theta_{JA}$	64	°C/W
Junction to Case	$\theta_{JC}$	4	°C/W


## ■ ELECTRICAL CHARACTERISTICS (T<sub>A</sub>= 25°C, unless otherwise specified)

 $V_{IN}$  =  $V_{OUT}$  + 1V or  $V_{IN}$  =2.25V whichever is greater,  $C_{IN}$  =1 $\mu$ F,  $C_{OUT}$  =2.2 $\mu$ F(Ceramic)

PARAMETER	SYMBOL	TEST CONDITIONS			MIN	TYP	MAX	UNIT	
Input Voltage	$V_{IN}$				2.25		6	V	
Output Voltage Accuracy	\/	T <sub>A</sub> =25°C , I <sub>OUT</sub> = 1mA ~5A			-2		2	%	
Output Voltage Accuracy	$V_{OUT}$	T <sub>A</sub> =0~85°C	T <sub>A</sub> =0~85°C, I <sub>OUT</sub> = 1mA~5A		-3		3	%	
Maximum Output Current	I <sub>OUT</sub>					5		Α	
Short-Circuit Current Limit	I <sub>LIMIT</sub>	V <sub>OUT</sub> >1.2V				7.5		Α	
Reference Current	$V_{REF}$	Measured on SET, V <sub>IN</sub> =2.8V, I <sub>OUT</sub> =10mA			0.784	0.8	0.816	٧	
One and Die Oranget		I <sub>OUT</sub> = 0mA				60			
Ground Pin Current	$I_{GND}$	I <sub>OUT</sub> = 1mA to	5A			90		μA	
			1.5V<=V <sub>O</sub>	<sub>UT</sub> <=1.8V			1800		
Dropout Voltage (Note)	$V_D$	I <sub>OUT</sub> =5A	1.8V <v<sub>OUT&lt;2.5V</v<sub>				1000	mV	
		2.5<=V <sub>OUT</sub>					650		
Line Regulation	$\frac{\Delta V_{OUT}}{\Delta V_{IN} \times V_{OUT}}$	V <sub>IN</sub> =V <sub>OUT</sub> +V <sub>D</sub> ~6V				0.08	0.18	%/V	
Load Regulation	$\Delta V_{OUT}$	V <sub>IN</sub> =V <sub>OUT</sub> +1\	/, I <sub>OUT</sub> =10m	nA~5A		0.25	1	%	
Output Voltage Noise	eN	f=10Hz to100kHz,C <sub>OUT</sub> =2.2µF				30		$\mu V_{RMS}$	
Shutdown Supply Current	I <sub>OFF</sub>	SHDN =GND			0.01	5	μA		
	PSRR	I <sub>OUT</sub> =100mA		f=100Hz		60		dB	
Power Supply Rejection		C <sub>OUT</sub> =10µF		f=1kHz		45			
	V <sub>IH</sub>	-		1.6			V		
Shutdown Threshold	V <sub>IL</sub>					0.6	V		
Thermal Shutdown Temperature	T <sub>SHDN</sub>				160		°C		
Thermal Shutdown Hysteresis	DT <sub>SHDN</sub>					50			

Note: The dropout voltage is defined as  $V_{IN}$  - $V_{OUT}$ , which is measured when  $V_{OUT}$  is  $V_{OUT(NORMAL)}$  - 100mV.

TYPICAL APPLICATION CIRCUIT



UTC assumes no responsibility for equipment failures that result from using products at values that exceed, even momentarily, rated values (such as maximum ratings, operating condition ranges, or other parameters) listed in products specifications of any and all UTC products described or contained herein. UTC products are not designed for use in life support appliances, devices or systems where malfunction of these products can be reasonably expected to result in personal injury. Reproduction in whole or in part is prohibited without the prior written consent of the copyright owner. The information presented in this document does not form part of any quotation or contract, is believed to be accurate and reliable and may be changed without notice.