

Addendum

HC908JB8AD/D
Rev. 0, 4/2002

Addendum to
MC68HC908JB8
Technical Data



This addendum provides additional information to the
MC68HC908JB8 Technical Data, Rev. 2
(Motorola document number MC68HC908JB8/D),

MC68HC08JB8A

The MC68HC08JB8A is the ROM part equivalent to the MC68HC908JB8. The entire MC68HC908JB8 data book apply to this ROM device, with exceptions outlined in this addendum.

Table 1. Summary of MC68HC08JB8A and MC68HC908JB8 Differences

	MC68HC08JB8A	MC68HC908JB8
Memory (\$DC00–\$FBFF)	8,192 bytes ROM	8,192 bytes FLASH
User vectors (\$FFF0–\$FFFF)	16 bytes ROM	16 bytes FLASH
Registers at \$FE08 and \$FF09	Not used; locations are reserved.	FLASH related registers. \$FE08 — FLCR \$FF09 — FLBPR
Monitor ROM (\$FC00–\$FDFF and \$FE10–\$FFDF)	\$FC00–\$FDFF: Not used. \$FE10–\$FFDF: Used for testing purposes only.	Used for testing and FLASH programming/erasing.
OSC1 and OSC2 pins	V _{DD} level (5V logic)	V _{REG} level (3.3V logic)

MCU Block Diagram **Figure 1** shows the block diagram of the MC68HC08JB8A.

Memory Map The MC68HC08JB8A has 8,192 bytes of user ROM from \$DC00 to \$FBFF, and 16 bytes of user ROM vectors from \$FFF0 to \$FFFF. On the MC68HC908JB8, these memory locations are FLASH memory.

Figure 2 shows the memory map of the MC68HC08JB8A.




Figure 1. MC68HC08JB8A Block Diagram

\$0000 ↓ \$003F	I/O Registers 64 Bytes
\$0040 ↓ \$013F	RAM 256 Bytes
\$0140 ↓ \$DBFF	Unimplemented 56,000 Bytes
\$DC00 ↓ \$FBFF	ROM 8,192 Bytes
\$FC00 ↓ \$FDFF	Unimplemented 512 Bytes
\$FE00	Break Status Register (BSR)
\$FE01	Reset Status Register (RSR)
\$FE02	Reserved
\$FE03	Break Flag Control Register (BFCR)
\$FE04	Interrupt Status Register 1 (INT1)
\$FE05	Reserved
\$FE06	Reserved
\$FE07	Reserved
\$FE08	Reserved
\$FE09	Reserved
\$FE0A	Reserved
\$FE0B	Reserved
\$FE0C	Break Address High Register (BRKH)
\$FE0D	Break Address Low Register (BRKL)
\$FE0E	Break Status and Control Register (BRKSCR)
\$FE0F	Reserved
\$FE10 ↓ \$FFDF	Monitor ROM 464 Bytes
\$FFE0 ↓ \$FFEF	Reserved 16 Bytes
\$FFF0 ↓ \$FFFF	ROM Vectors 16 Bytes

Figure 2. MC68HC08JB8A Memory Map

Reserved Registers

The two registers at \$FE08 and \$FE09 are reserved locations on the MC68HC08JB8A.

On the MC68HC908JB8, these two locations are the FLASH control register and the FLASH block protect register respectively.

Monitor ROM

The monitor program (monitor ROM: \$FE10–\$FFDF) on the MC68HC08JB8A is for device testing only. \$FC00–\$FDFF are unused.

Electrical Specifications

Electrical specifications for the MC68HC908JB8 apply to the MC68HC08JB8A, except for the parameters indicated below.

DC Electrical Characteristics

Table 2. DC Electrical Characteristics

Characteristic ⁽¹⁾	Symbol	Min	Typ ⁽²⁾	Max	Unit
Regulator output voltage	V _{REG}	3.0	3.3	3.6	V
Output high voltage (I _{Load} = –2.0 mA) PTA0–PTA7, PTB0–PTB7, PTC0–PTC7, PTE0–PTE2	V _{OH}	V _{REG} –0.8	—	—	V
Output low voltage (I _{Load} = 1.6 mA) All I/O pins (I _{Load} = 25 mA) PTD0–PTD1 in ILDD mode (I _{Load} = 10 mA) PTE3–PTE4 with USB disabled	V _{OL}	— — —	— — —	0.4 0.5 0.4	V
Input high voltage All ports, OSC1 $\overline{\text{IRQ}}$, $\overline{\text{RST}}$	V _{IH}	0.7 × V _{REG} 0.7 × V _{DD}	— —	V _{REG} V _{DD}	V
Input low voltage All ports, OSC1 $\overline{\text{IRQ}}$, $\overline{\text{RST}}$	V _{IL}	V _{SS} V _{SS}	— —	0.3 × V _{REG} 0.3 × V _{DD}	V
Output low current (V _{OL} = 2.0 V) PTD2–PTD5 in LDD mode	I _{OL}	12 (17)	17 (22)	22 (27)	mA
V _{DD} supply current, V _{DD} = 5.25V, f _{OP} = 3MHz	I _{DD}	—	6.0 (5.0)	7.5	mA
Run, with low speed USB ⁽³⁾					
Run, with USB suspended ⁽³⁾					
Wait, with low speed USB ⁽⁴⁾					
Wait, with USB suspended ⁽⁴⁾					
Stop ⁽⁵⁾ 0 °C to 70°C		—	30	100	μA

Table 2. DC Electrical Characteristics

Characteristic ⁽¹⁾	Symbol	Min	Typ ⁽²⁾	Max	Unit
I/O ports Hi-Z leakage current	I_{IL}	—	—	± 10	μA
Input current	I_{IN}	—	—	± 1	μA
Capacitance Ports (as input or output)	C_{Out} C_{In}	— —	— —	12 8	pF
POR re-arm voltage ⁽⁶⁾	V_{POR}	0	—	100	mV
POR rise-time ramp rate ⁽⁷⁾	R_{POR}	0.035	—	—	V/ms
Monitor mode entry voltage	$V_{DD}+V_{HI}$	$1.4 \times V_{DD}$		$2 \times V_{DD}$	V
Pullup resistors Port A, port B, port C, PTE0–PTE2, $\overline{RST}$, $\overline{IRQ}$ PTE3–PTE4 (with USB module disabled) D– (with USB module enabled)	R_{PU}	25 4 1.2	40 5 1.5	55 6 2.0	k Ω
LVI reset	V_{LVR}	2.8 (2.4)	3.3 (2.7)	3.8 (3.0) ⁽⁸⁾	V

- $V_{DD} = 4.0$ to 5.5 Vdc, $V_{SS} = 0$ Vdc, $T_A = T_L$ to T_H , unless otherwise noted.
- Typical values reflect average measurements at midpoint of voltage range, $25^\circ C$ only.
- Run (operating) I_{DD} measured using external square wave clock source ($f_{XCLK} = 6$ MHz). All inputs 0.2 V from rail. No dc loads. Less than 100 pF on all outputs. $C_L = 20$ pF on OSC2. All ports configured as inputs. OSC2 capacitance linearly affects run I_{DD} . Measured with all modules enabled.
- Wait I_{DD} measured using external square wave clock source ($f_{XCLK} = 6$ MHz); all inputs 0.2 V from rail; no dc loads; less than 100 pF on all outputs. $C_L = 20$ pF on OSC2; 15 k $\Omega \pm 5\%$ termination resistors on D+ and D– pins; all ports configured as inputs; OSC2 capacitance linearly affects wait I_{DD} .
- STOP I_{DD} measured with USB in suspend mode; OSC1 grounded; transceiver pullup resistor of 1.5 k $\Omega \pm 5\%$ between V_{REG} and D– pins and 15 k $\Omega \pm 5\%$ termination resistor on D+ pin; no port pins sourcing current.
- Maximum is highest voltage that POR is guaranteed.
- If minimum V_{REG} is not reached before the internal POR reset is released, $\overline{RST}$ must be driven low externally until minimum V_{REG} is reached.
- The numbers in parenthesis are MC68HC08JB8 (non-A part) values.

Memory Characteristics

Table 3. Memory Characteristics

Characteristic	Symbol	Min	Max	Unit
RAM data retention voltage	V_{RDR}	1.3	—	V

Notes:

Since MC68HC08JB8A is a ROM device, FLASH memory electrical characteristics do not apply.

MC68HC08JB8A Order Numbers

These part numbers are generic numbers only. To place an order, ROM code must be submitted to the ROM Processing Center (RPC).

Table 4. MC68HC08JB8A Order Numbers

MC order number	Package	Operating temperature range
MC68HC08JB8AJP	20-pin PDIP	0 °C to +70 °C
MC68HC08JB8AJDW	20-pin SOIC	0 °C to +70 °C
MC68HC08JB8AADW	28-pin SOIC	0 °C to +70 °C
MC68HC08JB8AFB	44-pin QFP	0 °C to +70 °C

MC68HC08JB8A and MC68HC08JB8 Differences

The MC68HC08JB8A and MC68HC08JB8 are identical devices, except for the following:

Table 5. MC68HC08JB8A and MC68HC08JB8 Differences

	MC68HC08JB8A	MC68HC08JB8
OSC1 and OSC2 pins	V _{DD} level (5V logic)	V _{REG} level (3.3V logic)
Output low current on PTD2–PTD5 in LDD mode	See Table 2 . DC Electrical Characteristics . The numbers in parenthesis are MC68HC08JB8 values.	
Operating I _{DD} currents		
LVI trip points		

NOTES

Freescale Semiconductor, Inc.

Home Page:

www.freescale.com

email:

support@freescale.com

USA/Europe or Locations Not Listed:

Freescale Semiconductor
Technical Information Center, CH370
1300 N. Alma School Road
Chandler, Arizona 85224
(800) 521-6274
480-768-2130

support@freescale.com

Europe, Middle East, and Africa:

Freescale Halbleiter Deutschland GmbH
Technical Information Center
Schatzbogen 7
81829 Muenchen, Germany
+44 1296 380 456 (English)
+46 8 52200080 (English)
+49 89 92103 559 (German)
+33 1 69 35 48 48 (French)
support@freescale.com

Japan:

Freescale Semiconductor Japan Ltd.
Headquarters
ARCO Tower 15F
1-8-1, Shimo-Meguro, Meguro-ku
Tokyo 153-0064, Japan
0120 191014
+81 2666 8080
support.japan@freescale.com

Asia/Pacific:

Freescale Semiconductor Hong Kong Ltd.
Technical Information Center
2 Dai King Street
Tai Po Industrial Estate,
Tai Po, N.T., Hong Kong
+800 2666 8080
support.asia@freescale.com

For Literature Requests Only:

Freescale Semiconductor
Literature Distribution Center
P.O. Box 5405
Denver, Colorado 80217
(800) 441-2447
303-675-2140
Fax: 303-675-2150
LDCForFreescaleSemiconductor@hibbertgroup.com

RoHS-compliant and/or Pb- free versions of Freescale products have the functionality and electrical characteristics of their non-RoHS-compliant and/or non-Pb- free counterparts. For further information, see <http://www.freescale.com> or contact your Freescale sales representative.

For information on Freescale's Environmental Products program, go to <http://www.freescale.com/epp>.

Information in this document is provided solely to enable system and software implementers to use Freescale Semiconductor products. There are no express or implied copyright licenses granted hereunder to design or fabricate any integrated circuits or integrated circuits based on the information in this document. Freescale Semiconductor reserves the right to make changes without further notice to any products herein. Freescale Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Freescale Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation consequential or incidental damages. "Typical" parameters which may be provided in Freescale Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. Freescale Semiconductor does not convey any license under its patent rights nor the rights of others. Freescale Semiconductor products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the Freescale Semiconductor product could create a situation where personal injury or death may occur. Should Buyer purchase or use Freescale Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and hold Freescale Semiconductor and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that Freescale Semiconductor was negligent regarding the design or manufacture of the part.



HC908JB8AD/D
Rev. 0
4/2003

**For More Information On This Product,
Go to: www.freescale.com**