


# MP4211

High Power, High Speed Switching Applications  
 For Printer Head Pin Driver and Pulse Motor Driver  
 For Solenoid Driver

Industrial Applications

Unit: mm

- 4-V gate drivability
- Small package by full molding (SIP 10 pin)
- High drain power dissipation (4 devices operation)  
 :  $P_T = 4 \text{ W}$  ( $T_a = 25^\circ\text{C}$ )
- Low drain-source ON resistance:  $R_{DS(ON)} = 0.16 \Omega$  (typ.)
- High forward transfer admittance:  $|Y_{fs}| = 4.0 \text{ S}$  (typ.)
- Low leakage current:  $I_{GSS} = \pm 10 \mu\text{A}$  (max) ( $V_{GS} = \pm 16 \text{ V}$ )  
 $I_{DSS} = -100 \mu\text{A}$  (max) ( $V_{DS} = -60 \text{ V}$ )
- Enhancement-mode:  $V_{th} = -0.8$  to  $-2.0 \text{ V}$  ( $V_{DS} = -10 \text{ V}$ ,  $I_D = -1 \text{ mA}$ )



## Maximum Ratings ( $T_a = 25^\circ\text{C}$ )

Characteristics	Symbol	Rating	Unit
Drain-source voltage	$V_{DSS}$	-60	V
Drain-gate voltage ( $R_{GS} = 20 \text{ k}\Omega$ )	$V_{DGR}$	-60	V
Gate-source voltage	$V_{GSS}$	$\pm 20$	V
Drain current	DC	$I_D$	-5
	Pulse	$I_{DP}$	-20
Drain power dissipation (1-device operation, $T_a = 25^\circ\text{C}$ )	$P_D$	2.0	W
Drain power dissipation (- device operation, $T_a = 25^\circ\text{C}$ )	$P_{DT}$	4.0	W
Single pulse avalanche energy (Note 1)	$E_{AS}$	273	mJ
Avalanche current	$I_{AR}$	-5	A
Repetitive avalanche energy (Note 2)	1-device operation	$E_{AR}$	0.2
	4-device operation	$E_{ART}$	0.4
Channel temperature	$T_{ch}$	150	$^\circ\text{C}$
Storage temperature range	$T_{stg}$	-55 to 150	$^\circ\text{C}$


Weight: 2.1 g (typ.)

Note 1: Condition for avalanche energy (single pulse) measurement  
 $V_{DD} = -25 \text{ V}$ , starting  $T_{ch} = 25^\circ\text{C}$ ,  $L = 14.84 \text{ mH}$ ,  $R_G = 25 \Omega$ ,  $I_{AR} = -5 \text{ A}$

Note 2: Repetitive rating; pulse width limited by maximum channel temperature

This transistor is an electrostatic-sensitive device. Please handle with caution.

## Array Configuration



## Thermal Characteristics

Characteristics	Symbol	Max	Unit
Thermal resistance from channel to ambient (4-device operation, $T_a = 25^\circ\text{C}$ )	$\Sigma R_{th(ch-a)}$	31.2	$^\circ\text{C/W}$
Maximum lead temperature for soldering purposes (3.2 mm from case for $t = 10$ s)	$T_L$	260	$^\circ\text{C}$


## Electrical Characteristics ( $T_a = 25^\circ\text{C}$ )







Characteristics		Symbol	Test Condition	Min	Typ.	Max	Unit
Gate leakage current		$I_{GSS}$	$V_{GS} = \pm 16$ V, $V_{DS} = 0$ V	—	—	$\pm 10$	$\mu\text{A}$
Drain cut-off current		$I_{DSS}$	$V_{DS} = -60$ V, $V_{GS} = 0$ V	—	—	-100	$\mu\text{A}$
Drain-source breakdown voltage		$V_{(BR)DSS}$	$I_D = -10$ mA, $V_{GS} = 0$ V	-60	—	—	V
Gate threshold voltage		$V_{th}$	$V_{DS} = -10$ V, $I_D = -1$ mA	-0.8	—	-2.0	V
Drain-source ON resistance		$R_{DS(ON)}$	$V_{GS} = -4$ V, $I_D = -2.5$ A	—	0.24	0.28	$\Omega$
			$V_{GS} = -10$ V, $I_D = -2.5$ A	—	0.16	0.19	
Forward transfer admittance		$ Y_{fs} $	$V_{DS} = -10$ V, $I_D = -2.5$ A	2.0	4.0	—	S
Input capacitance		$C_{iss}$	$V_{DS} = -10$ V, $V_{GS} = 0$ V, $f = 1$ MHz	—	630	—	pF
Reverse transfer capacitance		$C_{rss}$		—	95	—	pF
Output capacitance		$C_{oss}$		—	290	—	pF
Switching time	Rise time	$t_r$		—	25	—	ns
	Turn-on time	$t_{on}$		—	45	—	
	Fall time	$t_f$		—	55	—	
	Turn-off time	$t_{off}$		—	200	—	
Total gate charge (Gate-source plus gate-drain)		$Q_g$	$V_{DD} \approx -48$ V, $V_{GS} = -10$ V, $I_D = -5$ A	—	22	—	nC
Gate-source charge		$Q_{gs}$		—	16	—	nC
Gate-drain ("miller") charge		$Q_{gd}$		—	6	—	nC







## Source-Drain Diode Ratings and Characteristics (Ta = 25°C)






Characteristics	Symbol	Test Condition	Min	Typ.	Max	Unit
Continuous drain reverse current	$I_{DR}$	—	—	—	-5	A
Pulse drain reverse current	$I_{DRP}$	—	—	—	-20	A
Diode forward voltage	$V_{DSF}$	$I_{DR} = -5\text{ A}, V_{GS} = 0\text{ V}$	—	—	1.7	V
Reverse recovery time	$t_{rr}$	$I_{DR} = -5\text{ A}, V_{GS} = 0\text{ V}$ $dI_{DR}/dt = 50\text{ A}/\mu\text{s}$	—	80	—	ns
Reverse recovery charge	$Q_{rr}$		—	0.1	—	$\mu\text{C}$

## Marking









Peak  $I_{AR} = -5$  A,  $R_G = 25$   $\Omega$   
 $V_{DD} = -25$  V,  $L = 14.84$  mH

$$E_{AS} = \frac{1}{2} L \cdot I_{AR}^2 \cdot \left( \frac{B_{VDSS}}{B_{VDSS} - V_{DD}} \right)$$

**RESTRICTIONS ON PRODUCT USE**

030619EAA

- The information contained herein is subject to change without notice.
- The information contained herein is presented only as a guide for the applications of our products. No responsibility is assumed by TOSHIBA for any infringements of patents or other rights of the third parties which may result from its use. No license is granted by implication or otherwise under any patent or patent rights of TOSHIBA or others.
- TOSHIBA is continually working to improve the quality and reliability of its products. Nevertheless, semiconductor devices in general can malfunction or fail due to their inherent electrical sensitivity and vulnerability to physical stress. It is the responsibility of the buyer, when utilizing TOSHIBA products, to comply with the standards of safety in making a safe design for the entire system, and to avoid situations in which a malfunction or failure of such TOSHIBA products could cause loss of human life, bodily injury or damage to property.  
In developing your designs, please ensure that TOSHIBA products are used within specified operating ranges as set forth in the most recent TOSHIBA products specifications. Also, please keep in mind the precautions and conditions set forth in the "Handling Guide for Semiconductor Devices," or "TOSHIBA Semiconductor Reliability Handbook" etc..
- The TOSHIBA products listed in this document are intended for usage in general electronics applications (computer, personal equipment, office equipment, measuring equipment, industrial robotics, domestic appliances, etc.). These TOSHIBA products are neither intended nor warranted for usage in equipment that requires extraordinarily high quality and/or reliability or a malfunction or failure of which may cause loss of human life or bodily injury ("Unintended Usage"). Unintended Usage include atomic energy control instruments, airplane or spaceship instruments, transportation instruments, traffic signal instruments, combustion control instruments, medical instruments, all types of safety devices, etc.. Unintended Usage of TOSHIBA products listed in this document shall be made at the customer's own risk.
- TOSHIBA products should not be embedded to the downstream products which are prohibited to be produced and sold, under any law and regulations.