


SYNCHRONOUS SEPARATOR WITH COUNT DOWN

■GENERAL DESCRIPTION

The NJW1303 is a synchronous separator performs Horizontal and Vertical synchronous signal from composite video signals. It contains count down circuit for H,V keeping high sync separation in the weak signal. It is suitable for car navigation and LCD TV.


■PACKAGE OUTLINE



■FEATURES

- Operating Voltage $V^+ \approx 2.7V$ to $5.3V$
- Operating Current $5mA$ typ. at $V^+ \approx 5V$
- Output for HD, VD, C sync
- unnecessary adjustment of oscillation frequency for internal count down circuit
- Internal BGP
- Bi-CMOS Technology
- Package Outline SSOP14

■PIN FUNCTION, BLOCK DIAGRAM







■ ABSOLUTE MAXIMUM RATINGS (Ta=25°C)

PARAMETER	SYMBOL	RATINGS	UNIT
Supply Voltage	V^+	8.0	V
Power Dissipation	P_D	300	mW
Operating Temperature Range	T_{opr}	-40 to +85	°C
Storage Temperature	T_{stg}	-40 to +125	°C

■ RECOMMENDED OPERATING CONDITION

PARAMETER	SYMBOL	RATINGS	UNIT
Supply Voltage	V_{opr}	2.7 to 5.3	V


■ ELECTRICAL CHARACTERISTICS ($V^+=5V$, $T_a=25^\circ C$)

PARAMETER	SYMBOL	TEST CONDITION	MIN.	TYP.	MAX.	UNIT
Operating Current	I_{CC}	No input signal	3.3	5.0	7.5	mA
AFC Free Run Frequency	f_{OH}	Measure the Input connect to GND under 300ohm	15.654	15.734	15.814	kHz
AFC Lock Range	Δf_{HL1}	Miss lock to high frequency	+600	+700	-	Hz
	Δf_{HL2}	Miss lock to Low frequency	-	-700	-600	
AFC Capture Range	Δf_{HP1}	Capture from high frequency	+600	+700	-	Hz
	Δf_{HP2}	Capture from Low frequency	-	-700	-600	
Horizontal Output Pulse Width	P_{wHD}	Input Signal 	3.5	3.9	4.3	us
Horizontal Output Delay	T_{pDH}	Output Signal 	0.48	0.64	0.8	us
Horizontal Output Saturation Level	V_{oLH}	 *point1	-0.2	0.1	0.3	V
Horizontal AFC Keep Limit Input	V_{INGM}	Input is Color Bar of 1Vpp, and Horizontal signal of 4.8 uS pulth width. ATT less of miss lock Sync at valuable of input signal level.	-	-	-20	dB
BGP Pulse Width	P_{wGP}	Input Signal 	3.1	3.6	4.1	us
BGP Delay	T_{pDG}	Output Signal 	0.35	0.6	0.85	us
BGP Limit Input	V_{MINBGP}	Input is Color Bar of 1Vpp, and Horizontal signal of 4.8 uS pulth width. ATT less of changeable BGP output at less of input signal level.	-	-	-17	dB


■ ELECTRICAL CHARACTERISTICS (V⁺=5V, Ta=25°C)

PARAMETER	SYMBOLS	TEST CONDITIONS	MIN.	TYP.	MAX.	UNIT
Vertical Output Pulse Width	PwVD	*point	2.5	3.0	3.5	H
Vertical Output Delay	TpVD		0.47	0.66	0.85	H
Vertical Output Saturation Level	V _L VD	Low level of Vertical output	-	0.2	0.5	V
C.SYNC Output Delay	TpCS		0.32	0.5	0.64	us
C.SYNC Output Saturation Voltage	V _L CS		-	0.2	0.5	V


*point



*When measure of pulse timing



■TEST CIRCUIT




*1: CSBLA503KE5ZF10 at MURATA

*2: NTSC/PAL SW
 NTSC : GND
 PAL : Vcc, and 9 to 10pin is 360 ohm, 10 to 11pin is 2 k ohm

■APPLICATION NOTES

- The ratio of the vertical synchronous pulse term and the vertical synchronous signal cycle
 Please adjust following expression.

The vertical synchronous signal cycle / The vertical synchronous pulse term ≥ 75 (see following figure)



- The pulse width of horizontal synchronous signal shall be set 3.7 to 5.7μs

■ EQUIVALENT CIRCUIT

No.	NAME	INSIDE EQUIVALENT CIRCUIT	No.	NAME	INSIDE EQUIVALENT CIRCUIT
1	Csync. Out		10	VCO Filter 2	
2	Sync. In		11	VCO Filter 1	
3	Vcc	_____			
4	VD HD SW BGP		12	LPF	
5			6	DIGREF	_____
7			13	GND	_____
8					
9	VCO Out		14	VS	

MEMO

[CAUTION]
The specifications on this databook are only given for information , without any guarantee as regards either mistakes or omissions. The application circuits in this databook are described only to show representative usages of the product and not intended for the guarantee or permission of any right including the industrial rights.