

SK52U THRU SK525U

5.0 AMP Surface Mount Schottky Barrier Rectifiers

Features

- · Low Power Loss, High Efficiency
- Ideally Suited for Automatic Assembly
- For Use in Low Voltage Application
- Plastic Case Material has UL Flammability
 Classification Rating 94V-0

Mechanical Data


Case: Molded plastic SMB

 Terminals: Plated leads solderable per MIL-STD-750,Method 2026 guaranteed

Polarity: Color band dentes cathode end

Mounting Position: Any

Making: Type Number



Maximum Ratings and Electrical Characteristics

Rating at 25°C ambient temperature unless otherwise specified

Single phase, half wave, 60Hz, resistive or inductive load

For capacitive load derate current by 20%


| Type Number | SYMBOL | SK 52U | SK 53U | SK 54U | SK 545U | SK 55U | SK 56U | SK 58U | | SK 515U | SK 520U | SK 525U | |
|--|-------------------------|----------------------|-----------|-----------|------------|-----------|-----------|-----------|-----|------------|------------------------|------------------|------|
| Maximum Recurrent Peak Reverse Voltage | VRRM | 20 | 30 | 40 | 45 | 50 | 60 | 80 | 100 | 150 | 200 | 250 | V |
| Maximum RMS Voltage | V _{RMS} | 14 | 21 | 28 | 31 | 35 | 42 | 56 | 70 | 105 | 140 | 175 | ٧ |
| Maximum DC Blocking Voltage | VDC | 20 | 30 | 40 | 45 | 50 | 60 | 80 | 100 | 150 | 200 | 250 | ٧ |
| Average Rectified Output Current @TL =100°C | l _{F(AV)} | 5.0 | | | | | | | | | | | Α |
| Peak Forward Surge Current 8.3ms Single half sine-wave superimposed on rated load (JEDEC Method) | IFSM | 110 | | | | | | | | | | Α | |
| Forward Voltage @IF=5.0A | V _{FM} | 0.53 | | | 0.6 | 67 | 0.82 | | 0. | 9 | 0.92 | ٧ | |
| Maximum Forward Power Dissipation | P _D | 2.65 | | | 3.3 | 35 | 4.1 | | 4. | 5 | 4.6 | W | |
| Peak Reverse Current @T _A =25 °C | | 0.1 0.05 | | | | | | | | | | ^ | |
| At Rated DC Blocking Voltage @T _A =100 °C | - I _R | 10 | | | | | | | 5 | | | | ⊢ mA |
| I ² t Rating for fusing (t <8.3ms) | I ² t | 50.21 | | | | | | | | | | A ² s | |
| Typical Junction Capacitance (Note 1) | C₁ | 220 110 | | | | | | | | рF | | | |
| Typical Thermal Resistance (Note 2) | Re JA Re JC Re JL | 94.5 20.5 14.5 | | | | | | | | | | ℃W | |
| Operating Temperature Range | TJ | -55 to+150 | | | | | | | | | $^{\circ}\!\mathbb{C}$ | | |
| Storage Temperature Range | Тѕтс | -55 to +150 | | | | | | | | | | $^{\circ}$ C | |

Note:

- 1. Measured at 1.0 MHz and Applied reverse Voltage of 4.0V D.C
- 2.Thermal Resistance from Junction to lead mounted on P.C.B. with 0.3" x 0.3" (8.0 mm x 8.0 mm) copper pad areas.

version:07 1 of 3

5.0 AMP Surface Mount Schottky Barrier Rectifiers







Fig. 2. May Not Despitive Despitive Despitive Course Course







FIG.5 MOUNTING PAD LAYOUT



PERCENT OF RATED PEAK REVERSE VOLTAGE,%

version:07 2 of 3



SK52U THRU SK525U

5.0 AMP Surface Mount Schottky Barrier Rectifiers

Important Notice and Disclaimer

- Reproducing and modifying information of the document is prohibited without permission from XINNUO
- XINNUO reserves the right to make changes to this document and its products and specifications
- XINNUO disclaims any and all liability arising out of the application or use of any product including damages incidentally and consequentially occurred.
- XINNUO does not assume any and all implied warranties, including warranties of fitness for particular purpose, non-infringement and merchantability.
- Applications shown on the here in document are examples of standard use and operation. Customers are responsible in comprehending the suitable use in particular applications.
 - XINNUO makes no representation or warranty that such applications will be suitable for the specified use without further testing or modification.
- The products shown here in are not designed and authorized for equipments requiring high level of reliability or relating to human life and for any applications concerning life-saving or life-sustaining, such as medical instruments, transportation equipment, aerospace machinery et cetera. Customers using or selling these products for use in such applications do so at their own ris k andagree to fully indemnify XINNUO for any damages resulting from such improper use or sale.
- Since XINNUO uses lot number as the tracking base, please provide the lot number for tracking when complaining.

version:07 3 of 3