


**TIS 97 TIS 98**

NPN SILICON PLANAR EPITAXIAL TRANSISTORS

MICRO ELECTRONICS

CASE T0-92 F

THE TIS97 AND TIS98 ARE LOW NOISE NPN SILICON PLANAR EPITAXIAL TRANSISTORS FOR USE IN HI-FI AUDIO AMPLIFIERS AND GENERAL PURPOSE LOW FREQUENCY APPLICATIONS.



CEB

ABSOLUTE MAXIMUM RATINGS

		TIS97	TIS98
Collector-Base Voltage	VCBO	60V	80V
Collector-Emitter Voltage	VCEO	40V	60V
Emitter-Base Voltage	VEBO	6V	6V
Collector Current	IC	200mA	200mA
Total Power Dissipation @ $T_A \leq 25^\circ\text{C}$	P_{tot}	360mW	
@ $T_C \leq 25^\circ\text{C}$		500mW	
Operating Junction & Storage Temperature	T_j, T_{stg}	-65 to 150°C	

ELECTRICAL CHARACTERISTICS @ $T_A = 25^\circ\text{C}$

PARAMETER	SYMBOL	TIS97		TIS98		UNIT	TEST CONDITIONS
		MIN	TYP	MAX	MIN	TYP	MAX
Collector-Emitter Breakdown Voltage	BVCEO	40			60		
Collector Cutoff Current	ICBO		10		10	nA	$V_{CB}=40V, I_E=0$
			10			μA	$V_{CB}=60V, I_E=0$
					10	μA	$V_{CB}=80V, I_E=0$
Emitter Cutoff Current	IEBO		20		20	nA	$V_{EB}=6V, I_C=0$
Collector-Emitter Saturation Voltage	VCE(sat)*				0.5	V	$I_C=100\text{mA}, I_B=5\text{mA}$
Collector-Emitter Voltage	VCE *				1	V	$I_C=10\text{mA}, I_B=0.1\text{mA}$
Base-Emitter Voltage	VBE *	0.45	0.65			V	$I_C=100\mu\text{A}, V_{CE}=5V$
				0.5	0.7	V	$I_C=1\text{mA}, V_{CE}=5V$
D.C. Current Gain	HFE *	250	700				$I_C=100\mu\text{A}, V_{CE}=5V$
				100	300		$I_C=1\text{mA}, V_{CE}=5V$

* Pulse Test : Pulse Width=0.3mS, Duty Cycle=1%

MICRO ELECTRONICS LTD.

38 HUNG TO ROAD, KWUN TONG, HONG KONG. TELEX 43510
KWUN TONG P. O. BOX69477 CABLE ADDRESS "MICROTRON"
TELEPHONE:- 3-430181-6 3-893363, 3-892423

FAX: 3-410321

1-2.Bmp

PARAMETER	SYMBOL	TIS97			TIS98			UNIT	TEST CONDITIONS
		MIN	TYP	MAX	MIN	TYP	MAX		
Collector-Base Capacitance	C _{cb}	1		4	1		4	pF	V _{CB} =5V I _E =0 f=1MHz
Emitter-Base Capacitance	C _{eb}			16			16	pF	V _{EB} =0.5V I _E =0 f=1MHz
Input Impedance	h _{ie}	115			6.4			KΩ	I _C =100μA V _{CE} =5V f=1kHz
								KΩ	I _C =1mA V _{CE} =5V f=1kHz
Small Signal Current Gain	h _{fe}	250	800		100		400		I _C =100μA V _{CE} =5V f=1kHz
									I _C =1mA V _{CE} =5V f=1kHz
Voltage Feedback Ratio	h _{re}	30x 10 ⁻⁴			1.5x 10 ⁻⁴				I _C =100μA V _{CE} =5V f=1kHz
									I _C =1mA V _{CE} =5V f=1kHz
Output Admittance	h _{oe}	11			6			μV	I _C =100μA V _{CE} =5V f=1kHz
								μV	I _C =1mA V _{CE} =5V f=1kHz
Forward Transfer Admittance	y _{fe}	3.8			38			mV	I _C =100μA V _{CE} =5V f=1kHz
								mV	I _C =1mA V _{CE} =5V f=1kHz
Forward Current Transfer Ratio	h _{fe}	2			2				I _C =10mA V _{CE} =5V f=100MHz
Spot Noise Figure	NF			2		-		dB	I _C =30μA V _{CE} =5V R _G =10KΩ f=1kHz BW=100Hz
Average Noise Figure	$\overline{NF}$			3		-		dB	I _C =100μA V _{CE} =5V R _G =10KΩ BW=15.7kHz

TIS97 #2

2-2-BMP