

HITACHI

Electron Tube & Devices

Division, Hitachi, Ltd.

Date : Nov. 21, '95

For Messrs

CUSTOMER'S ACCEPTANCE SPECIFICATIONS

TECHNICAL DATA

TX26D80VC1CAA

CONTENTS

No.	Item	Sheet No.	Page
-	COVER	3284TTD 0431-1	1-1/1
-	RECORD OF REVISION	3284TTD 0431-1	2-1/1
-	APPLICATION	3284TTD 0431-1	3-1/1
1	ABSOLUTE MAXIMUM RATINGS	3284TTD 0431-1	4-1/1
2	OPTICAL CHARACTERISTICS	3284TTD 0431-1	5-1/2~2/2
3	ELECTRICAL CHARACTERISTICS	3284TTD 0431-1	6-1/1
4	BLOCK DIAGRAM	3284TTD 0431-1	7-1/1
5	INTERFACE PIN CONNECTION	3284TTD 0431-1	8-1/2~2/2
6	INTERFACE TIMING	3284TTD 0431-1	9-1/3~3/3
7	DIMENSIONAL OUTLINE	3284TTD 0431-1	10-1/1
8	DESIGNATION OF LOT MARK	3284TTD 0431-1	11-1/1
9	-	-	-
10	PRECAUTION	3284TTD 0431-1	13-1/4~4/4

Electron Tube & Devices Division, Hitachi, Ltd.	Sh. No.	3284TTD 0431-1	Page	1-1/1
--	------------	----------------	------	-------

RECORD OF REVISION

Date	Sheet No.	Summary

Hitachi, Ltd.	Date	Nov. 21, '95	Sh. No.	3284TID 0431-1	Page	2-1/1
---------------	------	--------------	------------	----------------	------	-------

APPLICATIONS

This specification is applied to the following TFT Liquid Crystal Display Module with Back-light unit.

Note : Inverter device for Back-light is not built in so it should be prepared by yourself.

- Type Name : TX26D30VC1CAA
- Display Area : H246×V184.5 [mm]
- Display Dots : H(800×3)×V600 [dots]
(Display Pixels) (H800×V600 pixels)
- Color Pixel Arrangement : R·G·B Vertical Stripe
- Display Mode : Transmissive Mode
Normally White Mode
- Color Number : 262k Colors
- Viewing Angle : 6:00 Direction
- Dimensions Outline : H276.5×V199.0×t8.0 [mm]
- Weight : Less than 500 [g]

Hitachi, Ltd.	Date	Nov. 21, '95	Sh. No.	3284TTD 0431-1	Page	3-1/1
---------------	------	--------------	------------	----------------	------	-------

1. ABSOLUTE MAXIMUM RATINGS

1.1 ENVIRONMENTAL ABSOLUTE MAXIMUM RATINGS

I T E M	O P E R A T I N G		S T O R A G E		U N I T	N o t e
	M I N	M A X	M I N	M A X		
Ambient Temperature	10	40	-20	60	℃	1)
Humidity	2)		2)		%RH	1)
Vibration	-	4.9 (0.5G)	-	19.6 (2G)	m/s ²	3)
Shock	-	29.4 (3G)	-	490 (50G)		4)
Corrosive Gas	NOT ACCEPTABLE		NOT ACCEPTABLE		-	
Illuminance of LCD surface	-	50,000	-	50,000	lx	

Note 1) Environmental temperature and humidity of this unit, not of system installed with this unit.

At low temperature the brightness of CFL drop and the life time of CFL become to be short.

2) Ambient temp. $T_a \leq 40^\circ\text{C}$: 85%RH MAX. Without condensation

$T_a > 40^\circ\text{C}$: Absolute humidity must be lower than the humidity of 85%RH at 40°C . Without condensation

3) 20~50Hz.

4) 7ms.

1.2 ELECTRICAL ABSOLUTE MAXIMUM RATINGS

(1) TFT LIQUID CRYSTAL DISPLAY MODULE

$V_{ss} = 0\text{V}$

I T E M	S Y M B O L	M I N	M A X	U N I T	N O T E
Power Supply Voltage	V_{DD}	0	4.3	V	
Input Voltage	V_i	-0.2	$V_{DD} + 0.2$	V	1)
Electro-static Durability	V_{ESD}	± 100		V	2), 3)
	V_{ESD1}	± 8		kV	2), 4)

Note 1) V_{sync} , H_{sync} , $DTMG$, $DCLK$, RD , GD , BD , are subjected.

2) 200pF~250Ω 25℃~70%RH

3) I/F connector pins are subjected.

4) The surface of Metal bezel and LCD panel are subjected.

(2) BACK-LIGHT UNIT

I T E M	S Y M B O L	M I N	M A X	U N I T
Lamp Current	I_L	0	5	mA
Lamp Voltage	V_L	0	2000	V

Hitachi, Ltd.	Date Nov. 21. '95	Sh. No.	3284TTD 0431-1	Page 4-1/1
---------------	-------------------	---------	----------------	------------

2. OPTICAL CHARACTERISTICS


The following items are measured when the conditions of this unit (TFT panel and Back-light) and measuring systems are stable. The ambient light excluding Back-light is nothing.

• Measuring equipment : TOPCON BM-7, Prichard 1980, or equivalent

Temperature of LCD=25°C, $V_{DD}=3.3V$, $f_v=60Hz$, $I_L=3.5mA$

I T E M		SYMBOL	CONDITION	MIN.	TYP.	MAX.	UNIT	NOTE
Contrast Ratio		CR	$\theta=0^\circ$ Note 1)	30	80	—	—	2)
Response Time	RISE	tr		—	35	90	ms	3)
	FALL	tf		—	20	60		
Brightness (white)		Twh		—	70	—	cd/m ²	
Color of CIE	Red	x		—	(0.58)	—	—	
		y			(0.34)			
	Green	x		—	(0.30)			
		y			(0.54)			
	Blue	x		—	(0.15)			
		y			(0.13)			
	White	x		—	(0.31)			
		y			(0.32)			

Note 1) Definition of Viewing Angle




Hitachi, Ltd.	Date	Nov. 21. '95	Sh. No.	3284TTD 0431-1	Page	5-1/2
---------------	------	--------------	---------	----------------	------	-------

Note 2) Definition of Contrast Ratio (CR)

$$CR = \frac{\text{Brightness when displaying White raster}}{\text{Brightness when displaying Black raster}}$$

Note 3) Definition of Response Time



3. ELECTRICAL CHARACTERISTICS


(1) TFT LIQUID CRYSTAL DISPLAY MODULE

$T_a=25^\circ\text{C}$, $V_{gs}=0\text{V}$

ITEM	SYMBOL	MIN.	TYP.	MAX.	UNIT	NOTE
Power Supply Voltage	V_{DD}	3.0	3.3	3.6	V	
Input Voltage for Logic Circuits	Hi	V_{IH}	$0.75 \times V_{DD}$	V_{DD}	V	1)
	Lo	V_{IL}	V_{gs}	$0.25 \times V_{DD}$		
Power Supply Current	I_{DD}	—	190	370	mA	2), 3)
Vsync Frequency	f_v	—	60	65	Hz	
Hsync Frequency	f_H	—	37.5	39.2	kHz	
DCLK Frequency	f_{CLK}	—	38.4	40	MHz	

Note 1) Display data pins and Timing signal pins are subjected.

2) $f_v=60\text{Hz}$, $f_{CLK}=36\text{MHz}$, $V_{DD}=3.3\text{V}$, DC Current



Typical value is measured when displaying Black raster.

Maximum is measured when displaying Pixel-checkers.

3) Current capacity for V_{DD} power source should be larger than 3A

(2) BACK-LIGHT UNIT

$T_a=25^\circ\text{C}$

ITEM	SYMBOL	MIN.	TYP.	MAX.	UNIT	NOTE
Lamp Current	I_L	2.0	3.5	5.0	mA _{rms}	1)
		—	—	7.0	mA _{0-peak}	
Lamp Voltage	V_L	—	595	660	V _{rms}	
Frequency	f_L	—	50	—	kHz	2)
Starting Lamp Voltage	V_s	—	—	930	V _{rms}	3)
		—	—	1620		

Note 1) Higher I_L cause the short life time of CFL.

2) Lamp frequency may produce interference with Hsync frequency, causing beat or flicker on the display. Therefore lamp frequency shall be as different as possible from Hsync frequency, to avoid interference.


3) $T_a=0^\circ\text{C}$

4) Regarding output voltage of transformer on inverter circuit, when output is open, more than 1700V is recommended.


Hitachi, Ltd.	Date Nov. 21. '95	Sh. No.	3284TTD 0431-1	Page 6-1/1
---------------	-------------------	---------	----------------	------------

4. BLOCK DIAGRAM

(1) TFT LIQUID CRYSTAL DISPLAY MODULE



(2) BACK-LIGHT UNIT



Hitachi, Ltd.	Date	Nov. 21, '95	Sh. No.	3284TTD 0431-1	Page	7-1/1
---------------	------	--------------	------------	----------------	------	-------

5. INTERFACE PIN ASSIGNMENT

(1) TFT LIQUID CRYSTAL DISPLAY MODULE CN1 (HIROSE:DF9B-41P-1V)

Pin No	SYMBOL	DESCRIPTION	NOTE
1	Vss	GND (0V)	1)
2	DCLK	Dot Clock	
3	Vss	GND (0V)	1)
4	Hsync	Horizontal Synchronization	
5	Vsync	Vertical Synchronization	
6	Vss		1)
7	Vss	GND (0V)	
8	Vss		
9	R0		
10	R1	Red Data	
11	R2		
12	Vss	GND (0V)	1)
13	R3		
14	R4	Red Data	
15	R5		
16	Vss		1)
17	Vss	GND (0V)	
18	Vss		
19	G0		
20	G1	Green Data	
21	G2		
22	Vss	GND (0V)	1)
23	G3		
24	G4	Green Data	
25	G5		
26	Vss		1)
27	Vss	GND (0V)	
28	Vss		
29	B0		
30	B1	Blue Data	
31	B2		
32	Vss	GND (0V)	1)
33	B3		
34	B4	Blue Data	
35	B5		
36	Vss	GND (0V)	1)
37	DTMG	Display Timing	
38	VSS	GND (0V)	
39	Vss	Power Supply (+3.3V)	2)
40	Vss		
41	(IC)		3)

- Note 1) All Vss pins should be connected to GND (0V).
Metal bezel is connected internally to Vss.
2) All Vss pins should be connected to +3.3V.
3) Keep open. Hitachi test use only.

(2) BACK-LIGHT UNIT CN2 (JST:BHR-03VS-1)

Pin No.	SYMBOL	DESCRIPTION
1	V _L	Power Supply
2	(NC)	
3	GND	GND (0V)

Hitachi, Ltd.	Date	Nov. 21. '95	Sh. No.	3284TTD 0431-1	Page	8-1/
---------------	------	--------------	------------	----------------	------	------

RELATIONSHIP BETWEEN DISPLAYED COLOR AND INPUT DATA

INPUT DATA		R DATA					G DATA					B DATA							
		R5	R4	R3	R2	R1	R0	G5	G4	G3	G2	G1	G0	B5	B4	B3	B2	B1	B0
		MSB					LSE	MSB					LSE	MSB					LSE
COLOR																			
BASIC COLOR	BLACK	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	RED (0)	1	1	1	1	1	1	0	0	0	0	0	0	0	0	0	0	0	0
	GREEN (0)	0	0	0	0	0	0	1	1	1	1	1	1	0	0	0	0	0	0
	BLUE (0)	0	0	0	0	0	0	0	0	0	0	0	0	1	1	1	1	1	1
	CYAN	0	0	0	0	0	0	1	1	1	1	1	1	1	1	1	1	1	1
	MAGENTA	1	1	1	1	1	1	0	0	0	0	0	0	1	1	1	1	1	1
	YELLOW	1	1	1	1	1	1	1	1	1	1	1	1	0	0	0	0	0	0
	WHITE	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1
RED	BLACK	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	RED (62)	0	0	0	0	0	1	0	0	0	0	0	0	0	0	0	0	0	0
	RED (61)	0	0	0	0	1	0	0	0	0	0	0	0	0	0	0	0	0	0
	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:
	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:
	RED (2)	1	1	1	1	0	1	0	0	0	0	0	0	0	0	0	0	0	0
	RED (1)	1	1	1	1	1	0	0	0	0	0	0	0	0	0	0	0	0	0
	RED (0)	1	1	1	1	1	1	0	0	0	0	0	0	0	0	0	0	0	0
GREEN	BLACK	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	GREEN (62)	0	0	0	0	0	0	0	0	0	0	0	1	0	0	0	0	0	0
	GREEN (61)	0	0	0	0	0	0	0	0	0	0	1	0	0	0	0	0	0	0
	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:
	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:
	GREEN (2)	0	0	0	0	0	0	1	1	1	1	0	1	0	0	0	0	0	0
	GREEN (1)	0	0	0	0	0	0	1	1	1	1	1	0	0	0	0	0	0	0
	GREEN (0)	0	0	0	0	0	0	1	1	1	1	1	1	0	0	0	0	0	0
BLUE	BLACK	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	BLUE (62)	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	1
	BLUE (61)	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	1	0
	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:
	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:
	BLUE (2)	0	0	0	0	0	0	0	0	0	0	0	0	1	1	1	1	0	1
	BLUE (1)	0	0	0	0	0	0	0	0	0	0	0	0	1	1	1	1	1	0
	BLUE (0)	0	0	0	0	0	0	0	0	0	0	0	0	1	1	1	1	1	1

Note 1) Definition of gray scale :

Color (n) --- n indicates gray scale level. Lower n means brighter level.


2) Data : 1:Hi, 0:Lo

Hitachi, Ltd.	Date Nov. 21, '95	Sh. No.	3284TTD 0431-1	Page 8-2/2
---------------	-------------------	---------	----------------	------------

6. INTERFACE TIMING

6.1 TIMING CHART


① Data : Latched at Fall edge of DCLK



6.2 INTERFACE TIMING SPECIFICATION

I T E M		SYMBOL	MIN	TYP.	MAX.	UNIT	NOTE
DCLK	Period	t_{clk}	25	(26)	—	ns	
	Width-Low	t_{wcl}	8	—	—		
	Width-High	t_{wch}	8	—	—		
	Rise Time	t_{rclk}	—	—	25		
	Fall Time	t_{fclk}	—	—	25		
	Duty	D	0.45	0.5	0.55	—	$D=t_{wchl}/t_{clk}$
Hsync	Set up Time	t_{sh}	6	—	—	ns	for DCLK
	Hold Time	t_{hh}	6	—	—		
	Period	t_{hp}	$1052-t_{hsp}$	(1024)	1200	t_{clk}	
	Width-Active	t_{wh}	8	—	120		
	Rise/Fall Time	t_{hr}, t_{fr}	—	—	30	ns	
Vsync	Set up Time	t_{sv}	0	—	—	t_{clk}	for Hsync
	Hold Time	t_{hv}	2	—	—		
	Period	t_{vp}	603	(625)	1000	t_{hp}	
	Width-Active	t_{vh}	1	—	24		
	Rise/Fall Time	t_{vr}, t_{vr}	—	—	50	ns	
DTMG	Set up Time	t_{si}	6	—	—	ns	for DCLK
	Hold Time	t_{hi}	6	—	—		
	Rise/Fall Time	t_{ir}, t_{if}	—	—	30	ns	
	Horizontal Back Porch	t_{hbp}	32	—	—	t_{clk}	
	Horizontal Front Porch	t_{hfp}	16	—	—		
	Vertical Back Porch	t_{vbp}	0	—	—	t_{hp}	
	Vertical Front Porch	t_{vfp}	3	—	—		
DATA	Set up Time	t_{so}	6	—	—	ns	for DCLK
	Hold Time	t_{ho}	6	—	—		
	Rise/Fall Time	t_{sr}, t_{sf}	—	—	25	ns	

6.3 TIMING BETWEEN INTERFACE SIGNAL AND POWER SUPPLY




* Set $0V \leq V_i(t) \leq V_{DD}(t)$.

Here, $V_i(t)$, $V_{DD}(t)$ indicate the transitive state of V_i , V_{DD} when power supply is turned ON or OFF.

NOTE 1) Do not keep interface signal high-impedance when power on.

Hitachi, Ltd.	Date Nov. 21, '95	Sh. No.	3284TTD 0431-1	Page 9-3/3
---------------	-------------------	---------	----------------	------------

7. DIMENSIONAL OUTLINE




Note

- 1) CN1 : Hirose DF9B-41P-1V
(Mating side connector)
DF9*-41S-1V
- 2) CN2 : J. S. T. BHR-03VS-1
Cable length is about
50mm.
(Mating side connector)
SMO2 (8. 0) B-BHS-TB
- 3) Tolerance not specified is $\pm 0.5\text{mm}$.
- 4) Dimensions in parenthesis are
reference value.
- 5) Position, size and form of tab
and grooves on Metal bezel are
not specified.

8. DESIGNATION OF LOT MARK

8.1 LOT MARK



NOTE 1) Optional Mark for HITACHI.

2) Year

Year	'95	'96	'97	'98	'99	2000	'01	'02	'03	'04	'05
Mark	5	6	7	8	9	0	1	2	3	4	5

3) Month

Month	Jan.	Feb.	Mar.	Apr.	May	June	July	Aug.	Sept.	Oct.	Nov.	Dec.
Mark	A	B	C	D	E	F	G	H	J	K	L	M


8.2 LOCATION OF LOT MARK

Lot mark is printed on Label. And Label is attached to the surface of Metal bezel.

The form of character will be changed without notice.

8. DESIGNATION OF LOT MARK

8.1 LOT MARK



NOTE 1) Optional Mark for HITACHI.

2) Year

Year	'95	'96	'97	'98	'99	2000	'01	'02	'03	'04	'05
Mark	5	6	7	8	9	0	1	2	3	4	5

3) Month

Month	Jan.	Feb.	Mar.	Apr.	May	June	July	Aug.	Sept.	Oct.	Nov.	Dec.
Mark	A	B	C	D	E	F	G	H	J	K	L	M

8.2 LOCATION OF LOT MARK

Lot mark is printed on Label. And Label is attached to the surface of Metal bezel.

The form of character will be changed without notice.

10.2 OPERATING PRECAUTION

- (1) The spike noise causes the mis-operation of circuits. Be lower the spike noise as follows :

$V_{os} = \pm 200\text{mV}$, $V_i = \pm 200\text{mV}$ (Over and under shoot voltage)

- (2) Response time depends on the temperature. (In lower temperature, it becomes longer).

And also Transmittance and Color depend on the temperature.

- (3) Brightness depends on the temperature. (In lower temperature, it becomes lower).

And in lower temperature, response time (required time that brightness is stable after turn on) becomes longer.

- (4) Be carefull for condensation at sudden temperature change.

Condensation make damage to polarizer or electrical contact part. And after fading condensation, smear or spot will occur.

- (5) When fixed patterns are displayed at long times, afterimage is likely to occur.

- (6) Module has high frequency circuit. If you need to shield the electromagnetic noise, please do in yours.

- (7) When Back-light unit is operating, it sounds.

If you need to shield the noise, please do in yours.

- (8) Please connect the Back-light connector to the inverter circuit directly.

The long cable between CFL and the inverter may cause the brightness drop of CFL and may cause the rise of starting lamp Voltage (V_s).

- (9) Do not connect or remove the module from main system with power applied.

10.3 ELECTROSTATIC DISCHARGE CONTROL

Since Module is composed with electronic circuit, it is not strong to electrostatic discharge. Make certain that treatment persons are connected to ground through list band etc.. And don't touch I/F pin directly.

10.4 PRECAUTION FOR STRONG LIGHT EXPOSURE

Strong light exposure causes degradation of polarizer and color filter.

Hitachi, Ltd.	Date	Nov. 21, '95	Sh. No.	3284TTD 0431-1	Page	13-2/4
---------------	------	--------------	------------	----------------	------	--------

10. 5 STORAGE

When storing Module as spares for long time, the following precautions are necessary.

- (1) Store them in a dark place ; do not expose them to sunlight or fluorescent light.

Keep the temperature between 5°C and 35°C at normal humidity.

- (2) The polarizer surface should not come in contact with any other object.

It is recommended that they be stored in the container in which they were shipped.

10. 6 HANDLING PRECAUTIONS FOR PROTECTION FILM

- (1) When the protection film is peeled off, static electricity is generated between the film and the polarizer.

This film should be peeled off slowly and carefully by people who are electrically grounded and with well ion-blown equipment or in such a condition, etc.

- (2) The protection film is attached to the polarizer with a small amount of glue. If some stress is applied to rub the protection film against the polarizer during the time you peel off the film, the glue is apt to remain more on the polarizer. So please carefully peel off the protection film without rubbing it against the polarizer.

- (3) When the Module with protection film attached is stored for long time, sometimes there remains a very small amount of glue, still on the polarizer after the protection film is peeled off.

Please refrain from storing the Module at the high temperature and high humidity for glue is apt to remain in these condition.

- (4) The Glue may be taken for the Modules failure, but you can remove the Glue easily.

When the glue remains on the polarizer surface or its vestige is recognized, please wipe them off with absorbent cotton waste or other soft material like chamois soaked with Normal-hexane.

Hitachi, Ltd.	Date	Nov. 21, '95	Sh. No.	3284TTD 0431-1	Page	13-3/4
---------------	------	--------------	------------	----------------	------	--------

10. 7 SAFETY

- (1) If Module is broken, be careful to handle not to injure. (TFT/LCD and Lamp are made of glass.)
Please wash hands sufficiently when you touch the liquid crystal coming out from broken LCDs.
- (2) As it is possible for PCB or other electronic parts of module to smell to smoke and to take fire because of the short circuit.
Please design the circuit of your instrument not to flow the electric current to TFT/LCD module more than 1A (by apply the fuse for example).
- (3) As Back-light unit has high voltage circuit internal, do not open the case and do not insert foreign materials in the case.

Hitachi, Ltd.	Date	Nov. 21, '95	Sh. No.	3284TTD 0431-1	Page	13-4/4
---------------	------	--------------	------------	----------------	------	--------