

STRUCTURE Silicon Monolithic Integrated Circuit

PRODUCT NAME IC for DC—AC inverter control

 TYPE **BD9241F**

 FUNCTION

1. For 36V high voltage process/ 1 ch Full Bridge control
2. Current, voltage feedback control
3. Built-in soft start circuit
4. Built-in timer-latch circuit
5. Built-in the malfunction preventing circuit (UVLO) when lower voltage
6. Shifting to current consumption save mode from STB terminal
7. External PWM,DC voltage control and current linear control

ABSOLUTE MAXIMUM RATINGS ($T_a = 25^{\circ}\text{C}$)

Parameter	Symbol	Rating	Unit
Power Supply Voltage	VCC	36	V
Operating Temperature Range	Topr	-40~+85	°C
Storage Temperature Range	Tstg	-55~+150	°C
allowable loss	Pd	687*	mW
Junction Temperature	Tjmax	+150	°C

*Reduced by 5.5mW/°C when Ta=25°C or over (when 70.0mm×70.0mm×1.6mm board is mounting)

OPERATING Range


Parameter	Symbol	Range	Unit
Power Supply Voltage	VCC	9~30	V
Terminal Voltage (SRT,RT,VS,IS,COMP,DUTY)	-	-0.3~5.5	V
Drive output frequency	fOUT	30~90	kHz
BCT oscillation frequency	fBCT	0.10~0.50	kHz

OELECTRICAL CHARACTERISTICS (Ta=25°C, VCC=15V)


Parameter	Symbol	Rating			Unit	Condition
		MIN	Standard	MAX		
((devices whole))						
Circuit Current at operating	ICC1	—	2.3	5.0	mA	
Circuit Current when standby	ICC2	—	0	10	μA	
((Standby control, SEL control))						
Standby Terminal voltage H	VstH	2.0	—	VCC	V	System ○ N
Standby Terminal voltage L	VstL	-0.3	—	0.8	V	System ○ F F
SEL Terminal voltage H	VSELH	2.4	—	VCC	V	DUTY Terminal : 0.5V→2.0V Burst dimming : 100%→0%
SEL Terminal voltage L	VSELL	-0.3	—	0.8	V	DUTY Terminal : 0.5V→2.0V Burst dimming : 0%→100%
((Timer—Latch))						
Voltage setting time	VCP	1.9	2.0	2.1	V	
Current setting time	ICP	0.85	1.0	1.15	μA	
((O S C Block))						
Active edge setting current	Iact	1.25/RT	1.5/RT	1.75/RT	A	
MAX DUTY	MAXDUTY	44	46.4	49	%	RT=100kΩ
Soft start time	TSS	50	100	150	msec	
SRT Terminal ON Resistant	RSRT	—	100	200	Ω	
((U V L OBLOCK))						
Voltage starting operation	VuvloH	6	7	8	V	
Hysteresis width	ΔVuvloH	0.15	0.3	0.6	V	
((Feedback system))						
IS Threshold voltage	VIS	1.225	1.250	1.275	V	
VS Threshold voltage	VVS	1.210	1.250	1.290	V	
IS Source current1	IIS1	—	—	0.9	μA	DUTY=2.0V
IS Source current 2	IIS2	40	50	60	μA	DUTY=0V、IS=0.5V
VS Source current	IVS	—	—	1.0	μA	
ISCOMP Detecting voltage	VISC	0.45	0.50	0.55	V	
((Output block))						
P 1, P 2 Output voltage H	VOUTPH	VCC-0.3	VCC	—	V	
P 1, P 2 Output voltage L	VOUTPL	VCC-10.3	VCC-9.3	VCC-8.3	V	
N 1, N 2 Output voltage H	VOUTNH	8.3	9.3	10.3	V	
N 1, N 2 Output voltage L	VOUTNL	—	0	0.3	V	
P 1, P 2 Output sink resistance	RsinkP1,2	—	3	10	Ω	Isink=10mA
P 1, P 2 Output source resistance	R source P1,2	—	6	12	Ω	Isource=10mA
N 1, N 2 Output sink resistance	RsinkN1,2	—	4	10	Ω	Isink=10mA
N 1, N 2 Output source resistance	RsourceN1,2	—	6	12	Ω	Isource=10mA
Drive output frequency	FOUT	48.5	50	51.5	kHz	RT=100kΩ
((Burst mode setting block))						
Triangular wave upper voltage	VburH	1.9	2.0	2.1	V	
Triangular wave lower voltage	VburL	0.4	0.5	0.6	V	
Triangular wave frequency	FBOSC	337	350	363	Hz	BCT=4700pF
((COMP Block))						
Over-voltage detecting voltage	VCOMPH	1.9	2.00	2.1	V	
Hysteresis width	VCOMP	0.1	0.2	0.4	V	

www.DataSheet4U.com (It is not the radiation-proof design for this product.)

○Dimensional outline drawing



○ Block diagram



○Terminal description

Terminal No	Terminal name	Function
1	N2	External FET drive circuit output terminal
2	P2	External FET drive circuit output terminal
3	VCC	Power terminal
4	SEL	Dimming(POS,NEG)select terminal
5	CP	Timer — latch setting capacity connection terminal
6	GND	GROUND
7	SRT	Connecting terminal for charging and discharging current setting resistance of OSC block
8	RT	Connecting terminal for charging and discharging current setting resistance of OSC block
9	VS	Error amplifier input terminal②
10	IS	Error amplifier input terminal①
11	FB	Error amplifier output terminal
12	COMP	Over-voltage detecting terminal
13	BCT	Connecting terminal for charging and discharging current setting capacity of BOSC block.
14	DUTY	Switching terminal of PWM mode and burst mode
15	STB	Standby switch terminal
16	PGND	External FET drive circuit GND terminal
17	P1	External FET drive circuit output terminal
18	N1	External FET drive circuit output terminal

○ Usage notes

1. About the absolute maximum ratings

The damage may occur If absolute maximum rating such as applied voltage and operating temperature range etc. is exceeded, moreover such destructive conditions as short mode or open mode etc. can not be assumed, so If a particular mode such as exceeding the absolute maximum rating is assumed, please consider taking physical safety measures such as fuse etc.

2. As long as being operation range, the operation of circuit function will be assured in the range of operating ambient temperature. About characteristic value, the specification value of electric characteristic can't be guaranteed, but the characteristic value doesn't change rapidly in these ranges.

3. When attaching to the printed substrate, pay special attention to the direction and proper placement of the IC. If the IC is attached incorrectly, it may be destroyed. Destruction can also occur when there is a short, which can be caused by foreign objects entering between outputs or an output and the power GND.

4. Please be careful that there is a possibility of malfunction which is happening when you use it in a strong electromagnetic field.

5. The potential of GND terminal and PGND terminal is used with not over $\pm 0.3V$ please.

6. This IC has a built-in Temperature Protection Circuit (TSD circuit). The temperature protection circuit (TSD circuit) is only to cut off the IC from thermal runaway, and has not been designed to protect or compensate the IC. Therefore, the user should not plan to activate this circuit with continued operation in mind.

7. Although the quality of this product has been tightly controlled, the damage may occur If absolute maximum rating such as applied voltage and operating temperature range etc. is exceeded, moreover such destructive conditions as short mode or open mode etc. can not be assumed, so If a particular mode such as exceeding the absolute maximum rating is assumed, please consider taking a measures such as fuse etc.

8. Regarding the external FET, since gate voltage will be changed regarding parasitic capacity between drain gates while switching the drain voltage, please think over dispersion etc of our company's IC, please select FET with sufficient margin.

9. CP timer does not operate during the time of soft start.

10. To prevent the destruction from external static electricity, please give resistance to the pin which directly link with connector etc.

11. This IC is a monolithic IC, and between each element there is a P+ isolation and P substrate for element separation. There is a P-N junction and other parasitic elements formed between this P-layer and each element's N-layer, as shown in Fig. when the resistors and transistors are connected to the terminal,

- When GND > (terminal A) at the resistance, or GND > (terminal B) at the transistor (NPN), the P-N junction operates as a parasitic diode.

- Also, when GND > (terminal B) at the transistor, a parasitic NPN transistor operates by the N-layer of other elements which close to the aforementioned parasitic diode.

With the IC's configuration, the production of parasitic elements by the relationships of the electrical potentials is inevitable. The operation of the parasitic elements can also interfere with the circuit operation, leading to malfunction and even destruction. Therefore, uses which cause the parasitic elements to operate, such as applying voltage to the input terminal which is lower than the GND (P-substrate), should be avoided.




Fig.1 Simple Structure of Monolithic IC

Notes

No copying or reproduction of this document, in part or in whole, is permitted without the consent of ROHM Co.,Ltd.

The content specified herein is subject to change for improvement without notice.

The content specified herein is for the purpose of introducing ROHM's products (hereinafter "Products"). If you wish to use any such Product, please be sure to refer to the specifications, which can be obtained from ROHM upon request.

Examples of application circuits, circuit constants and any other information contained herein illustrate the standard usage and operations of the Products. The peripheral conditions must be taken into account when designing circuits for mass production.

Great care was taken in ensuring the accuracy of the information specified in this document. However, should you incur any damage arising from any inaccuracy or misprint of such information, ROHM shall bear no responsibility for such damage.

The technical information specified herein is intended only to show the typical functions of and examples of application circuits for the Products. ROHM does not grant you, explicitly or implicitly, any license to use or exercise intellectual property or other rights held by ROHM and other parties. ROHM shall bear no responsibility whatsoever for any dispute arising from the use of such technical information.

The Products specified in this document are intended to be used with general-use electronic equipment or devices (such as audio visual equipment, office-automation equipment, communication devices, electronic appliances and amusement devices).

The Products specified in this document are not designed to be radiation tolerant.

While ROHM always makes efforts to enhance the quality and reliability of its Products, a Product may fail or malfunction for a variety of reasons.

Please be sure to implement in your equipment using the Products safety measures to guard against the possibility of physical injury, fire or any other damage caused in the event of the failure of any Product, such as derating, redundancy, fire control and fail-safe designs. ROHM shall bear no responsibility whatsoever for your use of any Product outside of the prescribed scope or not in accordance with the instruction manual.

The Products are not designed or manufactured to be used with any equipment, device or system which requires an extremely high level of reliability the failure or malfunction of which may result in a direct threat to human life or create a risk of human injury (such as a medical instrument, transportation equipment, aerospace machinery, nuclear-reactor controller, fuel-controller or other safety device). ROHM shall bear no responsibility in any way for use of any of the Products for the above special purposes. If a Product is intended to be used for any such special purpose, please contact a ROHM sales representative before purchasing.

If you intend to export or ship overseas any Product or technology specified herein that may be controlled under the Foreign Exchange and the Foreign Trade Law, you will be required to obtain a license or permit under the Law.