

## DUAL LOW VOLTAGE POWER AMPLIFIER


### ■ GENERAL DESCRIPTION

The NJM2073 is a monolithic integrated circuit in 8 lead dual-in-line package, which is designed for dual audio power amplifier in portable radio and handy cassette player.

### ■ FEATURES

- Operating Voltage (  $V^+ = 1.8V \sim 15V$  )
- Low Crossover Distortion
- Low Operating Current
- Bridge or Stereo Configuration
- No Turn-on Noise
- Package Outline DIP8, DMP8
- Bipolar Technology

### ■ PACKAGE OUTLINE




NJM2073D



NJM2073M

### ■ PIN CONFIGURATION



## ■ ABSOLUTE MAXIMUM RATINGS

( Ta=25°C )

| PARAMETER                   | SYMBOL    | RATINGS                      | UNIT |
|-----------------------------|-----------|------------------------------|------|
| Supply Voltage              | $V^+$     | 15                           | V    |
| Output Peak Current         | $I_{OP}$  | 1                            | A    |
| Power Dissipation           | $P_D$     | ( DIP8 ) 700<br>( DMP8 ) 300 | mW   |
| Input Voltage Range         | $V_{IN}$  | $\pm 0.4$                    | V    |
| Operating Temperature Range | $T_{opr}$ | -40~+85                      | °C   |
| Storage Temperature Range   | $T_{stg}$ | -40~+125                     | °C   |

## ■ ELECTRICAL CHARACTERISTICS D-Type

(1) BTL Configuration ( Test Circuit Fig.1 )

(  $V^+=6V, Ta=25^\circ C$  )

| PARAMETER                                        | SYMBOL       | TEST CONDITION                                | MIN. | TYP. | MAX. | UNIT       |
|--------------------------------------------------|--------------|-----------------------------------------------|------|------|------|------------|
| Operating Voltage                                | $V^+$        |                                               | 1.8  | -    | 15   | V          |
| Operating Current                                | $I_{CC}$     | $R_L = \infty$                                | -    | 6    | 9    | mA         |
| Output Offset Voltage<br>( Between the Outputs ) | $\Delta V_O$ | $R_L = 8\Omega$                               | -    | 10   | 50   | mV         |
| Input Bias Current                               | $I_B$        |                                               | -    | 100  | -    | nA         |
| Output Power                                     | $P_O$        | THD=10%, f=1kHz                               | -    | 2.0  | -    | W          |
|                                                  | $P_O$        | $V^+=9V, R_L=16\Omega$ ( Note )               | 0.9  | 1.2  | -    | W          |
|                                                  | $P_O$        | $V^+=6V, R_L=8\Omega$ ( Note )                | -    | 0.6  | -    | W          |
|                                                  | $P_O$        | $V^+=4.5V, R_L=8\Omega$                       | -    | 0.8  | -    | W          |
|                                                  | $P_O$        | $V^+=4.5V, R_L=4\Omega$ ( Note )              | 200  | 300  | -    | mW         |
|                                                  | $P_O$        | $V^+=3V, R_L=4\Omega$                         | -    | 80   | -    | mW         |
|                                                  | $P_O$        | $V^+=2V, R_L=4\Omega$                         | -    | -    | -    | -          |
|                                                  | $P_O$        | THD=1%, f=40Hz~15kHz                          | -    | 1.0  | -    | W          |
|                                                  | $P_O$        | $V^+=6V, R_L=8\Omega$                         | -    | 0.6  | -    | W          |
|                                                  | $P_O$        | $V^+=4.5V, R_L=4\Omega$                       | -    | 0.2  | -    | %          |
| Total Harmonic Distortion                        | THD          | $P_O=0.5W, R_L=8\Omega, f=1kHz$               | -    | 44   | 47   | dB         |
| Close Loop Voltage Gain                          | $A_V$        | f=1kHz                                        | 41   | -    | -    | k $\Omega$ |
| Input Impedance                                  | $Z_{IN}$     | f=1kHz                                        | 100  | -    | -    | $\mu V$    |
| Equivalent Input Noise Voltage                   | $V_{NI1}$    | $R_S=10k\Omega, A$ Curve                      | -    | 2    | -    | $\mu V$    |
|                                                  | $V_{NI2}$    | $R_S=10k\Omega, B=22Hz\sim 22kHz$             | -    | 2.5  | -    | dB         |
| Ripple Rejection                                 | RR           | f=100Hz                                       | -    | 40   | -    | kHz        |
| Cutoff Frequency                                 | $f_H$        | $A_V=-3dB$ from f=1kHz, $R_L=8\Omega, P_O=1W$ | -    | 130  | -    | -          |

( Note ) At on PC Board

## (2) Stereo Configuration ( Test Circuit Fig.2 )

| PARAMETER                      | SYMBOL       | TEST CONDITION                                   | MIN. | TYP. | MAX.    | UNIT       |
|--------------------------------|--------------|--------------------------------------------------|------|------|---------|------------|
| Operating Voltage              | $V^+$        |                                                  | 1.8  | -    | 15      | V          |
| Output Voltage                 | $V_O$        |                                                  | -    | 2.7  | -       | V          |
| Operating Current              | $I_{CC}$     | $R_L = \infty$                                   | -    | 6    | 9       | mA         |
| Input Bias Current             | $I_B$        |                                                  | -    | 100  | -       | nA         |
| Output Power ( Each Channel )  |              | THD=10%, f=1kHz                                  |      |      |         |            |
|                                | $P_O$        | $V^+=6V, R_L=4\Omega$ ( Note )                   | 0.5  | 0.65 | -       | W          |
|                                | $P_O$        | $V^+=4.5V, R_L=4\Omega$                          | -    | 0.32 | -       | W          |
|                                | $P_O$        | $V^+=3V, R_L=4\Omega$                            | -    | 120  | -       | mW         |
|                                | $P_O$        | $V^+=2V, R_L=4\Omega$                            | -    | 30   | -       | mW         |
|                                |              | THD=1%, f=1kHz                                   |      |      |         |            |
|                                | $P_O$        | $V^+=6V, R_L=4\Omega$                            | -    | 500  | -       | mW         |
|                                | $P_O$        | $V^+=4.5V, R_L=4\Omega$                          | -    | 250  | -       | mW         |
| Total Harmonic Distortion      | THD          | $P_O=0.4W, R_L=4\Omega, f=1kHz$                  | -    | 0.25 | -       | %          |
| Voltage Gain                   | $A_V$        | f=1kHz                                           | 41   | 44   | 47      | dB         |
| Channel Balance                | $\Delta A_V$ |                                                  | -    | -    | $\pm 1$ | dB         |
| Input Impedance                | $Z_{IN}$     | f=1kHz                                           | 100  | -    | -       | k $\Omega$ |
| Equivalent Input Noise Voltage | $V_{NI1}$    | $R_S=10k\Omega, A$ Curve                         | -    | 2.5  | -       | $\mu V$    |
|                                | $V_{NI2}$    | $R_S=10k\Omega, B=22Hz\sim 22kHz$                | -    | 3    | -       | $\mu V$    |
| Ripple Rejection               | RR           | f=100Hz, $C_X=100\mu F$                          | 24   | 30   | -       | dB         |
| Cutoff Frequency               | $f_H$        | $A_V=-3dB$ from f=1kHz, $R_L=8\Omega, P_O=250mW$ | -    | 200  | -       | kHz        |

( Note ) At on PC Board

## ■ ELECTRICAL CHARACTERISTICS M-Type

### (1) BTL Configuration ( Test Circuit Fig.1 )

(  $V^+=6V, T_a=25^\circ C$  )

| PARAMETER                      | SYMBOL       | TEST CONDITION                                   | MIN. | TYP. | MAX. | UNIT       |
|--------------------------------|--------------|--------------------------------------------------|------|------|------|------------|
| Operating Voltage              | $V^+$        |                                                  | 1.8  | -    | 15   | V          |
| Operating Current              | $I_{CC}$     | $R_L = \infty$                                   | -    | 6    | 9    | mA         |
| Output Offset Voltage          | $\Delta V_O$ | $R_L=8\Omega$                                    | -    | 10   | 50   | mV         |
| ( Between the Outputs )        |              |                                                  |      |      |      |            |
| Input Bias Current             | $I_B$        |                                                  | -    | 100  | -    | nA         |
| Output Power                   |              | THD=10%, f=1kHz                                  |      |      |      |            |
|                                | $P_O$        | $V^+=6V, R_L=16\Omega$ ( Note )                  | -    | 0.8  | -    | W          |
|                                | $P_O$        | $V^+=4V, R_L=8\Omega$ ( Note )                   | 350  | 460  | -    | mW         |
|                                | $P_O$        | $V^+=3V, R_L=4\Omega$ ( Note )                   | 200  | 300  | -    | mW         |
|                                | $P_O$        | $V^+=2V, R_L=4\Omega$                            | -    | 80   | -    | mW         |
|                                |              | THD=1%, f=40Hz~15kHz                             |      |      |      |            |
|                                | $P_O$        | $V^+=4V, R_L=8\Omega$                            | -    | 380  | -    | mW         |
| Total Harmonic Distortion      | THD          | $V^+=4V, R_L=8\Omega, P_O=200mW, f=1kHz$         | -    | 0.2  | -    | %          |
| Close Loop Voltage Gain        | $A_V$        | f=1kHz                                           | 41   | 44   | 47   | dB         |
| Input Impedance                | $Z_{IN}$     | f=1kHz                                           | 100  | -    | -    | k $\Omega$ |
| Equivalent Input Noise Voltage | $V_{NI1}$    | $R_S=10k\Omega, A$ Curve                         | -    | 2    | -    | $\mu V$    |
|                                | $V_{NI2}$    | $R_S=10k\Omega, B=22Hz\sim 22kHz$                | -    | 2.5  | -    | $\mu V$    |
| Ripple Rejection               | RR           | f=100Hz                                          | -    | 40   | -    | dB         |
| Cutoff Frequency               | $f_H$        | $A_V=-3dB$ from f=1kHz, $R_L=16\Omega, P_O=0.5W$ | -    | 130  | -    | kHz        |

( Note ) At on PC Board


## (2) Stereo Configuration ( Test Circuit Fig.2 )

| PARAMETER                      | SYMBOL       | TEST CONDITION                                    | MIN. | TYP. | MAX.    | UNIT       |
|--------------------------------|--------------|---------------------------------------------------|------|------|---------|------------|
| Operating Voltage              | $V^+$        |                                                   | 1.8  | -    | 15      | V          |
| Output Voltage                 | $V_O$        |                                                   | -    | 2.7  | -       | V          |
| Operating Current              | $I_{CC}$     | $R_L = \infty$                                    | -    | 6    | 9       | mA         |
| Input Bias Current             | $I_B$        |                                                   | -    | 100  | -       | nA         |
| Output Power ( Each Channel )  | $P_O$        | THD=10%, f=1kHz<br>$V^+=6V, R_L=16\Omega$         | -    | 240  | -       | mW         |
|                                | $P_O$        | $V^+=5V, R_L=8\Omega$ ( Note )                    | -    | 270  | -       | mW         |
|                                | $P_O$        | $V^+=4V, R_L=4\Omega$ ( Note )                    | 180  | 250  | -       | mW         |
|                                | $P_O$        | $V^+=3V, R_L=4\Omega$                             | -    | 120  | -       | mW         |
|                                | $P_O$        | $V^+=2V, R_L=4\Omega$                             | -    | 30   | -       | mW         |
|                                | $P_O$        | THD=1%, f=1kHz<br>$V^+=4V, R_L=4\Omega$           | -    | 180  | -       | mW         |
| Total Harmonic Distortion      | THD          | $V^+=4V, R_L=4\Omega, P_O=150mW, f=1kHz$          | -    | 0.25 | -       | %          |
| Voltage Gain                   | $A_V$        | f=1kHz                                            | 41   | 44   | 47      | dB         |
| Channel Balance                | $\Delta A_V$ |                                                   | -    | -    | $\pm 1$ | dB         |
| Input Impedance                | $Z_{IN}$     | f=1kHz                                            | 100  | -    | -       | k $\Omega$ |
| Equivalent Input Noise Voltage | $V_{NI1}$    | $R_S=10k\Omega, A$ Curve                          | -    | 2.5  | -       | $\mu V$    |
|                                | $V_{NI2}$    | $R_S=10k\Omega, B=22Hz\sim 22kHz$                 | -    | 3    | -       | $\mu V$    |
| Ripple Rejection               | RR           | f=100Hz, $C_X=100\mu F$                           | 24   | 30   | -       | dB         |
| Cutoff Frequency               | $f_H$        | $A_V=-3dB$ from f=1kHz, $R_L=16\Omega, P_O=125mW$ | -    | 200  | -       | kHz        |

( Note ) At on PC Board


## ■ TYPICAL APPLICATION & TEST CIRCUIT

Fig.1 BTL Configuration



note: pin No. to D,M-Type


Fig.2 Stereo Configuration



## ■ PARASTIC OSCILLATION PREVENTING CIRCUIT

Put  $1\Omega + 0.22\mu\text{F}$  on parallel to load, if the load is speaker. Recommend putting  $0.1\mu\text{F}$  and more than  $100\mu\text{F}$  capacitors with good high frequency characteristics in to near ground and supply voltage pins.

In BTL operation of less than 2V supply voltage, parastic oscillation may be occurred with  $R=1\Omega$ . And so recommended R to be the same value of pure resistance(r) when it is lower than 3V.



## ■ MUTING CIRCUIT

When Mute ON, OUTPUT level saturates to GND side.

Fig.3 BTL Configuration





Fig.4 Stereo Configuration




## ■ VOLTAGE GAIN REDUCTION APPLICATION EXAMPLE

### (1) Outline of way to further Reduction

NJM2073 by taking in assumption, as one of OP-AMP ( Gain 44dB, minus input impedance about  $300\Omega$  ), to feedback from output to minus input helps to get reduction of stabilized Voltage Gain. Fig.5 indicates the model example.

Here is the point to be noticed that, in order to get the appropriate output Bias Voltage, it is important to keep the minus input floating as DC condition, (inserting  $C_X$ ), and also that when extended too much reduction of Gain might cause Oscillation due to high band phase margin. The reduction of voltage gain is limited at around 26dB (20 times), and when oscillation, it is necessary to attach the oscillation stopper. Please examine the  $C_X$  value accordingly to the application requirement.

Fig.5 Model of Voltage Gain Reduction



$$A_v = \frac{v_0}{v_{in}} \cong \frac{R_s + R_f}{R_s + \frac{R_s + R_f}{A_v} + \frac{R_s \times R_f}{160 \times 300}} \approx \frac{R_s + R_f}{R_s + \frac{R_s + R_f}{A_v} + \frac{R_s \times R_f}{160 \times 300}}$$

## (2) The Application Example of Voltage Gain Reduction. ( STEREO )

Fig.6 indicates the application example and Table1 indicates the recommendable value of parts to be attached externally.

Table1,Applying purpose and Recommended Value of Externally parts to be attached.

| EXTERNAL PARTS | APPLICATION PURPOSE                    | RECOMMENDED VALUE                         | REMARKS                                                                                                                                                                                               |
|----------------|----------------------------------------|-------------------------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| $R_g$          | Plus input to be grounded by fixed DC  | Under about 100k $\Omega$                 | Catch the noise when much higher.                                                                                                                                                                     |
| $R_s$          | AV shall be decided with $R_f$         | -                                         |                                                                                                                                                                                                       |
| $R_f$          | AV shall be decided with $R_s$         | About 5k $\Omega$                         | The co-temperature of AV becomes higher in case when $R_s$ is higher resistance.The current from output pin to GND becomes higher,in case when $R_s$ is lower resistance.(The current sinks in vain.) |
| $C_x$          | Minus input to be grounded by fixed DC | -                                         | Low-band Cut off frequency (fL) is to be decided. The rise time becomes longer in case that $C_x$ is big.                                                                                             |
| $C_{CUP}$      | Output DC Decoupling                   | When $R_L=8\Omega$ ,More than 220 $\mu$ F | fL shall be decided by $C_{CUP}$ and $Z_L$ .                                                                                                                                                          |
| $C_{P1}$       | Stabilization of $V^+$                 | More than about $C_{CUP}$                 | Inserting near around $V^+$ pin and GND pin.                                                                                                                                                          |
| $C_{P2}$       | Prevention of Oscillation              | More than 0.1 $\mu$ F                     |                                                                                                                                                                                                       |
| $r$            | Prevention of Oscillation              | About $R_L$                               | Inserting near around $V^+$ pin and GND pin.                                                                                                                                                          |
| $C$            | Prevention of Oscillation              | 0.22 $\mu$ F                              | To be examined by about the resistor volume of the speaker load.                                                                                                                                      |

Fig.6 STEREO Application Example.










Fig.7 indicates the application example, Table2 shows recommended value of externally attaching parts.

|          |  |             |  |
|----------|--|-------------|--|
| EXTERNAL |  | RECOMMENDED |  |
|----------|--|-------------|--|


## ■ TYPICAL CHARACTERISTICS



## ■ TYPICAL CHARACTERISTICS


**Total Harmonic Distortion (BTL)**

( $V^+ = 6V$ ,  $R_L = 8\Omega$ )




**Total Harmonic Distortion (Stereo)**

( $V^+ = 6V$ ,  $R_L = 4\Omega$ )




**Power Dissipation vs. Output Power (BTL)**

( $R_L = 4\Omega$ ,  $f = 1kHz$ ,  $T_a = 25^\circ C$ )




**Power Dissipation vs. Output Power (BTL)**

( $R_L = 8\Omega$ ,  $f = 1kHz$ ,  $T_a = 25^\circ C$ )




**Power Dissipation vs. Output Power (BTL)**

( $R_L = 16\Omega$ ,  $f = 1kHz$ ,  $T_a = 25^\circ C$ )







**Power Dissipation vs. Output Power (BTL)**




( $R_L = 32\Omega$ ,  $f = 1kHz$ )



## ■ TYPICAL CHARACTERISTICS



## ■ TYPICAL CHARACTERISTICS



**[CAUTION]**

The specifications on this databook are only given for information, without any guarantee as regards either mistakes or omissions. The application circuits in this databook are described only to show representative usages of the product and not intended for the guarantee or permission of any right including the industrial rights.