## The RF Line NPN Silicon RF Power Transistor

The TP3032 is designed for 26 volts, common emitter, 960 MHz base station amplifiers, for use in analog and digital systems.

- Specified 26 Volts, 960 MHz Characteristics Output Power — 21 Watts Gain — 7.5 dB min
- Silicon Nitride Passivated
- Gold Metallized, Emitter Ballasted for Long Life and Resistance to Metal Migration
- Class AB Operation

MAXIMUM RATINGS

• Circuit board photomaster available upon request by contacting RF Tactical Marketing in Phoenix, AZ.

		-	
Rating	Symbol	Value	Unit
Collector-Emitter Voltage	VCER	40	Vdc
Collector-Base Voltage	VCBO	48	Vdc
Emitter-Base Voltage	VEBO	3.5	Vdc
Collector-Current - Continuous	ιc	4	Adc
Total Device Dissipation @ T <sub>C</sub> = 25°C Derate above 25°C	PD	52.5 0.3	Watts W/°C
Storage Temperature Range	T <sub>stg</sub>	– 65 to +150	°C
Operating Junction Temperature	Тј	200	°C



**TP3032** 

21 W, 960 MHz RF POWER TRANSISTOR

NPN SILICON

CASE 319-07, STYLE 2

## THERMAL CHARACTERISTICS

Characteristic	Symbol	Мах	Unit
Thermal Resistance, Junction to Case (1)		3.3	°C/W

**ELECTRICAL CHARACTERISTICS** (T<sub>C</sub> = 25°C unless otherwise noted.)

Characteristic	Symbol	Min	Тур	Max	Unit
OFF CHARACTERISTICS					
Collector–Emitter Breakdown Voltage $(I_C = 30 \text{ mA}, R_{BE} = 75 \Omega)$	V(BR)CER	40	—	—	Vdc
Emitter-Base Breakdown Voltage (IE = 5 mAdc)	V(BR)EBO	3.5	_	—	Vdc
Collector–Base Breakdown Voltage (I <sub>C</sub> = 30 mAdc)	V(BR)CBO	48	—	—	Vdc
Collector–Emitter Leakage ( $V_{CE} = 26 \text{ V}, \text{ R}_{BE} = 75 \Omega$ )	ICER	_	_	8	mA
ON CHARACTERISTICS					
DC Current Gain (I <sub>C</sub> =1 Adc, V <sub>CE</sub> = 10 Vdc)	hFE	15	_	80	_

NOTE:

1. Thermal resistance is determined under specified RF operating condition.



(continued)

## **ELECTRICAL CHARACTERISTICS** — continued ( $T_C = 25^{\circ}C$ unless otherwise noted.)

Characteristic	Symbol	Min	Тур	Max	Unit
DYNAMIC CHARACTERISTICS					
Output Capacitance ( $V_{CB} = 26 \text{ V}, I_E = 0, f = 1 \text{ MHz}$ )	C <sub>ob</sub>	_	30	—	pF
FUNCTIONAL TESTS					
Common–Emitter Amplifier Gain (V <sub>CC</sub> = 26 V, P <sub>out</sub> = 21 W, I <sub>CQ</sub> = 100 mA, f = 960 MHz)	Gp	7.5	8.5	-	dB
Load Mismatch $(V_{CC} = 26 \text{ V}, P_{out} = 21 \text{ W}, I_{CQ} = 100 \text{ mA}, \text{ Load VSWR} = 5:1, at All Phase Angles at Frequency of Test}$	Ψ	No Degradation in Output Power			
Collector Efficiency (V <sub>CC</sub> = 26 V, P <sub>out</sub> = 21 W, f = 960 MHz)	η	50	55	_	%
Over Drive (V <sub>CC</sub> = 26 V, P <sub>in</sub> = 6 W, f = 960 MHz)	OD	No Degradation in Output Power			



	VCE = 26 V	$P_{out} = 21 \text{ VV}$
f (MHz)	<b>Z<sub>in</sub></b> (Ω)	Z <sub>OL</sub> * (Ω)
860	2.9 – j0.4	2 + j2.2
880	2.9 – j0.9	2.1 + j2.2
900	2.9 – j1.45	2.25 + j2.5
935	3.2 – j0.95	2.4 + j2.3
960	3.25 – j1.5	2.5 + j2
980	3.55 – j1.1	2.6 + j2.15

Z<sub>OL</sub>\* = Conjugate of optimum load impedance into which the device operates at a given output power, voltage, current and frequency.

Figure 1. Series Equivalent Input and Output Impedances







Pout, , OUTPUT POWER (WATTS)



Figure 6. Test Circuit Components View



PACKAGE DIMENSIONS

Motorola reserves the right to make changes without further notice to any products herein. Motorola makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Motorola assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation consequential or incidental damages. "Typical" parameters can and do vary in different applications. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. Motorola does not convey any license under its patent rights nor the rights of others. Motorola products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the Motorola product could create a situation where personal injury or death may occur. Should Buyer purchase or use Motorola products for any such unintended or unauthorized application, Buyer shall indemnify and hold Motorola and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death Motorola was negligent regarding the design or manufacture of the part. Motorola and with such unintended or unauthorized use, even if such claim alleges that Motorola was negligent regarding the design or manufacture of the part. Motorola and with such unintended or unauthorized use, local is claim alleges that Motorola was negligent regarding the design or manufacture of the part.

## Literature Distribution Centers:

USA: Motorola Literature Distribution; P.O. Box 20912; Phoenix, Arizona 85036.

EUROPE: Motorola Ltd.; European Literature Centre; 88 Tanners Drive, Blakelands, Milton Keynes, MK14 5BP, England.

JAPAN: Nippon Motorola Ltd.; 4-32-1, Nishi-Gotanda, Shinagawa-ku, Tokyo 141, Japan.

٥

ASIA PACIFIC: Motorola Semiconductors H.K. Ltd.; Silicon Harbour Center, No. 2 Dai King Street, Tai Po Industrial Estate, Tai Po, N.T., Hong Kong.



