


40A GLASS PASSIVATED AVALANCHE BUTTON DIODE

Features

- Glass Passivated Die Construction
- High Power Capacity
- Avalanche Voltage 24 to 32 Volts
- High Surge Current Capability
- Low Cost Construction Utilizing Void-Free Molded Plastic Technique

Mechanical Data

- Case: Molded Plastic
- Terminals: Plated Terminals Solderable per MIL-STD-202, Method 208
- Polarity:Color Ring Denotes Cathode End
- Weight: 1.8 grams (approx.)Mounting Position: Any



	AR		ARS			
Dim	Min	Max	Min	Max		
Α	10.03	10.29	8.31	8.81		
В	5.54	5.64	5.54	5.64		
С	5.94	6.25	5.94	6.25		
D	4.19	4.45	4.19	4.45		
All Dimensions in mm						

S Suffix Designates ARS Package No Suffix Designates AR Package

Maximum Ratings and Electrical Characteristics @TA=25°C unless otherwise specified

Single Phase, half wave, 60Hz, resistive or inductive load. For capacitive load, derate current by 20%.

Characteristic	Symbol	AR/S2540	Unit	
Peak Repetitive Reverse Voltage Working Peak Reverse Voltage DC Blocking Voltage		VRRM VRWM VR	20	V
Average Rectified Output Current	@T _A = 150°C	lo	40	Α
Breakdown Voltage Min. Breakdwon Voltage Max.	$@I_R = 100mA$ $@I_R = 100mA$	VBR	24 32	>
Non-Repetitive Peak Forward Surge Current 8.3ms Single half sine-wave superimposed on rated load (JEDEC Method) @T _J = 150°C		IFSM	600	А
Peak Reverse Surge Current		IRSM	150	Α
Forward Voltage	@I _F = 100A	VFM	1.05	V
Peak Reverse Current at Rated DC Blocking Voltage @T _C = 25		IRM	200	nA
Typical Thermal Resistance Junction to Case (Note 1)	R ⊕ JC	0.8	K/W	
Operating and Storage Temperature Range	ТJ, Tsтg	-50 to +175	°C	

Note: 1. Thermal Resistance: Junction to case, single side cooled.

ORDERING INFORMATION

Product No.	Package Type	Shipping Quantity	
AR2540	10mm Button	1000 Units/Box	
ARS2540	8.6mm Button	1000 Units/Box	

Shipping quantity given is for minimum packing quantity only. For minimum order quantity, please consult the Sales Department.

Won-Top Electronics Co., Ltd (WTE) has checked all information carefully and believes it to be correct and accurate. However, WTE cannot assume any responsibility for inaccuracies. Furthermore, this information does not give the purchaser of semiconductor devices any license under patent rights to manufacturer. WTE reserves the right to change any or all information herein without further notice.

WARNING: DO NOT USE IN LIFE SUPPORT EQUIPMENT. WTE power semiconductor products are not authorized for use as critical components in life support devices or systems without the express written approval.

Won-Top Electronics Co., Ltd.

No. 44 Yu Kang North 3rd Road, Chine Chen Dist., Kaohsiung, Taiwan

Phone: 886-7-822-5408 or 886-7-822-5410

Fax: 886-7-822-5417 Email: sales@wontop.com Internet: http://www.wontop.com

We power your everyday.