

## **Contents**

Features .....	1
Pin Assignment .....	1
Block Diagram .....	2
Operation Mode .....	2
Absolute Maximum Ratings .....	2
Recommended Operating Conditions ...	2
DC Electrical Characteristics .....	3
Rewriting Times .....	3
Pin Capacitance .....	3
AC Electrical Characteristics .....	4
Operation .....	8
Dimensions .....	9
Ordering Information .....	10
Characteristics .....	11

The S-2860B and the S-2864B are low power 8K×8-bit parallel E<sup>2</sup>PROMs. The S-2860B features wide operating voltage range, and the S-2864B features 5-V single power supply. Since provided with 32-byte page write function, they can perform fast programming operation.

## ■ Features

- Access time: 150 ns  
(V<sub>CC</sub> = 5 V ± 10%, Ta = 0°C to 70°C)
- Low power consumption  
Operating: 30 mA max. (V<sub>CC</sub> = 5 V ± 10%)  
Standby: 1 μA max. (V<sub>CC</sub> = 5 V ± 10%)
- Operating voltage range
 

<u>S-2860B</u>	<u>S-2864B</u>
Read: 1.8 to 5.5 V	5 V ± 10%
Write: 2.7 to 5.5 V	5 V ± 10%
- Write inhibition  
S-2860B: 2.1 V typ.  
S-2864B: 3.5 V typ.
- Data polling
- Page write for 32 bytes
- Rewritings : 10<sup>5</sup> times
- Data retention: 10 years
- Program noise immunity
- Package: 28-pin SOP/TSOP
- Supply in bare chip is also available

## ■ Pin Assignment




Figure 1

# CMOS 64K-bit PARALLEL E<sup>2</sup>PROM S-2860B/2864B

## ■ Block Diagram




Figure 2

## ■ Operation Mode

Table 1

Mode	$\overline{CE}$	$\overline{OE}$	$\overline{WE}$	I/O
Read	L	L	H	Data output
Write	L	H	L	Data input
Write inhibition	x	x	H	—
	x	L	x	—
Standby	H	x	x	High-Z

X : Don't care

## ■ Absolute Maximum Ratings

Table 2

Parameter	Symbol	Ratings	Unit
Power supply voltage	$V_{CC}$	-0.3 to +7.0	V
Input voltage	$V_{IN}$	-0.3 to $V_{CC} + 0.3$	V
Output voltage	$V_{OUT}$	-0.3 to $V_{CC}$	V
Storage temperature under bias	$T_{bias}$	-50 to +95	°C
Storage temperature	$T_{stg}$	-65 to +150	°C

## ■ Recommended Operating Conditions

Table 3

Parameter	Symbol	Conditions		Min.	Typ.	Max.	Unit
Power supply voltage	$V_{CC}$	S-2860B	Read	1.8	—	5.5	V
		S-2860B	Write	2.7	—	5.5	V
		S-2864B		4.5	5.0	5.5	V
High level input voltage	$V_{IH}$	$V_{CC} = 2.7$ to $5.5$ V		2.2	—	$V_{CC} + 0.3$	V
		$V_{CC} = 1.8$ to $2.7$ V		$0.8 \times V_{CC}$	—	$V_{CC} + 0.3$	V
Low level input voltage	$V_{IL}$	$V_{CC} = 4.5$ to $5.5$ V		-0.3	—	0.8	V
		$V_{CC} = 2.7$ to $4.5$ V		-0.3	—	0.4	V
		$V_{CC} = 1.8$ to $2.7$ V		-0.3	—	$0.2 \times V_{CC}$	V
Operating temperature	$T_{opr}$			-40	—	85	°C

## ■ DC Electrical Characteristics

### 1. S-2860B

Table 4

(Ta = -40°C to 85°C)

Parameter	Symbol	Conditions	5 V ± 10%			3 V ± 10%			Unit
			Min.	Typ.	Max.	Min.	Typ.	Max.	
Current consumption (Read)	I <sub>CC1</sub>	CE ≤ V <sub>IL</sub> , V <sub>IN</sub> ≤ V <sub>IL</sub> or V <sub>IN</sub> ≥ V <sub>IH</sub> I <sub>OUT</sub> = 0 mA, f = 1/t <sub>RC</sub>	—	—	30	—	—	15	mA
	I <sub>CC2</sub>	CE ≤ 0.2 V, V <sub>IN</sub> ≤ 0.2 V or V <sub>IN</sub> ≥ V <sub>CC</sub> - 0.2 V I <sub>OUT</sub> = 0 mA, f = 1/t <sub>RC</sub>	—	—	25	—	—	10	mA
Current consumption (Program)	I <sub>CC3</sub>	CE ≤ V <sub>IL</sub> , V <sub>IN</sub> ≤ V <sub>IL</sub> or V <sub>IN</sub> ≥ V <sub>IH</sub>	—	—	30	—	—	15	mA
	I <sub>CC4</sub>	CE ≤ 0.2 V, V <sub>IN</sub> ≤ 0.2 V or V <sub>IN</sub> ≥ V <sub>CC</sub> - 0.2 V	—	—	25	—	—	10	mA
Standby current	I <sub>SB1</sub>	CE ≥ V <sub>IH</sub>	—	—	1	—	—	0.5	mA
	I <sub>SB2</sub>	CE ≥ V <sub>CC</sub> - 0.2 V	—	—	1.0	—	—	1.0	μA
Input leakage current	I <sub>LI</sub>	V <sub>IN</sub> = GND to V <sub>CC</sub>	—	—	1.0	—	—	1.0	μA
Output leakage current	I <sub>LO</sub>	V <sub>I/O</sub> = GND to V <sub>CC</sub>	—	—	1.0	—	—	1.0	μA
High level output voltage	V <sub>OH</sub>	5-V operation: I <sub>OH</sub> = -400 μA 3-V operation: I <sub>OH</sub> = -100 μA	2.4	—	—	2.4	—	—	V
Low level output voltage	V <sub>OL</sub>	5-V operation: I <sub>OL</sub> = 2.1 mA 3-V operation: I <sub>OL</sub> = 400 μA	—	—	0.4	—	—	0.4	V

### 2. S-2864B

Table 5

(Ta = -40°C to 85°C, V<sub>CC</sub> = 5 V ± 10%)

Parameter	Symbol	Conditions	Min.	Typ.	Max.	Unit
Current consumption (Read)	I <sub>CC1</sub>	CE ≤ V <sub>IL</sub> , V <sub>IN</sub> ≤ V <sub>IL</sub> or V <sub>IN</sub> ≥ V <sub>IH</sub> I <sub>OUT</sub> = 0 mA, f = 1/t <sub>RC</sub>	—	—	30	mA
	I <sub>CC2</sub>	CE ≤ 0.2 V, V <sub>IN</sub> ≤ 0.2 V or V <sub>IN</sub> ≥ V <sub>CC</sub> - 0.2 V I <sub>OUT</sub> = 0 mA, f = 1/t <sub>RC</sub>	—	—	25	mA
Current consumption (Program)	I <sub>CC3</sub>	CE ≤ V <sub>IL</sub> , V <sub>IN</sub> ≤ V <sub>IL</sub> or V <sub>IN</sub> ≥ V <sub>IH</sub>	—	—	30	mA
	I <sub>CC4</sub>	CE ≤ 0.2 V, V <sub>IN</sub> ≤ 0.2 V or V <sub>IN</sub> ≥ V <sub>CC</sub> - 0.2 V	—	—	25	mA
Standby current	I <sub>SB1</sub>	CE ≥ V <sub>IH</sub>	—	—	1	mA
	I <sub>SB2</sub>	CE ≥ V <sub>CC</sub> - 0.2 V	—	—	1.0	μA
Input leakage current	I <sub>LI</sub>	V <sub>IN</sub> = GND to V <sub>CC</sub>	—	—	1.0	μA
Output leakage current	I <sub>LO</sub>	V <sub>I/O</sub> = GND to V <sub>CC</sub>	—	—	1.0	μA
High level output voltage	V <sub>OH</sub>	I <sub>OH</sub> = -400 μA	2.4	—	—	V
Low level output voltage	V <sub>OL</sub>	I <sub>OL</sub> = 2.1 mA	—	—	0.4	V

## ■ Rewriting Times

Table 6

Parameter	Symbol	Min.	Typ.	Max.	Unit
Rewriting times	N <sub>W</sub>	10 <sup>5</sup>	—	—	times/byte

## ■ Pin Capacitance

Table 7


Parameter	Symbol	Conditions	Min.	Typ.	Max.	Unit
Input capacitance	C <sub>IN</sub>	V <sub>IN</sub> = 0 V	—	—	10	pF
Input / output capacitance	C <sub>I/O</sub>	V <sub>I/O</sub> = 0 V	—	—	10	pF

# CMOS 64K-bit PARALLEL E<sup>2</sup>PROM S-2860B/2864B

## ■ AC Electrical Characteristics

**Table 8 Measuring conditions**

Parameter	S-2860B	S-2864B
Input pulse levels	$V_{IL} = 0.2\text{ V}$ $V_{IH} = 2.4\text{ V}$	$V_{IL} = 0.4\text{ V}$ $V_{IH} = 2.4\text{ V}$
Input rise and fall time	10 ns	10 ns
I/O reference level	1.5 V	1.5 V
Output load	See Figure 3	See Figure 3



\* (When measuring  $t_{CLZ}$ ,  $t_{OLZ}$ ,  $t_{CHZ}$ ,  $t_{OHZ}$ ,  $t_{WHZ}$ ,  $t_{WLZ}$ ) : 5pF

**Figure 3 Output load measuring circuit**

### 1. Read Cycle

#### (1) 5-V operation

**Table 9**

( $V_{CC} = 5\text{ V} \pm 10\%$ )

Parameter	Symbol	0°C to 70°C		-40°C to 85°C		Unit
		Min.	Max.	Min.	Max.	
Read cycle time	$t_{RC}$	150	—	200	—	ns
$\overline{CE}$ access time	$t_{CE}$	—	150	—	200	ns
Address access time	$t_{AA}$	—	150	—	200	ns
$\overline{OE}$ access time	$t_{OE}$	—	70	—	90	ns
Output enable time ( $\overline{CE}$ )	$t_{CLZ}$	10	—	10	—	ns
Output enable time ( $\overline{OE}$ )	$t_{OLZ}$	10	—	10	—	ns
Output disable time ( $\overline{CE}$ )	$t_{CHZ}$	10	70	10	90	ns
Output disable time ( $\overline{OE}$ )	$t_{OHZ}$	10	70	10	90	ns
Output data hold time	$t_{OH}$	5	—	5	—	ns

#### (2) 3-V operation (S-2860B only)

**Table 10**

( $V_{CC} = 3\text{ V} \pm 10\%$ )

Parameter	Symbol	0°C to 70°C		-40°C to 85°C		Unit
		Min.	Max.	Min.	Max.	
Read cycle time	$t_{RC}$	400	—	500	—	ns
$\overline{CE}$ access time	$t_{CE}$	—	400	—	500	ns
Address access time	$t_{AA}$	—	400	—	500	ns
$\overline{OE}$ access time	$t_{OE}$	—	200	—	250	ns
Output enable time ( $\overline{CE}$ )	$t_{CLZ}$	25	—	30	—	ns
Output enable time ( $\overline{OE}$ )	$t_{OLZ}$	25	—	30	—	ns
Output disable time ( $\overline{CE}$ )	$t_{CHZ}$	25	200	30	250	ns
Output disable time ( $\overline{OE}$ )	$t_{OHZ}$	25	200	30	250	ns
Output data hold time	$t_{OH}$	10	—	15	—	ns

**2. Write Cycle**

**(1) 5-V operation**

**Table 11**

(V<sub>CC</sub> = 5 V ± 10%)


Parameter	Symbol	0°C to 70°C		- 40°C to 85°C		Unit
		Min.	Max.	Min.	Max.	
Write cycle time	t <sub>WC</sub>	—	10	—	10	ms
Address setup time	t <sub>AS</sub>	0	—	0	—	ns
Address hold time	t <sub>AH</sub>	120	—	150	—	ns
Write setup time	t <sub>CS</sub>	0	—	0	—	ns
Write hold time	t <sub>CH</sub>	0	—	0	—	ns
CE pulse width	t <sub>CW</sub>	120	—	150	—	ns
OE setup time	t <sub>OES</sub>	15	—	20	—	ns
OE hold time	t <sub>OEH</sub>	15	—	20	—	ns
WE pulse width	t <sub>WP</sub>	120	—	150	—	ns
Data setup time	t <sub>DS</sub>	85	—	100	—	ns
Data hold time	t <sub>DH</sub>	0	—	0	—	ns
Page load time (page data setting time)	t <sub>PL</sub>	0.3	30	0.3	30	μs
Page load time (page data write start time)	t <sub>PDL</sub>	100	—	100	—	μs

**(2) 3-V operation (S-2860B only)**


**Table 12**

(V<sub>CC</sub> = 3 V ± 10%)


Parameter	Symbol	0°C to 70°C		- 40°C to 85°C		Unit
		Min.	Max.	Min.	Max.	
Write cycle time	t <sub>WC</sub>	—	10	—	10	ms
Address setup time	t <sub>AS</sub>	0	—	0	—	ns
Address hold time	t <sub>AH</sub>	300	—	350	—	ns
Write setup time	t <sub>CS</sub>	0	—	0	—	ns
Write hold time	t <sub>CH</sub>	0	—	0	—	ns
CE pulse width	t <sub>CW</sub>	300	—	350	—	ns
OE setup time	t <sub>OES</sub>	30	—	35	—	ns
OE hold time	t <sub>OEH</sub>	30	—	35	—	ns
WE pulse width	t <sub>WP</sub>	300	—	350	—	ns
Data setup time	t <sub>DS</sub>	180	—	210	—	ns
Data hold time	t <sub>DH</sub>	0	—	0	—	ns
Page load time (page data setting time)	t <sub>PL</sub>	0.3	30	0.3	30	μs
Page load time (page data write start time)	t <sub>PDL</sub>	100	—	100	—	μs




**Figure 4** Read cycle



**Figure 5**  $\overline{WE}$  controlled write cycle



**Figure 6  $\overline{CE}$  controlled write cycle**



**Figure 7 Page write cycle**

## ■ Operation

### (1) Read mode

This mode outputs data to I/O<sub>0</sub> to I/O<sub>7</sub> when both  $\overline{CE}$  and  $\overline{OE}$  are low and when  $\overline{WE}$  is high. The data bus is high impedance when either  $\overline{CE}$  or  $\overline{OE}$  is high.

### (2) Byte write mode

A byte write cycle starts when both  $\overline{CE}$  and  $\overline{WE}$  are low and  $\overline{OE}$  is high.  $\overline{CE}$ -and  $\overline{WE}$ -controlled write cycles are available. The address is latched at the falling of  $CE$  or  $WE$  whichever occurs last, and the data is latched at the rising of  $\overline{CE}$  or  $WE$  whichever occurs first.

### (3) Page write mode

In this mode, 1 page program operation of 32 bytes is completed in 10 ms, and all memory area is written within 3 second because the device organization is 256-page  $\times$  32-byte. When starting this mode, first, addresses A<sub>5</sub> to A<sub>12</sub> assign the page, then A<sub>0</sub> to A<sub>4</sub> assign the address to each byte within the page sequentially or at random. Less than 32 bytes of program is available. This address assignment is performed while  $0.3 \mu s \leq t_{PL} \leq 30 \mu s$ , and the program operation starts when  $t_{PDL} \geq 100 \mu s$ .

### (4) Data polling

This function is to output the complement data written last on I/O<sub>7</sub> and to output low to I/O<sub>0</sub> to I/O<sub>6</sub>. This operation is performed by read operation during write cycle.

### (5) Erase all mode

All data is erased when  $\overline{OE}$  is 13 V and both  $\overline{CE}$  and  $\overline{WE}$  are low. During erase all mode, A<sub>0</sub> to A<sub>12</sub> and I/O<sub>0</sub> to I/O<sub>7</sub> must be fixed to either high or low.




Figure 8


### (6) Write inhibition

Write operation is inhibited in the following cases :

- When power supply voltage is under write inhibit voltage ( $V_{WI}$ ).
  - S-2864B :  $V_{WI} = 3.5$  V typ.
  - S-2860B :  $V_{WI} = 2.1$  V typ.
- When  $\overline{OE}$  is low, or  $\overline{WE}$  is high.

### (7) Program noise immunity


$\overline{CE}$ ,  $\overline{OE}$  and  $\overline{WE}$  are noise protected for preventing erroneous write operation of power on and off. Less than 20 ns write pulse will not activate a write cycle at 5-V operation, and less than 50 ns at 3-V operation. See Figure 9.



**Figure 9**

■ Dimensions (Unit : mm)

1. 28-pin SOP



**Figure 10**

2. 28-pin TSOP





Figure 11

■ Ordering Information




Note: Each bit is set to 1 before delivery (except bare chip)


## ■ Characteristics

### 1. DC characteristics


1.1 Current consumption (READ)  $I_{CC1}$  – Ambient temperature  $T_a$




1.2 Current consumption (READ)  $I_{CC1}$  – Ambient temperature  $T_a$




1.3 Current consumption (READ)  $I_{CC1}$  – Power supply voltage  $V_{CC}$




1.4 Current consumption (READ)  $I_{CC1}$  – Read cycle time  $t_{RC}$




1.5 Current consumption (READ)  $I_{CC2}$  – Ambient temperature  $T_a$




1.6 Current consumption (READ)  $I_{CC2}$  – Ambient temperature  $T_a$




1.7 Current consumption (READ)  $I_{CC2}$  – Power supply voltage  $V_{CC}$




1.8 Current consumption (READ)  $I_{CC2}$  – Read cycle time  $t_{RC}$




1.9 Current consumption (PROGRAM)  $I_{CC3}$  –  
 Ambient temperature  $T_a$




1.10 Current consumption (PROGRAM)  $I_{CC3}$  –  
 Ambient temperature  $T_a$




1.11 Current consumption (PROGRAM)  $I_{CC3}$  –  
 Power Supply Voltage  $V_{CC}$




1.12 Current consumption (PROGRAM)  $I_{CC3}$  –  
 Ambient temperature  $T_a$




1.13 Current consumption (PROGRAM)  $I_{CC4}$  –  
 Ambient temperature  $T_a$




1.14 Current consumption (PROGRAM)  $I_{CC4}$  –  
 Ambient temperature  $T_a$




1.15 Current consumption (PROGRAM)  $I_{CC4}$  –  
 Power Supply Voltage  $V_{CC}$




1.16 Current consumption (PROGRAM)  $I_{CC4}$  –  
 Ambient temperature  $T_a$




1.17 Standby current  $I_{SB1}$  –  
Ambient temperature  $T_a$




1.18 Standby current  $I_{SB1}$  –  
Ambient temperature  $T_a$




1.19 Standby current  $I_{SB2}$  –  
Ambient temperature  $T_a$




1.20 Standby current  $I_{SB2}$  –  
Ambient temperature  $T_a$




1.21 Input leakage current  $I_{LI}$  –  
Ambient temperature  $T_a$




1.22 Input leakage current  $I_{LI}$  –  
Ambient temperature  $T_a$




1.23 Output leakage current  $I_{LO}$  –  
Ambient temperature  $T_a$




1.24 Output leakage current  $I_{LO}$  –  
Ambient temperature  $T_a$




1.25 High level output voltage  $V_{OH}$  –  
 Ambient temperature  $T_a$




1.26 High level output voltage  $V_{OH}$  –  
 Ambient temperature  $T_a$




1.27 Low level output voltage  $V_{OL}$  –  
 Ambient temperature  $T_a$




1.28 Low level output voltage  $V_{OL}$  –  
 Ambient temperature  $T_a$




1.29 High level input voltage  $V_{IH}$  –  
 Ambient temperature  $T_a$



1.30 Low level input voltage  $V_{IL}$  –  
 Ambient temperature  $T_a$




1.31 Low level input voltage  $V_{IL}$  –  
 Ambient temperature  $T_a$




## 2. AC characteristics


2.1 Write cycle time  $t_{WC}$  – Ambient temperature  $T_a$




2.2 Write cycle time  $t_{WC}$  – Ambient temperature  $T_a$




2.3 Write cycle time  $t_{WC}$  – Power supply voltage  $V_{CC}$




2.4 Address access time  $t_{AA}$  – Ambient temperature  $T_a$




2.5 Address access time  $t_{AA}$  – Ambient temperature  $T_a$










2.6  $\overline{CE}$  access time  $t_{CE}$  – Ambient temperature  $T_a$



2.7  $\overline{CE}$  access time  $t_{CE}$  – Ambient temperature  $T_a$





2.15 Data hold time  $t_{DH}$  –  
Ambient temperature  $T_a$

