

Surface Mount High Output Infrared LEDs

Absolute maximum ratings ($T_a=25^{\circ}\text{C}$)

Parameter	Symbol	Limits	Unit
Forward current	I_F	100	mA
Reverse voltage	V_R	5	V
Power dissipation	P_D	180	mW
Operating temperature	T_{opr}	$-25 \sim +85$	$^{\circ}\text{C}$
Storage temperature	T_{stg}	$-40 \sim +85$	$^{\circ}\text{C}$

Applications

Light source for sensors
(proximity sensors,
signal transmission applications)

Features

- 1) Higt compact, low-profile
- 2) Higt output, over a narrow angle
- 3) Exellent temperature property
- 4) Long life,high reliability
- 5) Original optical tecnology is ultra-high-output surface mount infrared LEDs.

Electrical and optical characteristics ($T_a=25^{\circ}\text{C}$)

Parameter	Symbol	Min.	Typ.	Max.	Unit	Conditions
Forward voltage	V_F	—	1.7	2.5	V	$I_F=100\text{mA}$
Reverse current	I_R	—	—	15	μA	$V_R=5\text{V}$
Peak light emitting wavelength	λ_{peak}	—	870	—	nm	$I_F=100\text{mA}$
View angle	$\theta_{1/2}$	—	± 20	—	deg.	—
Radiant intensity	I_E	10	—	100	mW/sr	$I_F=100\text{mA}$

* Non-coherent infrared light emitting diode used.

* This product is not designed to be protected against electromagnetic wave.

Electrical and optical characteristics curves




Fig.1 Forward current fall off




Fig.2 Forward current vs. Forward voltage




Fig.3 Radiant intensity vs. Forward current




Fig.4 Relative radiant vs. Ambient temperature




Fig.5 Spectrum data






Fig.6 Radiant intensity



Internal connection diagram



- Notes:
- 1. Unspecified tolerance shall be ± 0.15 .
 - 2. Dimension in parenthesis are show for reference.




Fig.7 Wavelength vs. Ambient temperature

Notes

No copying or reproduction of this document, in part or in whole, is permitted without the consent of ROHM Co.,Ltd.

The content specified herein is subject to change for improvement without notice.

The content specified herein is for the purpose of introducing ROHM's products (hereinafter "Products"). If you wish to use any such Product, please be sure to refer to the specifications, which can be obtained from ROHM upon request.

Examples of application circuits, circuit constants and any other information contained herein illustrate the standard usage and operations of the Products. The peripheral conditions must be taken into account when designing circuits for mass production.

Great care was taken in ensuring the accuracy of the information specified in this document. However, should you incur any damage arising from any inaccuracy or misprint of such information, ROHM shall bear no responsibility for such damage.

The technical information specified herein is intended only to show the typical functions of and examples of application circuits for the Products. ROHM does not grant you, explicitly or implicitly, any license to use or exercise intellectual property or other rights held by ROHM and other parties. ROHM shall bear no responsibility whatsoever for any dispute arising from the use of such technical information.

The Products specified in this document are intended to be used with general-use electronic equipment or devices (such as audio visual equipment, office-automation equipment, communication devices, electronic appliances and amusement devices).

The Products specified in this document are not designed to be radiation tolerant.

While ROHM always makes efforts to enhance the quality and reliability of its Products, a Product may fail or malfunction for a variety of reasons.

Please be sure to implement in your equipment using the Products safety measures to guard against the possibility of physical injury, fire or any other damage caused in the event of the failure of any Product, such as derating, redundancy, fire control and fail-safe designs. ROHM shall bear no responsibility whatsoever for your use of any Product outside of the prescribed scope or not in accordance with the instruction manual.

The Products are not designed or manufactured to be used with any equipment, device or system which requires an extremely high level of reliability the failure or malfunction of which may result in a direct threat to human life or create a risk of human injury (such as a medical instrument, transportation equipment, aerospace machinery, nuclear-reactor controller, fuel-controller or other safety device). ROHM shall bear no responsibility in any way for use of any of the Products for the above special purposes. If a Product is intended to be used for any such special purpose, please contact a ROHM sales representative before purchasing.

If you intend to export or ship overseas any Product or technology specified herein that may be controlled under the Foreign Exchange and the Foreign Trade Law, you will be required to obtain a license or permit under the Law.



Thank you for your accessing to ROHM product informations.
More detail product informations and catalogs are available, please contact us.

ROHM Customer Support System

<http://www.rohm.com/contact/>