



8.2 TABELA TENSÃO

Pino	Descrição	Valor (Vdc)	Pino	Descrição	Valor (Vdc)
1	IRFVO	1,08	33	VDDP 3,3	3,42
2	VP2	5,14	34	SDA	3,95
3	VCCAUDIO	8,23	35	SCL	3,40
4	PLLIF	2,00	36	RELAY	0,06
5	GND2	GND	37	AV/TV	ON 3,40 OFF 0,0
6	DECSDEM	2,28	38	STANDY BY	ON 3,40 OFF 0,0
7	FMDEMOUT	2,62	39	SYS	NC
8	EHTO	1,11	40	VDD	3,39
9	AGC	0,67	41	GND5	GND
10	IREF	1,93	42	VPE	0,03
11	VSC	2,45	43	VDDAI3,3	3,39
12	VIFIN2	1,90	44	BOUT	2,10
13	VIFIN1	1,90	45	GOUT	1,97
14	VDRA	0,82	46	ROUT	2,03
15	VDRB	0,81	47	BLKIN	3,39
16	AVL/EW	0	48	BLKIN	2,37
17	DECBG	2,30	49	PB	N.C
18	SECPLL	2,30	50	Y/Y3/CVBS3	N.C
19	GND1	GND	51	PR/C3	N.C
20	PH1LF	2,26	52	YOUT	1,62
21	PH2LF	2,12	53	YSYNC	1,70
22	VP1	5,18	54	VP3	5,13
23	DECDIG	2,52	55	GND3	GND
24	XTAL OUT	1,68	56	HOUT	0,37
25	XTAL IN	1,71	57	FBISO	0,40
26	IR	5,19	58	LSR	3,57
27	MUTE	3,38	59	LSL	3,56
28	TITLE	0,02	60	02/C3/C4/ALN5R/Cin	N.C
29	KEY	3,42	61	AIN3/IN1R/ARIN	2,20
30	BAND2	N.C	62	CVBS/Y2V1	1,41
31	BAND1	N.C	63	AIN2/A1NL/ALIN	2,20
32	TUNNIG	NC	64	CVBS4/Y4/AIN5L	1,41

descrição dos terminais e tensão